

© Copyright SEK Svensk Elstandard. Reproduction in any form without permission is prohibited.

REDLINE VERSION

Supraledning – Del 17: Mätning av elektroniska egenskaper – Lokal kritisk strömtäthet och dess fördelning i supraledande film med stor area

Superconductivity –

Part 17: Electronic characteristic measurements –

Local critical current density and its distribution in large-area superconducting films

En så kallad "Redline version" (RLV) innehåller både den fastställda IEC-standarden och en ändringsmarkerad standard. Alla tillägg och borttagningar sedan den tidigare utgåvan är markerade med färg. Med en RLV sparar du mycket tid när du ska identifiera och bedöma aktuella ändringar i standarden. SEK Svensk Elstandard kan bara ge ut en RLV i de fall den finns tillgänglig från IEC.



IEC 61788-17

Edition 2.0 2021-04
REDLINE VERSION

INTERNATIONAL STANDARD



**Superconductivity –
Part 17: Electronic characteristic measurements – Local critical current density
and its distribution in large-area superconducting films**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 17.220.20; 29.050

ISBN 978-2-8322-9765-0

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD.....	5
INTRODUCTION.....	2
1 Scope.....	9
2 Normative references	9
3 Terms and definitions	9
4 Requirements	10
5 Apparatus.....	11
5.1 Measurement equipment.....	11
5.2 Components for inductive measurements.....	12
6 Measurement procedure	13
6.1 General.....	13
6.2 Determination of the experimental coil coefficient	13
6.3 Measurement of J_C in sample films.....	18
6.4 Measurement of J_C with only one frequency	18
6.5 Examples of the theoretical and experimental coil coefficients	19
7 Uncertainty in the test method	20
7.1 Major sources of systematic effects that affect the U_3 measurement.....	20
7.2 Effect of deviation from the prescribed value in the coil-to-film distance	21
7.3 Uncertainty in the experimental coil coefficient and the obtained J_C	22
7.4 Effects of the film edge	23
7.5 Specimen protection	23
8 Test report.....	23
8.1 Identification of test specimen.....	23
8.2 Report of J_C values	23
8.3 Report of test conditions	23
Annex A (informative) Additional information relating to Clauses 1 to 8.....	24
A.1 Comments on other methods for measuring the local J_C of large-area HTS films.....	24
A.2 Requirements	24
A.3 Theory of the third-harmonic voltage generation	25
A.4 Calculation of the induced electric fields	26
A.5 Theoretical coil coefficient k and experimental coil coefficient k'	27
A.6 Scaling of the U_3 – I_0 curves and the constant-inductance criterion to determine I_{th}	27
A.7 Effects of reversible flux motion	29
Annex B (informative) Optional measurement systems.....	30
B.1 Overview.....	30
B.2 Harmonic noises arising from the power source and their reduction	31
Annex C (informative) Uncertainty considerations	40
Annex C (informative) Evaluation of the uncertainty	40
C.1 Evaluation of the uncertainty in the experimental coil coefficient	40
C.2 Uncertainty in the calculation of induced electric fields.....	41
C.3 Experimental results on the effect of the deviation of the coil-to-film distance	42

C.4	Examples of the Type-A uncertainties of J_C and n -values, originating from the experimental uncertainty in the U_3 measurement	42
C.5	Evaluation of the uncertainty in the obtained J_C	43
C.6	Experimental results that reveal the effect of the film edge	44
	Bibliography	46

Figure 1	– Diagram for an electric circuit used for inductive J_C measurement of HTS films	11
Figure 2	– Illustration showing techniques to press the sample coil to HTS films	12
Figure 3	– Example of a calibration wafer used to determine the coil coefficient	13
Figure 4	– Illustration of the sample coil and the magnetic field during measurement	15
Figure 5	– Illustration of the sample coil and its magnetic field generation	15
Figure 6	– Example of the normalized third-harmonic voltages (U_3/fI_0) measured with various frequencies	17
Figure 6	– E - J characteristics measured by a transport method and the U_3 inductive method	17
Figure 7	– Illustration of coils 1 and 3 in Table 2	20
Figure 8	– The coil-factor function $F(r) = 2H_0/I_0$ calculated for the three coils	20
Figure 9	– The coil-to-film distance Z_1 dependence of the theoretical coil coefficient k	22
Figure A.1	– Illustration of the sample coil and the magnetic field during measurement	26
Figure A.2	– U_3 and U_3/I_0 plotted against I_0 in a YBCO thin film measured in applied DC magnetic fields, and the scaling observed when normalized by I_{th} (insets)	28
Figure A.3	– Example of the normalized third-harmonic voltages (U_3/fI_0) measured with various frequencies	28
Figure B.1	– Schematic diagram for the variable- RL -cancel circuit	31
Figure B.2	– Diagram for an electrical circuit used for the two-coil method	31
Figure B.3	– Harmonic noises arising from the power source	32
Figure B.4	– Noise reduction using a cancel coil with a superconducting film	32
Figure B.5	– Normalized harmonic noises (U_3/fI_0) arising from the power source	33
Figure B.6	– Normalized noise voltages after the reduction using a cancel coil with a superconducting film	33
Figure B.7	– Normalized noise voltages after the reduction using a cancel coil without a superconducting film	34
Figure B.8	– Normalized noise voltages with the two-coil system shown in Figure B.2	34
Figure C.1	– Effect of the coil position against a superconducting thin film on the measured J_C values	45
Table 1	– Specifications and theoretical coil coefficients k of sample coils	16
Table 2	– Specifications and coil coefficients of typical sample coils	19
Table C.1	– Output signals from two nominally identical extensometers	46
Table C.2	– Mean values of two output signals	46
Table C.3	– Experimental standard deviations of two output signals	46
Table C.4	– Standard uncertainties of two output signals	46
Table C.5	– Coefficient of variations of two output signals	46

Table C.1 – Uncertainty budget table for the experimental coil coefficient k' 41
Table C.2 – Examples of repeated measurements of J_C and n -values43

INTERNATIONAL ELECTROTECHNICAL COMMISSION

SUPERCONDUCTIVITY –

**Part 17: Electronic characteristic measurements –
Local critical current density and its distribution
in large-area superconducting films**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

This redline version of the official IEC Standard allows the user to identify the changes made to the previous edition IEC 61788-17:2013. A vertical bar appears in the margin wherever a change has been made. Additions are in green text, deletions are in strikethrough red text.

IEC 61788-17 has been prepared by IEC technical committee 90: Superconductivity. It is an International Standard.

This second edition cancels and replaces the first edition published in 2013. This edition constitutes a technical revision.

This edition includes the following a significant technical change with respect to the previous edition:

- a) A simple method to calculate theoretical coil coefficient k is described in 6.2.1.

The text of this International Standard is based on the following documents:

FDIS	Report on voting
90/462/FDIS	90/464/RVD

Full information on the voting for the approval of this International Standard can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

A list of all the parts of the IEC 61788 series, published under the general title *Superconductivity*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

Over thirty years after their discovery in 1986, high-temperature superconductors are now finding their way into products and technologies that will revolutionize information transmission, transportation, and energy. Among them, high-temperature superconducting (HTS) microwave filters, which exploit the extremely low surface resistance of superconductors, have already been commercialized. They have two major advantages over conventional non-superconducting filters, namely: low insertion loss (low noise characteristics) and high frequency selectivity (sharp cut) [1]¹. These advantages enable a reduced number of base stations, improved speech quality, more efficient use of frequency bandwidths, and reduced unnecessary radio wave noise.

Large-area superconducting thin films have been developed for use in microwave devices [2]. They are also ~~used~~ considered for use in emerging superconducting power devices, such as resistive-type superconducting fault-current limiters (SFCLs) [3] [4] [5], superconducting fault detectors used for superconductor-triggered fault current limiters [6] [7] and persistent-current switches used for persistent-current HTS magnets [8] [9]. The critical current density J_c is one of the key parameters that describe the quality of large-area HTS films. Nondestructive, AC inductive methods are widely used to measure J_c and its distribution for large-area HTS films [10] [11] [12] [13], among which the method utilizing third-harmonic voltages $U_3 \cos(3\omega t + \theta)$ is the most popular [10] [11], where ω , t and θ denote the angular frequency, time, and initial phase, respectively. However, these conventional methods are not accurate because they have not considered the electric-field E criterion of the J_c measurement [14] [15] and sometimes use an inappropriate criterion to determine the threshold current I_{th} from which J_c is calculated [16]. A conventional method can obtain J_c values that differ from the accurate values by 10 % to 20 % [15]. It is thus ~~necessary~~ important to establish standard test methods to precisely measure the local critical current density and its distribution, to which all involved in the HTS filter industry can refer for quality control of the HTS films. Background knowledge on the inductive J_c measurements of HTS thin films is summarized in Annex A.

In these inductive methods, AC magnetic fields are generated with AC currents $I_0 \cos \omega t$ in a small coil mounted just above the film, and J_c is calculated from the threshold coil current I_{th} , at which full penetration of the magnetic field to the film is achieved [17]. For the inductive method using third-harmonic voltages U_3 , U_3 is measured as a function of I_0 , and the I_{th} is determined as the coil current I_0 at which U_3 starts to emerge. The induced electric fields E in the superconducting film at $I_0 = I_{th}$, which are proportional to the frequency f of the AC current, can be estimated by a simple Bean model [14]. A standard method has been proposed to precisely measure J_c with an electric-field criterion by detecting U_3 and obtaining the n -value (index of the power-law E - J characteristics) by measuring I_{th} precisely at various frequencies [14] [15] [18] [19]. This method not only obtains precise J_c values, but also facilitates the detection of degraded parts in inhomogeneous specimens, because the decline of n -value is more ~~remarkable~~ noticeable than the decrease of J_c in such parts [15]. It is noted that this standard method is excellent for assessing homogeneity in large-area HTS films, although the relevant parameter for designing microwave devices is not J_c , but the surface resistance. For application of large-area superconducting thin films to SFCLs, knowledge on J_c distribution is vital, because J_c distribution significantly affects quench distribution in SFCLs during faults.

The International Electrotechnical Commission (IEC) draws attention to the fact that it is claimed that compliance with this document may involve the use of a patent ~~concerning the determination of the E - J characteristics by inductive J_c measurements as a function of frequency, given in the Introduction, Clause 1, Clause 4 and 5.1~~. IEC takes no position concerning the evidence, validity, and scope of this patent right.

¹ Numbers in square brackets refer to the Bibliography.

The holder of this patent right has assured IEC that s/he is willing to negotiate licences ~~free of charge~~ under reasonable and non-discriminatory terms and conditions with applicants throughout the world. In this respect, the statement of the holder of this patent right is registered with IEC. Information may be obtained from the patent database available at <http://patents.iec.ch>.

~~Name of holder of patent right:~~

~~National Institute of Advanced Industrial Science and Technology~~

~~Address:~~

~~Intellectual Property Planning Office, Intellectual Property Department-
1-1-1, Umezono, Tsukuba, Ibaraki Prefecture, Japan~~

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights other than those ~~identified above~~ in the patent database. IEC shall not be held responsible for identifying any or all such patent rights.

~~ISO (www.iso.org/patents) and IEC (<http://patents.iec.ch>) maintain on-line data bases of patents relevant to their standards. Users are encouraged to consult the data bases for the most up-to-date information concerning patents.~~

SUPERCONDUCTIVITY –

Part 17: Electronic characteristic measurements – Local critical current density and its distribution in large-area superconducting films

1 Scope

This part of IEC 61788 ~~describes~~ specifies the measurements of the local critical current density (J_c) and its distribution in large-area high-temperature superconducting (HTS) films by an inductive method using third-harmonic voltages. The most important consideration for precise measurements is to determine J_c at liquid nitrogen temperatures by an electric-field criterion and obtain current-voltage characteristics from its frequency dependence. Although it is possible to measure J_c in applied DC magnetic fields [20] [21], the scope of this document is limited to the measurement without DC magnetic fields.

This technique intrinsically measures the critical sheet current that is the product of J_c and the film thickness d . The range and measurement resolution for $J_c d$ of HTS films are as follows.

- $J_c d$: from 200 A/m to 32 kA/m (based on results, not limitation).
- Measurement resolution: 100 A/m (based on results, not limitation).

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

~~IEC 60050 (all parts), International Electrotechnical Vocabulary (available at <http://www.electropedia.org><<http://www.electropedia.org>>)~~

IEC 60050-815, *International Electrotechnical Vocabulary – Part 815: Superconductivity* (available at <<http://www.electropedia.org>>)

© Copyright SEK Svensk Elstandard. Reproduction in any form without permission is prohibited.

Supraledning – Del 17: Mätning av elektroniska egenskaper – Lokal kritisk strömtäthet och dess fördelning i supraledande film med stor area

Superconductivity –

Part 17: Electronic characteristic measurements –

Local critical current density and its distribution in large-area superconducting films

Som svensk standard gäller europastandarden EN IEC 61788-17:2021. Den svenska standarden innehåller den officiella engelska språkversionen av EN IEC 61788-17:2021.

Nationellt förord

Europastandarden EN IEC 61788-17:2021

består av:

- **europastandardens ikraftsättningsdokument**, utarbetat inom CENELEC
- **IEC 61788-17, Second edition, 2021 - Superconductivity - Part 17: Electronic characteristic measurements - Local critical current density and its distribution in large-area superconducting films**

utarbetad inom International Electrotechnical Commission, IEC.

Tidigare fastställd svensk standard SS-EN 61788-17, utgåva 1, 2013, gäller ej fr o m 2024-06-02.

ICS 17.220.20; 29.050.00

Denna standard är fastställd av SEK Svensk Elstandard, som också kan lämna upplysningar om **sakinnehållet** i standarden.
Postadress: Box 1284, 164 29 KISTA
Telefon: 08 - 444 14 00.
E-post: sek@elstandard.se. Internet: www.elstandard.se

Standarder underlättar utvecklingen och höjer elsäkerheten

Det finns många fördelar med att ha gemensamma tekniska regler för bl a mätning, säkerhet och provning och för utförande, skötsel och dokumentation av elprodukter och elanläggningar.

Genom att utforma sådana standarder blir säkerhetsfordringar tydliga och utvecklingskostnaderna rimliga samtidigt som marknadens acceptans för produkten eller tjänsten ökar.

Många standarder inom elområdet beskriver tekniska lösningar och metoder som åstadkommer den elsäkerhet som föreskrivs av svenska myndigheter och av EU.

SEK är Sveriges röst i standardiseringsarbetet inom elområdet

SEK Svensk Elstandard svarar för standardiseringen inom elområdet i Sverige och samordnar svensk medverkan i internationell och europeisk standardisering. SEK är en ideell organisation med frivilligt deltagande från svenska myndigheter, företag och organisationer som vill medverka till och påverka utformningen av tekniska regler inom elektrotekniken.

SEK samordnar svenska intressenters medverkan i SEKs tekniska kommittéer och stödjer svenska experters medverkan i internationella och europeiska projekt.

Stora delar av arbetet sker internationellt

Utformningen av standarder sker i allt väsentligt i internationellt och europeiskt samarbete. SEK är svensk nationalkommitté av International Electrotechnical Commission (IEC) och Comité Européen de Normalisation Electrotechnique (CENELEC).

Standardiseringsarbetet inom SEK är organiserat i referensgrupper bestående av ett antal tekniska kommittéer som speglar hur arbetet inom IEC och CENELEC är organiserat.

Arbetet i de tekniska kommittéerna är öppet för alla svenska organisationer, företag, institutioner, myndigheter och statliga verk. Den årliga avgiften för deltagandet och intäkter från försäljning finansierar SEKs standardiseringsverksamhet och medlemsavgift till IEC och CENELEC.

Var med och påverka!

Den som deltar i SEKs tekniska kommittéarbete har möjlighet att påverka framtida standarder och får tidig tillgång till information och dokumentation om utvecklingen inom sitt teknikområde. Arbetet och kontakterna med kollegor, kunder och konkurrenter kan gynnsamt påverka enskilda företags affärsutveckling och bidrar till deltagarnas egen kompetensutveckling.

Du som vill dra nytta av dessa möjligheter är välkommen att kontakta SEKs kansli för mer information.

SEK Svensk Elstandard

Box 1284
164 29 Kista
Tel 08-444 14 00
www.elstandard.se

English Version

Superconductivity - Part 17: Electronic characteristic
measurements - Local critical current density and its distribution
in large-area superconducting films
(IEC 61788-17:2021)

Supraconductivité - Partie 17: Mesures de caractéristiques
électroniques - Densité de courant critique local et sa
distribution dans les films supraconducteurs de grande
surface
(IEC 61788-17:2021)

Supraleitfähigkeit - Teil 17: Messungen der elektronischen
Charakteristik - Lokale kritische Stromdichte und deren
Verteilung in großflächigen supraleitenden Schichten
(IEC 61788-17:2021)

This European Standard was approved by CENELEC on 2021-06-02. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Republic of North Macedonia, Romania, Serbia, Slovakia, Slovenia, Spain, Sweden, Switzerland, Turkey and the United Kingdom.



European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

CEN-CENELEC Management Centre: Rue de la Science 23, B-1040 Brussels

European foreword

The text of document 90/462/FDIS, future edition 2 of IEC 61788-17, prepared by IEC/TC 90 "Superconductivity" was submitted to the IEC-CENELEC parallel vote and approved by CENELEC as EN IEC 61788-17:2021.

The following dates are fixed:

- latest date by which the document has to be implemented at national level by publication of an identical national standard or by endorsement (dop) 2022-03-02
- latest date by which the national standards conflicting with the document have to be withdrawn (dow) 2024-06-02

This document supersedes EN 61788-17:2013 and all of its amendments and corrigenda (if any).

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC shall not be held responsible for identifying any or all such patent rights.

Endorsement notice

The text of the International Standard IEC 61788-17:2021 was approved by CENELEC as a European Standard without any modification.

Annex ZA (normative)

Normative references to international publications with their corresponding European publications

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

NOTE 1 Where an International Publication has been modified by common modifications, indicated by (mod), the relevant EN/HD applies.

NOTE 2 Up-to-date information on the latest versions of the European Standards listed in this annex is available here: www.cenelec.eu.

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 60050-815	-	International Electrotechnical Vocabulary - Part 815: Superconductivity	-	-



IEC 61788-17

Edition 2.0 2021-04

INTERNATIONAL STANDARD



**Superconductivity –
Part 17: Electronic characteristic measurements – Local critical current density
and its distribution in large-area superconducting films**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 17.220.20; 29.050

ISBN 978-2-8322-9663-9

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD	4
INTRODUCTION	6
1 Scope	8
2 Normative references	8
3 Terms and definitions	8
4 Requirements	9
5 Apparatus	10
5.1 Measurement equipment	10
5.2 Components for inductive measurements	11
6 Measurement procedure	12
6.1 General	12
6.2 Determination of the experimental coil coefficient	12
6.3 Measurement of J_C in sample films	16
6.4 Measurement of J_C with only one frequency	16
6.5 Examples of the theoretical and experimental coil coefficients	17
7 Uncertainty in the test method	18
7.1 Major sources of systematic effects that affect the U_3 measurement	18
7.2 Effect of deviation from the prescribed value in the coil-to-film distance	19
7.3 Uncertainty in the experimental coil coefficient and the obtained J_C	20
7.4 Effects of the film edge	20
7.5 Specimen protection	20
8 Test report	21
8.1 Identification of test specimen	21
8.2 Report of J_C values	21
8.3 Report of test conditions	21
Annex A (informative) Additional information relating to Clauses 1 to 8	22
A.1 Comments on other methods for measuring the local J_C of large-area HTS films	22
A.2 Requirements	22
A.3 Theory of the third-harmonic voltage generation	23
A.4 Calculation of the induced electric fields	24
A.5 Theoretical coil coefficient k and experimental coil coefficient k'	25
A.6 Scaling of the U_3 – I_0 curves and the constant-inductance criterion to determine I_{th}	25
A.7 Effects of reversible flux motion	27
Annex B (informative) Optional measurement systems	28
B.1 Overview	28
B.2 Harmonic noises arising from the power source and their reduction	29
Annex C (informative) Evaluation of the uncertainty	33
C.1 Evaluation of the uncertainty in the experimental coil coefficient	33
C.2 Uncertainty in the calculation of induced electric fields	34
C.3 Experimental results on the effect of the deviation of the coil-to-film distance	35

C.4	Examples of the Type-A uncertainties of J_C and n -values, originating from the experimental uncertainty in the U_3 measurement	35
C.5	Evaluation of the uncertainty in the obtained J_C	36
C.6	Experimental results that reveal the effect of the film edge	37
	Bibliography	39
Figure 1	– Diagram for an electric circuit used for inductive J_C measurement of HTS films	10
Figure 2	– Illustration showing techniques to press the sample coil to HTS films	11
Figure 3	– Example of a calibration wafer used to determine the coil coefficient	12
Figure 4	– Illustration of the sample coil and the magnetic field during measurement	13
Figure 5	– Illustration of the sample coil and its magnetic field generation	14
Figure 6	– E - J characteristics measured by a transport method and the U_3 inductive method	16
Figure 7	– Illustration of coils 1 and 3 in Table 2	17
Figure 8	– The coil-factor function $F(r) = 2H_0/I_0$ calculated for the three coils	18
Figure 9	– The coil-to-film distance Z_1 dependence of the theoretical coil coefficient k	19
Figure A.1	– Illustration of the sample coil and the magnetic field during measurement	24
Figure A.2	– U_3 and U_3/I_0 plotted against I_0 in a YBCO thin film measured in applied DC magnetic fields, and the scaling observed when normalized by I_{th} (insets)	26
Figure A.3	– Example of the normalized third-harmonic voltages (U_3/fI_0) measured with various frequencies	26
Figure B.1	– Schematic diagram for the variable- RL -cancel circuit	29
Figure B.2	– Diagram for an electrical circuit used for the two-coil method	29
Figure B.3	– Harmonic noises arising from the power source	30
Figure B.4	– Noise reduction using a cancel coil with a superconducting film	30
Figure B.5	– Normalized harmonic noises (U_3/fI_0) arising from the power source	31
Figure B.6	– Normalized noise voltages after the reduction using a cancel coil with a superconducting film	31
Figure B.7	– Normalized noise voltages after the reduction using a cancel coil without a superconducting film	32
Figure B.8	– Normalized noise voltages with the two-coil system shown in Figure B.2	32
Figure C.1	– Effect of the coil position against a superconducting thin film on the measured J_C values	38
Table 1	– Specifications and theoretical coil coefficients k of sample coils	14
Table 2	– Specifications and coil coefficients of typical sample coils	17
Table C.1	– Uncertainty budget table for the experimental coil coefficient k'	34
Table C.2	– Examples of repeated measurements of J_C and n -values	36

INTERNATIONAL ELECTROTECHNICAL COMMISSION

SUPERCONDUCTIVITY –**Part 17: Electronic characteristic measurements –
Local critical current density and its distribution
in large-area superconducting films****FOREWORD**

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

IEC 61788-17 has been prepared by IEC technical committee 90: Superconductivity. It is an International Standard.

This second edition cancels and replaces the first edition published in 2013. This edition constitutes a technical revision.

This edition includes the following a significant technical change with respect to the previous edition:

- a) A simple method to calculate theoretical coil coefficient k is described in 6.2.1.

The text of this International Standard is based on the following documents:

FDIS	Report on voting
90/462/FDIS	90/464/RVD

Full information on the voting for the approval of this International Standard can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

A list of all the parts of the IEC 61788 series, published under the general title *Superconductivity*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

Over thirty years after their discovery in 1986, high-temperature superconductors are now finding their way into products and technologies that will revolutionize information transmission, transportation, and energy. Among them, high-temperature superconducting (HTS) microwave filters, which exploit the extremely low surface resistance of superconductors, have already been commercialized. They have two major advantages over conventional non-superconducting filters, namely: low insertion loss (low noise characteristics) and high frequency selectivity (sharp cut) [1]¹. These advantages enable a reduced number of base stations, improved speech quality, more efficient use of frequency bandwidths, and reduced unnecessary radio wave noise.

Large-area superconducting thin films have been developed for use in microwave devices [2]. They are also considered for use in emerging superconducting power devices, such as resistive-type superconducting fault-current limiters (SFCLs) [3] [4] [5], superconducting fault detectors used for superconductor-triggered fault current limiters [6] [7] and persistent-current switches used for persistent-current HTS magnets [8] [9]. The critical current density J_c is one of the key parameters that describe the quality of large-area HTS films. Nondestructive, AC inductive methods are widely used to measure J_c and its distribution for large-area HTS films [10] [11] [12] [13], among which the method utilizing third-harmonic voltages $U_3 \cos(3\omega t + \theta)$ is the most popular [10] [11], where ω , t and θ denote the angular frequency, time, and initial phase, respectively. However, these conventional methods are not accurate because they have not considered the electric-field E criterion of the J_c measurement [14] [15] and sometimes use an inappropriate criterion to determine the threshold current I_{th} from which J_c is calculated [16]. A conventional method can obtain J_c values that differ from the accurate values by 10 % to 20 % [15]. It is thus important to establish standard test methods to precisely measure the local critical current density and its distribution, to which all involved in the HTS filter industry can refer for quality control of the HTS films. Background knowledge on the inductive J_c measurements of HTS thin films is summarized in Annex A.

In these inductive methods, AC magnetic fields are generated with AC currents $I_0 \cos \omega t$ in a small coil mounted just above the film, and J_c is calculated from the threshold coil current I_{th} , at which full penetration of the magnetic field to the film is achieved [17]. For the inductive method using third-harmonic voltages U_3 , U_3 is measured as a function of I_0 , and the I_{th} is determined as the coil current I_0 at which U_3 starts to emerge. The induced electric fields E in the superconducting film at $I_0 = I_{th}$, which are proportional to the frequency f of the AC current, can be estimated by a simple Bean model [14]. A standard method has been proposed to precisely measure J_c with an electric-field criterion by detecting U_3 and obtaining the n -value (index of the power-law E - J characteristics) by measuring I_{th} precisely at various frequencies [14] [15] [18] [19]. This method not only obtains precise J_c values, but also facilitates the detection of degraded parts in inhomogeneous specimens, because the decline of n -value is more noticeable than the decrease of J_c in such parts [15]. It is noted that this standard method is excellent for assessing homogeneity in large-area HTS films, although the relevant parameter for designing microwave devices is not J_c , but the surface resistance. For application of large-area superconducting thin films to SFCLs, knowledge on J_c distribution is vital, because J_c distribution significantly affects quench distribution in SFCLs during faults.

The International Electrotechnical Commission (IEC) draws attention to the fact that it is claimed that compliance with this document may involve the use of a patent. IEC takes no position concerning the evidence, validity, and scope of this patent right.

¹ Numbers in square brackets refer to the Bibliography.

The holder of this patent right has assured IEC that s/he is willing to negotiate licences under reasonable and non-discriminatory terms and conditions with applicants throughout the world. In this respect, the statement of the holder of this patent right is registered with IEC. Information may be obtained from the patent database available at <http://patents.iec.ch>.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights other than those in the patent database. IEC shall not be held responsible for identifying any or all such patent rights.

SUPERCONDUCTIVITY –

Part 17: Electronic characteristic measurements – Local critical current density and its distribution in large-area superconducting films

1 Scope

This part of IEC 61788 specifies the measurements of the local critical current density (J_c) and its distribution in large-area high-temperature superconducting (HTS) films by an inductive method using third-harmonic voltages. The most important consideration for precise measurements is to determine J_c at liquid nitrogen temperatures by an electric-field criterion and obtain current-voltage characteristics from its frequency dependence. Although it is possible to measure J_c in applied DC magnetic fields [20] [21], the scope of this document is limited to the measurement without DC magnetic fields.

This technique intrinsically measures the critical sheet current that is the product of J_c and the film thickness d . The range and measurement resolution for $J_c d$ of HTS films are as follows.

- $J_c d$: from 200 A/m to 32 kA/m (based on results, not limitation).
- Measurement resolution: 100 A/m (based on results, not limitation).

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050-815, *International Electrotechnical Vocabulary – Part 815: Superconductivity* (available at <<http://www.electropedia.org>>)