

© Copyright SEK. Reproduction in any form without permission is prohibited.

## Kopplingsapparater för högst 1000 V – Del 2: Effektbrytare

*Low-voltage switchgear and controlgear –  
Part 2: Circuit-breakers*

Som svensk standard gäller europastandarden EN 60947-2:2017. Den svenska standarden innehåller den officiella engelska språkversionen av EN 60947-2:2017.

### Nationellt förord

Europastandarden EN 60947-2:2017

består av:

- **europastandardens ikraftsättningsdokument**, utarbetat inom CENELEC
- **IEC 60947-2, Fifth edition, 2016<sup>\*)</sup> - Low-voltage switchgear and controlgear - Part 2: Circuit-breakers**

utarbetad inom International Electrotechnical Commission, IEC.

Tidigare fastställd svensk standard SS-EN 60947-2, utgåva 4, 2006, SS-EN 60947-2/A1, utgåva 1, 2009 och SS-EN 60947-2/A2, utgåva 1, 2013, gäller ej fr o m 2020-10-13.

---

<sup>\*)</sup>Corrigendum November 2016 till IEC 60947-2:2016 är inarbetat i standarden.

### *Standarder underlättar utvecklingen och höjer elsäkerheten*

Det finns många fördelar med att ha gemensamma tekniska regler för bl a mätning, säkerhet och provning och för utförande, skötsel och dokumentation av elprodukter och elanläggningar.

Genom att utforma sådana standarder blir säkerhetsfordringar tydliga och utvecklingskostnaderna rimliga samtidigt som marknadens acceptans för produkten eller tjänsten ökar.

Många standarder inom elområdet beskriver tekniska lösningar och metoder som åstadkommer den elsäkerhet som föreskrivs av svenska myndigheter och av EU.

### *SEK är Sveriges röst i standardiseringsarbetet inom elområdet*

SEK Svensk Elstandard svarar för standardiseringen inom elområdet i Sverige och samordnar svensk medverkan i internationell och europeisk standardisering. SEK är en ideell organisation med frivilligt deltagande från svenska myndigheter, företag och organisationer som vill medverka till och påverka utformningen av tekniska regler inom elektrotekniken.

SEK samordnar svenska intressenters medverkan i SEKs tekniska kommittéer och stödjer svenska experters medverkan i internationella och europeiska projekt.

### *Stora delar av arbetet sker internationellt*

Utformningen av standarder sker i allt väsentligt i internationellt och europeiskt samarbete. SEK är svensk nationalkommitté av International Electrotechnical Commission (IEC) och Comité Européen de Normalisation Electrotechnique (CENELEC).

Standardiseringsarbetet inom SEK är organiserat i referensgrupper bestående av ett antal tekniska kommittéer som speglar hur arbetet inom IEC och CENELEC är organiserat.

Arbetet i de tekniska kommittéerna är öppet för alla svenska organisationer, företag, institutioner, myndigheter och statliga verk. Den årliga avgiften för deltagandet och intäkter från försäljning finansierar SEKs standardiseringsverksamhet och medlemsavgift till IEC och CENELEC.

### *Var med och påverka!*

Den som deltar i SEKs tekniska kommittéarbete har möjlighet att påverka framtida standarder och får tidig tillgång till information och dokumentation om utvecklingen inom sitt teknikområde. Arbetet och kontakterna med kollegor, kunder och konkurrenter kan gynnsamt påverka enskilda företags affärsutveckling och bidrar till deltagarnas egen kompetensutveckling.

Du som vill dra nytta av dessa möjligheter är välkommen att kontakta SEKs kansli för mer information.

### **SEK Svensk Elstandard**

Box 1284  
164 29 Kista  
Tel 08-444 14 00  
[www.elstandard.se](http://www.elstandard.se)

EUROPEAN STANDARD

**EN 60947-2**

NORME EUROPÉENNE

EUROPÄISCHE NORM

October 2017

ICS 29.130.20

Supersedes EN 60947-2:2006

English Version

**Low-voltage switchgear and controlgear -  
Part 2: Circuit-breakers  
(IEC 60947-2:2016 + COR1:2016)**

Appareillage à basse tension - Partie 2: Disjoncteurs  
(IEC 60947-2:2016 + COR1:2016)

Niederspannungsschaltgeräte - Teil 2: Leistungsschalter  
(IEC 60947-2:2016 + COR1:2016)

This European Standard was approved by CENELEC on 2016-07-12. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, Former Yugoslav Republic of Macedonia, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Romania, Serbia, Slovakia, Slovenia, Spain, Sweden, Switzerland, Turkey and the United Kingdom.



European Committee for Electrotechnical Standardization  
Comité Européen de Normalisation Electrotechnique  
Europäisches Komitee für Elektrotechnische Normung

**CEN-CENELEC Management Centre: Avenue Marnix 17, B-1000 Brussels**

## European foreword

The text of document 121A/71/FDIS, future edition 5 of IEC 60947-2, prepared by SC 121A "Low-voltage switchgear and controlgear" of IEC/TC 121 "Switchgear and controlgear and their assemblies for low voltage" was submitted to the IEC-CENELEC parallel vote and approved by CENELEC as EN 60947-2:2017.

The following dates are fixed:

- latest date by which the document has to be implemented at national level by publication of an identical national standard or by endorsement (dop) 2018-04-13
- latest date by which the national standards conflicting with the document have to be withdrawn (dow) 2020-10-13

This document supersedes EN 60947-2:2006.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC shall not be held responsible for identifying any or all such patent rights.

This document has been prepared under a mandate given to CENELEC by the European Commission and the European Free Trade Association, and supports essential requirements of EU Directives.

For the relationship with EU Directives and the standardization requests see informative Annex ZZA and Annex ZZB, which are integral parts of this document.

## Endorsement notice

The text of the International Standard IEC 60947-2:2016 + COR1:2016 was approved by CENELEC as a European Standard without any modification.

In the official version, for Bibliography, the following notes have to be added for the standards indicated:

IEC 60051 Series	NOTE	Harmonized as EN 60051 Series.
IEC 60112	NOTE	Harmonized as EN 60112.
IEC 60898 Series	NOTE	Harmonized as EN 60898 Series.
IEC 60934	NOTE	Harmonized as EN 60934.
IEC 60947-3	NOTE	Harmonized as EN 60947-3.
IEC 60947-5-1	NOTE	Harmonized as EN 60947-5-1.
IEC 61000-4-13	NOTE	Harmonized as EN 61000-4-13.
IEC 61008-1:2010	NOTE	Harmonized as EN 61008-1:2012 (modified).
IEC 61008-1:2010/A1:2012	NOTE	Harmonized as EN 61008-1:2012/A1:2014 (modified).
IEC 61008-1:2010/A2:2013	NOTE	Harmonized as EN 61008-1:2012/A2:2014 (modified).
IEC 61009-1:2010	NOTE	Harmonized as EN 61009-1:2012 (modified).
IEC 61009-1:2010/A1:2012	NOTE	Harmonized as EN 61009-1:2012/A1:2014 (modified).
IEC 61009-1:2010/A2:2013	NOTE	Harmonized as EN 61009-1:2012/A2:2014 (modified).
IEC 61131-1:2003	NOTE	Harmonized as EN 61131-1:2003 (not modified).
IEC 61439 Series	NOTE	Harmonized as EN 61439 Series.

## Annex ZA (normative)

### Normative references to international publications with their corresponding European publications

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

NOTE 1 When an International Publication has been modified by common modifications, indicated by (mod), the relevant EN/HD applies.

NOTE 2 Up-to-date information on the latest versions of the European Standards listed in this annex is available here: [www.cenelec.eu](http://www.cenelec.eu)

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 60068-2-14	-	Environmental testing - Part 2-14: Tests - Test N: Change of temperature	EN 60068-2-14	2009
IEC 60068-2-30	-	Environmental testing - Part 2-30: Tests - Test Db: Damp heat, cyclic (12 h + 12 h cycle)	EN 60068-2-30	2005
IEC 60269-1	2006	Low-voltage fuses - Part 1: General requirements	EN 60269-1	2007
IEC 60364	Series	Low-voltage electrical installations	HD 60364	Series
IEC 60664-1	2007	Insulation coordination for equipment within low-voltage systems - Part 1: Principles, requirements and tests	EN 60664-1	2007
IEC 60947-1	2007	Low-voltage switchgear and controlgear - Part 1: General rules	EN 60947-1	2007
+A1	2010		+A1	2011
+A2	2014		+A2	2014
IEC 60947-4-1	-	Low-voltage switchgear and controlgear - Part 4-1: Contactors and motor-starters - Electromechanical contactors and motor- starters	EN 60947-4-1	2010
IEC 61000-3-2	-	Electromagnetic compatibility (EMC) - Part 3-2: Limits - Limits for harmonic current emissions (equipment input current ≤ 16 A per phase)	EN 61000-3-2	2014
IEC 61000-3-3	-	Electromagnetic compatibility (EMC) - Part 3-3: Limits - Limitation of voltage changes, voltage fluctuations and flicker in public low-voltage supply systems, for equipment with rated current ≤ 16 A per phase and not subject to conditional connection	EN 61000-3-3	2013
IEC 61000-4-2	-	Electromagnetic compatibility (EMC) - Part 4-2: Testing and measurement techniques - Electrostatic discharge immunity test	EN 61000-4-2	2009

## EN 60947-2:2017

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 61000-4-3	2006	Electromagnetic compatibility (EMC) - Part 4-3: Testing and measurement techniques - Radiated, radio-frequency, electromagnetic field immunity test	EN 61000-4-3	2006
+A1	2007		+A1	2008
+A2	2010		+A2	2010
IEC 61000-4-4	2012	Electromagnetic compatibility (EMC) - Part 4-4: Testing and measurement techniques - Electrical fast transient/burst immunity test	EN 61000-4-4	2012
IEC 61000-4-5	2014	Electromagnetic compatibility (EMC) - Part 4-5: Testing and measurement techniques - Surge immunity test	EN 61000-4-5	2014
IEC 61000-4-6	2013	Electromagnetic compatibility (EMC) - Part 4-6: Testing and measurement techniques - Immunity to conducted disturbances, induced by radio-frequency fields	EN 61000-4-6	2014
IEC 61000-4-11	-	Electromagnetic compatibility (EMC) - Part 4-11: Testing and measurement techniques - Voltage dips, short interruptions and voltage variations immunity tests	EN 61000-4-11	2004
IEC 61140	-	Protection against electric shock - Common aspects for installation and equipment	EN 61140	2016
IEC 62475	2010	High-current test techniques - Definitions and requirements for test currents and measuring systems	EN 62475	2010
CISPR 11	-	Industrial, scientific and medical equipment - Radio-frequency disturbance characteristics - Limits and methods of measurement	EN 55011	2016
CISPR 22	-	Information technology equipment - Radio disturbance characteristics - Limits and methods of measurement	EN 55022 + AC	2010 <sup>1)</sup> 2011 <sup>1)</sup>

---

<sup>1)</sup> Superseded by EN 50561-1:2013.

## CONTENTS

FOREWORD.....	14
1 General .....	16
1.1 Scope and object .....	16
1.2 Normative references .....	17
2 Terms and definitions.....	18
3 Classification .....	22
4 Characteristics of circuit-breakers .....	23
4.1 Summary of characteristics .....	23
4.2 Type of circuit-breaker .....	23
4.3 Rated and limiting values of the main circuit .....	23
4.3.1 General.....	23
4.3.2 Rated voltages .....	23
4.3.3 Currents.....	24
4.3.4 Rated frequency.....	24
4.3.5 Rated duty .....	24
4.3.6 Short-circuit characteristics .....	24
4.4 Selectivity categories.....	27
4.5 Control circuits .....	27
4.5.1 Electrical control circuits .....	27
4.5.2 Air-supply control circuits (pneumatic or electro-pneumatic).....	27
4.6 Auxiliary circuits .....	27
4.7 Releases.....	28
4.7.1 Types.....	28
4.7.2 Characteristics .....	28
4.7.3 Current setting of over-current releases.....	28
4.7.4 Tripping time setting of over-current releases .....	29
4.8 Integral fuses (integrally fused circuit-breakers).....	29
5 Product information.....	29
5.1 Nature of the information .....	29
5.2 Marking.....	29
5.3 Instructions for installation, operation and maintenance .....	31
6 Normal service, mounting and transport conditions.....	31
7 Constructional and performance requirements.....	31
7.1 Constructional requirements .....	31
7.1.1 General.....	31
7.1.2 Withdrawable circuit-breakers .....	31
7.1.3 Additional requirements for circuit-breakers suitable for isolation .....	32
7.1.4 Clearances and creepage distances .....	32
7.1.5 Requirements for the safety of the operator .....	32
7.1.6 List of construction breaks.....	32
7.1.7 Additional requirements for circuit-breakers provided with a neutral pole.....	33
7.1.8 Digital inputs and outputs for use with programmable logic controllers (PLCs) .....	33
7.2 Performance requirements .....	33
7.2.1 Operating conditions .....	33
7.2.2 Temperature-rise .....	36

7.2.3	Dielectric properties .....	37
7.2.4	Ability to make and break under no load, normal load and overload conditions .....	37
7.2.5	Ability to make and break under short-circuit conditions .....	38
7.2.6	Vacant .....	38
7.2.7	Additional requirements for circuit-breakers suitable for isolation .....	38
7.2.8	Specific requirements for integrally fused circuit-breakers .....	39
7.2.9	Co-ordination between a circuit-breaker and another short-circuit protective device .....	39
7.3	Electromagnetic compatibility (EMC) .....	39
8	Tests .....	39
8.1	Kind of tests .....	39
8.1.1	General .....	39
8.1.2	Type tests .....	39
8.1.3	Routine tests .....	40
8.2	Compliance with constructional requirements .....	40
8.3	Type tests .....	40
8.3.1	Test sequences .....	40
8.3.2	General test conditions .....	48
8.3.3	Test sequence I: General performance characteristics .....	56
8.3.4	Test sequence II: Rated service short-circuit breaking capacity .....	65
8.3.5	Test sequence III: Rated ultimate short-circuit breaking capacity .....	66
8.3.6	Test sequence IV: Rated short-time withstand current .....	68
8.3.7	Test sequence V: Performance of integrally fused circuit-breakers .....	69
8.3.8	Test sequence VI: combined test sequence .....	71
8.3.9	Critical d.c. load current test .....	72
8.4	Routine tests .....	73
8.4.1	General .....	73
8.4.2	Mechanical operation tests .....	74
8.4.3	Verification of the calibration of overcurrent releases .....	74
8.4.4	Verification of the operation of undervoltage and shunt releases .....	75
8.4.5	Additional tests for CBRs .....	75
8.4.6	Dielectric tests .....	75
8.4.7	Test for the verification of clearances less than those corresponding to case A of Table 13 of IEC 60947-1:2007 .....	76
8.5	Special tests – Damp heat, salt mist, vibration and shock .....	76
Annex A (normative)	Co-ordination between a circuit-breaker and another short-circuit protective device associated in the same circuit .....	79
A.1	General .....	79
A.2	Scope and object .....	79
A.3	General requirements for the co-ordination of a circuit-breaker with another SCPD .....	80
A.3.1	General considerations .....	80
A.3.2	Take-over current .....	80
A.3.3	Behaviour of C <sub>1</sub> in association with another SCPD .....	80
A.4	Type and characteristics of the associated SCPD .....	80
A.5	Verification of selectivity .....	81
A.5.1	General .....	81
A.5.2	Consideration of selectivity by desk study .....	81
A.5.3	Selectivity determined by test .....	82



A.6	Verification of back-up protection .....	83
A.6.1	Determination of the take-over current.....	83
A.6.2	Verification of back-up protection .....	83
A.6.3	Tests for verification of back-up protection .....	83
A.6.4	Results to be obtained.....	84
Annex B (normative)	Circuit-breakers incorporating residual current protection .....	90
B.1	General.....	90
B.1.1	Preamble .....	90
B.1.2	Scope and object .....	90
B.2	Terms and definitions.....	91
B.2.1	Terms and definitions relating to currents flowing from live parts to earth.....	91
B.2.2	Terms and definitions relating to the energization of a CBR .....	91
B.2.3	Terms and definitions relating to the operation and the functions of a CBR.....	92
B.2.4	Terms and definitions relating to values and ranges of energizing quantities.....	93
B.3	Classification .....	94
B.3.1	Classification according to the method of operation of the residual current function.....	94
B.3.2	Classification according to the possibility of adjusting the residual operating current.....	94
B.3.3	Classification according to time-delay of the residual current function .....	94
B.3.4	Classification according to behaviour in presence of a d.c. component.....	94
B.4	Characteristics of CBRs concerning their residual current function.....	94
B.4.1	Rated values.....	94
B.4.2	Preferred and limiting values .....	95
B.4.3	Value of the rated residual short-circuit making and breaking capacity ( $I_{\Delta m}$ ) .....	96
B.4.4	Operating characteristics in case of an earth fault current in the presence or absence of a d.c. component .....	96
B.5	Marking.....	96
B.6	Normal service, mounting and transport conditions .....	97
B.7	Design and operating requirements .....	98
B.7.1	Design requirements .....	98
B.7.2	Operating requirements.....	98
B.7.3	Electromagnetic compatibility .....	100
B.8	Tests .....	100
B.8.1	General.....	100
B.8.2	Verification of the operating characteristic .....	103
B.8.3	Verification of dielectric properties.....	104
B.8.4	Verification of the operation of the test device at the limits of rated voltage.....	105
B.8.5	Verification of the limiting value of the non-operating current under over-current conditions.....	105
B.8.6	Verification of the resistance against unwanted tripping due to surge currents resulting from impulse voltages .....	106
B.8.7	Verification of the behaviour of CBRs of type A in the case of an earth fault current comprising a d.c. component .....	107
B.8.8	Verification of the behaviour of CBRs functionally dependent on line voltage classified under B.3.1.2.1 .....	108

B.8.9	Verification of the behaviour of CBRs functionally dependent on line voltage as classified under B.3.1.2.2 in the case of failure of line voltage.....	109
B.8.10	Verification of the residual short-circuit making and breaking capacity .....	110
B.8.11	Verification of the effects of environmental conditions.....	111
B.8.12	Verification of electromagnetic compatibility .....	111
B.8.13	Test for variations or interruptions of voltage and for voltage dips .....	113
Annex C (normative)	Individual pole short-circuit test sequence .....	120
C.1	General.....	120
C.2	Test of individual pole short-circuit breaking capacity.....	120
C.3	Verification of dielectric withstand.....	120
C.4	Verification of overload releases.....	120
Annex D	Vacant .....	121
Annex E (informative)	Items subject to agreement between manufacturer and user.....	122
Annex F (normative)	Additional tests for circuit-breakers with electronic over-current protection.....	123
F.1	General.....	123
F.2	List of tests .....	123
F.2.1	General.....	123
F.2.2	Electromagnetic compatibility (EMC) tests .....	123
F.2.3	Suitability for multiple frequencies .....	124
F.2.4	Dry heat test .....	124
F.2.5	Damp heat test.....	124
F.2.6	Temperature variation cycles at a specified rate of change .....	124
F.3	General test conditions.....	124
F.3.1	General.....	124
F.3.2	Electromagnetic compatibility tests .....	124
F.4	Immunity tests.....	125
F.4.1	Harmonic currents.....	125
F.4.2	Electrostatic discharges .....	126
F.4.3	Radiated RF electromagnetic fields .....	126
F.4.4	Electrical fast transient/burst (EFT/B) .....	126
F.4.5	Surges .....	127
F.4.6	Conducted disturbances induced by RF fields (common mode).....	127
F.4.7	Current dips .....	127
F.5	Emission tests.....	128
F.5.1	Harmonics .....	128
F.5.2	Voltage fluctuations.....	128
F.5.3	Conducted RF disturbances (150 kHz to 30 MHz) .....	128
F.5.4	Radiated RF disturbances (30 MHz to 1 GHz).....	128
F.6	Suitability for multiple frequencies .....	129
F.6.1	General.....	129
F.6.2	Test conditions.....	129
F.6.3	Test procedure.....	129
F.6.4	Test results .....	129
F.7	Dry heat test .....	129
F.7.1	Test procedure.....	129
F.7.2	Test results .....	130
F.7.3	Verification of overload releases.....	130
F.8	Damp heat test.....	130

F.8.1	Test procedure.....	130
F.8.2	Verification of overload releases.....	130
F.9	Temperature variation cycles at a specified rate of change .....	130
F.9.1	Test conditions.....	130
F.9.2	Test procedure.....	130
F.9.3	Test results .....	131
F.9.4	Verification of overload releases.....	131
Annex G (normative)	Power loss .....	144
G.1	General.....	144
G.2	Test methods .....	144
G.2.1	General case .....	144
G.2.2	AC circuit-breakers of rated current not exceeding 400 A.....	144
G.2.3	DC circuit-breakers .....	145
G.3	Test procedure.....	145
Annex H (normative)	Test sequence for circuit-breakers for IT systems .....	147
H.1	General.....	147
H.2	Individual pole short-circuit.....	147
H.3	Verification of dielectric withstand.....	148
H.4	Verification of overload releases.....	148
H.5	Marking.....	148
Annex J (normative)	Electromagnetic compatibility (EMC) – Requirements and test methods for circuit-breakers.....	149
J.1	General.....	149
J.2	Immunity.....	150
J.2.1	General.....	150
J.2.2	Electrostatic discharges .....	152
J.2.3	Radiated RF electromagnetic fields .....	153
J.2.4	Electrical fast transients/bursts (EFT/B).....	153
J.2.5	Surges .....	153
J.2.6	Conducted disturbances induced by RF fields (common mode).....	154
J.3	Emission .....	154
J.3.1	General.....	154
J.3.2	Conducted RF disturbances (150 kHz to 30 MHz) .....	155
J.3.3	Radiated RF disturbances (30 MHz to 1 000 MHz).....	155
Annex K (informative)	Glossary of symbols and graphical representation of characteristics.....	160
Annex L (normative)	Circuit-breakers not fulfilling the requirements for overcurrent protection.....	169
L.1	General.....	169
L.2	Terms and definitions .....	169
L.3	Classification .....	169
L.4	Rated values .....	169
L.4.1	Rated current ( $I_n$ ).....	169
L.4.2	Rated conditional short-circuit current ( $I_{CC}$ ).....	170
L.5	Product information .....	170
L.6	Constructional and performance requirements.....	170
L.7	Tests .....	170
L.7.1	General.....	170
L.7.2	Rated conditional short-circuit tests .....	171

Annex M (normative) Modular residual current devices (without integral current breaking device).....	174
M.1 General.....	174
M.1.1 Field of application .....	174
M.1.2 Field of application .....	174
M.2 Terms and definitions.....	174
M.2.1 Terms and definitions relating to the energization of an MRCD .....	174
M.2.2 Terms and definitions relating to the operation and the functions of an MRCD.....	175
M.3 Classification .....	175
M.3.1 Classification according to the configuration of the primary conductors .....	175
M.3.2 Classification according to the method of operation .....	176
M.3.3 Classification according to the possibility of adjusting the residual operating current.....	176
M.3.4 Classification according to time-delay of the residual current function .....	176
M.3.5 Classification according to behaviour in presence of a d.c. component.....	176
M.4 Characteristics of MRCDs .....	176
M.4.1 General characteristics .....	176
M.4.2 Characteristics of MRCDs concerning their residual current function.....	177
M.4.3 Behaviour under short-circuit conditions .....	178
M.4.4 Preferred and limiting values .....	178
M.5 Product information .....	179
M.6 Normal service, mounting and transport conditions .....	181
M.7 Design and operating requirements .....	181
M.7.1 Design requirements .....	181
M.7.2 Operating requirements.....	181
M.8 Tests .....	183
M.8.1 General.....	183
M.8.2 Compliance with constructional requirements .....	184
M.8.3 Verification of the operating characteristics .....	185
M.8.4 Verification of dielectric properties.....	187
M.8.5 Verification of the operation of the test device at the limits of the rated voltage.....	187
M.8.6 Verification of the limiting value of non-operating current under overcurrent conditions, in case of a single phase load .....	188
M.8.7 Resistance against unwanted tripping due to surge currents resulting from impulse voltages .....	188
M.8.8 Verification of the behaviour in case of an earth fault current comprising a d.c. component .....	188
M.8.9 Verification of the behaviour of MRCDs with separate sensing means in case of a failure of the sensing means connection.....	191
M.8.10 Verification of temperature-rise of terminal type MRCDs .....	191
M.8.11 Verification of mechanical and electrical endurance .....	191
M.8.12 Verification of the behaviour of MRCDs in case of failure of the voltage source for MRCDs classified under M.3.2.2.1 .....	192
M.8.13 Verification of the behaviour of MRCDs with voltage source as classified under M.3.2.2.2 in case of failure of the voltage source .....	193
M.8.14 Verification of the behaviour of the MRCD under short-circuit conditions .....	193
M.8.15 Verification of effects of environmental conditions .....	195
M.8.16 Verification of electromagnetic compatibility .....	195

Annex N (normative) Electromagnetic compatibility (EMC) – Additional requirements and test methods for devices not covered by Annex B, Annex F and Annex M.....	218
N.1    General.....	218
N.1.1    General.....	218
N.1.2    General test conditions.....	218
N.2    Immunity .....	218
N.2.1    General.....	218
N.2.2    Electrostatic discharges .....	219
N.2.3    Radiated RF electromagnetic fields .....	219
N.2.4    Electrical fast transients/bursts (EFT/B).....	219
N.2.5    Surges .....	220
N.2.6    Conducted disturbances induced by RF fields (common mode).....	220
N.2.7    Voltage dips and interruptions .....	220
N.3    Emission .....	220
N.3.1    General.....	220
N.3.2    Conducted RF disturbances (150 kHz to 30 MHz) .....	221
N.3.3    Radiated RF disturbances (30 MHz to 1 000 MHz).....	221
Annex O (normative) Instantaneous trip circuit-breakers (ICB) .....	222
O.1    General.....	222
O.2    Terms and definitions.....	222
O.3    Rated values .....	222
O.3.1    General.....	222
O.3.2    Rated current ( $I_n$ ).....	222
O.3.3    Rated short-circuit making capacity .....	222
O.3.4    Rated short-circuit breaking capacities .....	222
O.4    Product information .....	223
O.5    Constructional and performance requirements.....	223
O.6    Tests .....	223
O.6.1    Test sequence of the ICB alone.....	223
O.6.2    ICB associated with a specified protected device (i.e. motor-starter or overload relay).....	224
Annex P (normative) DC circuit-breakers for use in photovoltaic (PV) applications .....	225
P.1    Field of application .....	225
P.2    Terms and definitions.....	225
P.3    Classification .....	225
P.4    Characteristics of PV circuit-breakers .....	225
P.5    Product information.....	226
P.6    Normal service, mounting and transport conditions .....	226
P.7    Constructional and performance requirements.....	226
P.7.1    Constructional requirements.....	226
P.7.2    Performance requirements .....	226
P.7.3    Electromagnetic compatibility (EMC) .....	227
P.8    Tests .....	227
P.8.1    Kind of tests.....	227
P.8.2    Compliance with constructional requirements .....	227
P.8.3    Type tests .....	227
P.8.4    Routine tests.....	229
P.8.5    Special tests .....	229
Annex Q Vacant.....	230

Annex R (normative) Circuit-breakers incorporating residual current protection with automatic re-closing functions .....	231
R.1 General.....	231
R.1.1 Preamble .....	231
R.1.2 Field of application .....	231
R.2 Terms and definitions.....	232
R.3 Classification .....	233
R.3.1 According to the method of construction .....	233
R.3.2 According to the method of automatic reclosing .....	233
R.4 Characteristics .....	233
R.4.1 Rated automatic reclosing operating residual current ( $I_{\Delta ar}$ ) .....	233
R.4.2 Maximum number of consecutive reclosing operations.....	233
R.5 Marking and instructions.....	234
R.6 Normal service, mounting and transport conditions .....	234
R.7 Design and operating requirements .....	234
R.7.1 Design requirements .....	234
R.7.2 Operating requirements.....	235
R.8 Tests .....	236
R.8.1 General conditions .....	236
R.8.2 Verification of the non-reclosing after tripping under over-current conditions .....	236
R.8.3 Verification of the non-reclosing after intentional opening .....	236
R.8.4 Verification of the automatic reclosing function after tripping on earth fault .....	237
R.8.5 Verification of mechanical endurance .....	238
R.8.6 Verification of the isolation function .....	238
R.8.7 Verification of residual short-circuit making and breaking capacity .....	239
R.8.8 Verification of the automatic reclosing function after the test sequences of Clause B.8.....	239
R.8.9 Test items for external type automatic reclosing devices.....	239
Bibliography .....	242
Figure 1 – Test arrangement (connecting cables not shown) for short-circuit tests .....	78
Figure A.1 – Over-current co-ordination between a circuit-breaker and a fuse or back-up protection by a fuse: operating characteristics .....	85
Figure A.2 – Total selectivity between two circuit-breakers.....	86
Figure A.3 – Back-up protection by a circuit-breaker – Operating characteristics.....	87
Figure A.4 – Example of test circuit for conditional short-circuit breaking capacity tests showing cable connections for a 3-pole circuit-breaker ( $C_1$ ).....	88
Figure A.5 – Example of test circuit for the verification of selectivity.....	89
Figure B.1 – Test circuit for the verification of the operating characteristic (see B.8.2) .....	113
Figure B.2 – Test circuit for the verification of the limiting value of the non-operating current under over-current conditions (see B.8.5) .....	114
Figure B.3 – Test circuit for the verification of the behaviour of CBRs classified under B.3.1.2.2 (see B.8.9) .....	115
Figure B.4 – Current ring wave 0,5 $\mu$ s/100 kHz .....	116
Figure B.5 – Example of test circuit for the verification of resistance to unwanted tripping .....	116
Figure B.6 – Surge current wave 8/20 $\mu$ s .....	117

Figure B.7 – Test circuit for the verification of resistance to unwanted tripping in case of flashover without follow-on current (B.8.6.3) ..... 117

Figure B.8 – Test circuit for the verification of the correct operation of CBRs, in the case of residual pulsating direct currents (see B.8.7.2.1, B.8.7.2.2 and B.8.7.2.3) ..... 118

Figure B.9 – Test circuit for the verification of the correct operation of CBRs, in the case of a residual pulsating direct current superimposed by a smooth direct residual current (see B.8.7.2.4) ..... 119

Figure F.1 – Representation of test current produced by back-to-back thyristors in accordance with F.4.1 ..... 131

Figure F.2 – Test circuit for immunity and emission tests in accordance with F.4.1.3, F.4.2, F.4.3, F.4.6, F.4.7.1, F.5.4 and F.6.3 – Two phase poles in series..... 132

Figure F.3 – Test circuit for immunity and emission tests in accordance with F.4.1.3, F.4.2, F.4.3, F.4.6, F.4.7.1, F.5.4 and F.6.3 – Three phase poles in series ..... 132

Figure F.4 – Test circuit for immunity and emission tests in accordance with F.4.1.3, F.4.2, F.4.3, F.4.6, F.4.7.1, F.5.4 and F.6.3 – Three-phase connection ..... 133

Figure F.5 – Test current for the verification of the influence of the current dips and interruptions in accordance with F.4.7.1 ..... 133

Figure F.6 – Circuit for electrical fast transients/bursts (EFT/B) immunity test in accordance with F.4.4 – Two phase poles in series..... 134

Figure F.7 – Circuit for electrical fast transients/bursts (EFT/B) immunity test in accordance with F.4.4 – Three phase poles in series ..... 134

Figure F.8 – Circuit for electrical fast transients/bursts (EFT/B) immunity test in accordance with F.4.4 – Three-phase connection ..... 135

Figure F.9 – Test circuit for the verification of the influence of surges in the main circuit (line-to-earth) in accordance with F.4.5 – Two phase poles in series ..... 135

Figure F.10 – Test circuit for the verification of the influence of surges in the main circuit (line-to-earth) in accordance with F.4.5 – Three phase poles in series ..... 136

Figure F.11 – Test circuit for the verification of the influence of surges in the main circuit (line-to-earth) in accordance with F.4.5 – Three-phase connection..... 136

Figure F.12 – Test circuit for the verification of the influence of current surges in the main circuit in accordance with F.4.5 – Two phase poles in series ..... 137

Figure F.13 – Test circuit for the verification of the influence of current surges in the main circuit in accordance with F.4.5 – Three phase poles in series..... 137

Figure F.14 – Test circuit for the verification of the influence of current surges in the main circuit in accordance with F.4.5 – Three-phase connection ..... 138

Figure F.15 – Temperature variation cycles at a specified rate of change in accordance with F.9.1 ..... 138

Figure F.16 – General test set-up for immunity tests ..... 139

Figure F.17 – Test set-up for the verification of immunity to radiated RF electromagnetic fields ..... 140

Figure F.18 – Test set-up for the verification of immunity to electrical fast transients/bursts (EFT/B) on power lines ..... 140

Figure F.19 – Test set-up for verification of immunity to electrical fast transients/bursts (EFT/B) on signal lines ..... 141

Figure F.20 – General test set-up for the verification of immunity to conducted disturbances induced by RF fields (common mode) ..... 141

Figure F.21 – Arrangement of connections for the verification of immunity to conducted disturbances induced by RF fields – Two phase poles in series configuration..... 142

Figure F.22 – Arrangement of connections for the verification of immunity to conducted disturbances induced by RF fields – Three phase poles in series configuration ..... 142

Figure F.23 – Arrangement of connections for the verification of immunity to conducted disturbances induced by RF fields – Three-phase configuration .....	143
Figure G.1 – Example of power loss measurement according to G.2.1 .....	145
Figure G.2 – Example of power loss measurement according to G.2.2 and G.2.3 .....	146
Figure J.1 – EUT mounted in a metallic enclosure .....	156
Figure J.2 – Test set up for the measurement of radiated RF emissions.....	157
Figure J.3 – Test set up for the verification of immunity to electrostatic discharges .....	158
Figure J.4 – Test set up for the verification of immunity to radiated RF electromagnetic fields.....	158
Figure J.5 – Test set up for the verification of immunity to electrical fast transients/bursts (EFT/B) on power lines .....	159
Figure J.6 – Test set up for the verification of immunity to electrical fast transients/bursts (EFT/B) on signal lines .....	159
Figure K.1 – Relationship between symbols and tripping characteristics.....	162
Figure K.2 – Template for characteristics of cut-off current versus prospective current from 1 kA to 200 kA .....	163
Figure K.3 – Template for characteristics of cut-off current versus prospective current from 0,01 kA to 200 kA.....	164
Figure K.4 – Template for characteristics of let-through energy versus prospective current from 1 kA to 200 kA.....	165
Figure K.5 – Template for characteristics of let-through energy versus prospective current from 0,01 kA to 200 kA .....	166
Figure K.6 – Example of the use of template to Figure K.2.....	167
Figure K.7 – Example of the use of template to Figure K.4.....	168
Figure M.1 – Test circuits for the verification of operation in the case of a steady increase of residual current .....	197
Figure M.2 – Test circuits for the verification of operation in the case of a sudden appearance of residual current (with breaking device).....	198
Figure M.3 – Test circuits for the verification of operation in the case of a sudden appearance of residual current (without breaking device).....	199
Figure M.4 – Test circuits for the verification of the limiting value of non-operating current under overcurrent conditions .....	200
Figure M.5 – Test circuits for the verification of the resistance to unwanted tripping in the case of loading of the network capacitance.....	201
Figure M.6 – Test circuit for the verification of the resistance to unwanted tripping in the case of flashover without follow-on current .....	202
Figure M.7 – Test circuits for the verification of operation in the case of a continuous rise of a residual pulsating direct current .....	203
Figure M.8 – Test circuits for the verification of operation in the case of a sudden appearance of residual pulsating direct current (without breaking device) .....	204
Figure M.9 – Test circuits for the verification of operation in the case of a sudden appearance of residual pulsating direct current (with breaking device) .....	205
Figure M.10 – Test circuits for the verification of operation in the case of a residual pulsating direct current superimposed by smooth direct current of 6 mA .....	206
Figure M.11 – Test circuits for the verification of operation in the case of a slowly rising residual smooth direct current .....	207
Figure M.12 – Test circuits for the verification of operation in the case of a sudden appearance of residual smooth direct current (without breaking device) .....	208
Figure M.13 – Test circuits for the verification of operation in the case of a sudden appearance of residual smooth direct current (with breaking device).....	209



Figure M.14 – Test circuits for the verification of operation in the case of a slowly rising residual current resulting from a fault in a circuit fed by a three-pulse star or a six-pulse bridge connection..... 210

Figure M.15 – Test circuits for the verification of operation in the case of a slowly rising residual current resulting from a fault in a circuit fed by a two-pulse bridge connection line-to-line..... 211

Figure M.16 – Test circuit for the verification of the behaviour of MRCDs with separate sensing means in the case of a failure of the sensor means connection ..... 212

Figure M.17 – Test circuit for the verification of the behaviour of MRCD with separate sensing means under short-circuit conditions..... 213

Figure M.18 – Test circuit for the verification of the behaviour of MRCD with integral sensing means under short-circuit conditions..... 214

Figure M.19 – Test circuit for the verification of the behaviour of terminal type MRCD under short-circuit conditions..... 215

Figure M.20 – Verification of immunity to radiated RF electromagnetic fields – Test set-up for MRCD with separate sensing means (additional to the test of Annex B) ..... 216

Figure M.21 – Verification of immunity to electrical fast transients/bursts (EFT/B) on the sensing means connection of an MRCD with separate sensing means (additional to the test of Annex B) ..... 217

Figure M.22 – Verification of immunity to conducted disturbances induced by RF fields – Test set up for MRCD with separate sensing means (additional to the test of Annex B) ..... 217

Figure R.1 – Test circuit for the verification of the automatic reclosing functions ..... 241

  

Table 1 (void)..... 26

Table 2 – Ratio  $n$  between short-circuit making capacity and short-circuit breaking capacity and related power factor (for a.c. circuit-breakers) ..... 26

Table 3 – Minimum values of rated short-time withstand current ..... 27

Table 4 (void)..... 27

Table 5 – Preferred values of the rated control supply voltage, if different from that of the main circuit ..... 27

Table 6 – Characteristics of the opening operation of inverse time-delay over-current opening releases at the reference temperature ..... 35

Table 7 – Temperature-rise limits for terminals and accessible parts ..... 36

Table 8 – Number of operating cycles..... 38

Table 9 – Overall schema of test sequences<sup>a</sup>..... 43

Table 9a – Applicability of test sequences according to the relationship between  $I_{CS}$ ,  $I_{CU}$  and  $I_{CW}$ <sup>a</sup> ..... 44

Table 9b – Applicability of tests or test sequences to 1, 2 and 4-pole circuit-breakers according to the alternative programme 1 of 8.3.1.4..... 46

Table 9c – Applicability of tests or test sequences to 1, 2 and 3-pole circuit-breakers according to the alternative programme 2 of 8.3.1.4..... 47

Table 10 – Number of samples for test (1 of 2)..... 50

Table 11 – Values of power factors and time constants corresponding to test currents ..... 52

Table 12 – Test circuit characteristics for overload performance ..... 64

Table B.1 – Operating characteristic for non-time-delay type..... 95

Table B.2 – Operating characteristic for time-delay type having a limiting non-actuating time of 0,06 s ..... 96

Table B.3 – Requirements for CBRs functionally dependent on line voltage..... 100

Table B.4 – Additional test sequences ..... 102

Table B.5 – Tripping current range for CBRs in case of an earth fault comprising a d.c. component .....	107
Table F.1 – Test parameters for current dips and interruptions .....	128
Table J.1 – EMC – Immunity tests .....	151
Table J.2 – Reference data for immunity test specifications .....	152
Table J.3 – EMC – Emission tests .....	155
Table J.4 – Reference data for emission test specifications .....	155
Table M.1 – Product information .....	180
Table M.2 – Requirements for MRCDs with voltage source .....	182
Table M.3 – Test sequences .....	184
Table P.1 – Rated impulse withstand levels for PV circuit-breakers .....	225
Table P.2 – Number of operating cycles .....	227
Table R.1 – Test sequences for external type automatic re-closing devices .....	240

# INTERNATIONAL ELECTROTECHNICAL COMMISSION

---

## LOW-VOLTAGE SWITCHGEAR AND CONTROLGEAR –

### Part 2: Circuit-breakers

#### FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 60947-2 has been prepared by subcommittee 121A: Low-voltage switchgear and controlgear, of IEC technical committee 121: Switchgear and controlgear and their assemblies for low-voltage.

This fifth edition cancels and replaces the fourth edition published in 2006, Amendment 1:2009 and Amendment 2:2013. This edition constitutes a technical revision.

This edition includes the following significant additions with respect to the previous edition:

- tests for verification of selectivity in Annex A (see A.5.3);
- critical load current tests for d.c. circuit-breakers (see 8.3.9);
- new Annex P for circuit-breakers for use in photovoltaic applications;
- new Annex R for residual-current circuit-breakers with automatic reclosing functions.

The text of this standard is based on the following documents:

FDIS	Report on voting
121A/71/FDIS	121A/83/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts in the IEC 60947 series, published under the general title *Low-voltage switchgear and controlgear*, can be found on the IEC website.

This International Standard is to be used in conjunction with IEC 60947-1:2007 and its Amendment 1:2010 and Amendment 2:2014.

The provisions of the general rules dealt with in IEC 60947-1 are applicable to this standard, where specifically called for. Clauses and subclauses, tables, figures and annexes of the general rules thus applicable are identified by reference to IEC 60947-1 and its amendments when applicable, for example, 1.2.3 of IEC 60947-1:2007, Table 4 of IEC 60947-1:2007/AMD1:2010, or Annex A of IEC 60947-1:2007/AMD1:2010/AMD2:2014.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

The contents of the corrigendum of November 2016 have been included in this copy.

**IMPORTANT – The “colour inside” logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this publication using a colour printer.**

## LOW-VOLTAGE SWITCHGEAR AND CONTROLGEAR –

### Part 2: Circuit-breakers

#### 1 General

##### 1.1 Scope and object

This part of IEC 60947 series applies to circuit-breakers, the main contacts of which are intended to be connected to circuits, the rated voltage of which does not exceed 1 000 V a.c. or 1 500 V d.c.; it also contains additional requirements for integrally fused circuit-breakers.

Circuit-breakers rated above 1 000 V a.c. but not exceeding 1 500 V a.c. may also be tested to this standard.

It applies whatever the rated currents, the method of construction or the proposed applications of the circuit-breakers may be.

The requirements for circuit-breakers which are also intended to provide earth leakage protection are contained in Annex B.

The additional requirements for circuit-breakers with electronic over-current protection are contained in Annex F.

The additional requirements for circuit-breakers for IT systems are contained in Annex H.

The requirements and test methods for electromagnetic compatibility of circuit-breakers are contained in Annex J.

The requirements for circuit-breakers not fulfilling the requirements for over-current protection are contained in Annex L.

The requirements for modular residual current devices (without integral current breaking device) are contained in Annex M.

The requirements and test methods for electromagnetic compatibility of circuit-breaker auxiliaries are contained in Annex N.

The requirements and test methods for d.c. circuit-breakers for use in photovoltaic (PV) applications are contained in Annex P.

The requirements and test methods for circuit-breakers incorporating residual current protection with automatic reclosing functions are contained in Annex R.

Supplementary requirements for circuit-breakers used as direct-on-line starters are given in IEC 60947-4-1, applicable to low-voltage contactors and starters.

The requirements for circuit-breakers for the protection of wiring installations in buildings and similar applications, and designed for use by uninstructed persons, are contained in IEC 60898.

The requirements for circuit-breakers for equipment (for example electrical appliances) are contained in IEC 60934.

For certain specific applications (for example traction, rolling mills, marine service) particular or additional requirements may be necessary.

NOTE Circuit-breakers which are dealt with in this standard can be provided with devices for automatic opening under predetermined conditions other than those of over-current and undervoltage as, for example, reversal of power or current. This standard does not deal with the verification of operation under such pre-determined conditions.

The object of this standard is to state:

- a) the characteristics of circuit-breakers;
- b) the conditions with which circuit-breakers shall comply with reference to:
  - 1) operation and behaviour in normal service;
  - 2) operation and behaviour in case of overload and operation and behaviour in case of short-circuit, including co-ordination in service (selectivity and back-up protection);
  - 3) dielectric properties;
- c) tests intended for confirming that these conditions have been met and the methods to be adopted for these tests;
- d) information to be marked on or given with the apparatus.

## 1.2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60068-2-14, *Environmental testing – Part 2-14: Tests – Test N: Change of temperature*

IEC 60068-2-30, *Environmental testing – Part 2-30: Tests – Test Db: Damp heat, cyclic (12 h + 12 h cycle)*

IEC 60269-1:2006, *Low-voltage fuses – Part 1: General requirements*

IEC 60364 (all parts), *Low-voltage electrical installations*

IEC 60664-1:2007, *Insulation coordination for equipment within low-voltage systems – Part 1: Principles, requirements and tests*

IEC 60947-1:2007, *Low-voltage switchgear and controlgear – Part 1: General rules*

IEC 60947-1:2007/AMD1:2010

IEC 60947-1:2007/AMD2:2014

IEC 60947-4-1, *Low-voltage switchgear and controlgear – Part 4-1: Contactors and motor-starters – Electromechanical contactors and motor-starters*

IEC 61000-3-2, *Electromagnetic compatibility (EMC) – Part 3-2: Limits – Limits for harmonic current emissions (equipment input current  $\leq 16$  A per phase)*

IEC 61000-3-3, *Electromagnetic compatibility (EMC) – Part 3-3: Limits – Limitation of voltage changes, voltage fluctuations and flicker in public low-voltage supply systems, for equipment with rated current  $\leq 16$  A per phase and not subject to conditional connection*

IEC 61000-4-2, *Electromagnetic compatibility (EMC) – Part 4-2: Testing and measurement techniques – Electrostatic discharge immunity test*

IEC 61000-4-3:2006, *Electromagnetic compatibility (EMC) – Part 4-3: Testing and measurement techniques – Radiated, radio-frequency, electromagnetic field immunity test*  
IEC 61000-4-3:2006/AMD1:2007  
IEC 61000-4-3:2006/AMD2:2010

IEC 61000-4-4:2012, *Electromagnetic compatibility (EMC) – Part 4-4: Testing and measurement techniques – Electrical fast transient/burst immunity test*

IEC 61000-4-5:2014, *Electromagnetic compatibility (EMC) – Part 4-5: Testing and measurement techniques – Surge immunity test*

IEC 61000-4-6:2013, *Electromagnetic compatibility (EMC) – Part 4-6: Testing and measurement techniques – Immunity to conducted disturbances, induced by radio-frequency fields*

IEC 61000-4-11, *Electromagnetic compatibility (EMC) – Part 4-11: Testing and measurement techniques – Voltage dips, short interruptions and voltage variations immunity tests*

IEC 61140, *Protection against electric shock – Common aspects for installation and equipment*

IEC 62475:2010, *High-current test techniques – Definitions and requirements for test currents and measuring systems*

CISPR 11, *Industrial, scientific and medical equipment – Radio-frequency disturbance characteristics – Limits and methods of measurement*

CISPR 22, *Information technology equipment – Radio disturbance characteristics – Limits and methods of measurement*