

© Copyright SEK Svensk Elstandard. Reproduction in any form without permission is prohibited.

## Explosiv atmosfär – Del 14: Konstruktion, val och utförande av elinstallationer, inklusive kontroll före idrifttagning

*Explosive atmospheres –*

*Part 14: Electrical installation design, selection and installation of equipment, including initial inspection*

Som svensk standard gäller europastandarden EN IEC 60079-14:2024. Den svenska standarden innehåller den officiella engelska språkversionen av EN IEC 60079-14:2024.

### Nationellt förord

Europastandarden EN IEC 60079-14:2024

består av:

- **europastandardens ikraftsättningsdokument**, utarbetat inom CENELEC
- **IEC 60079-14, Sixth edition, 2024 - Explosive atmospheres – Part 14: Electrical installation design, selection and installation of equipment, including initial inspection**

utarbetad inom International Electrotechnical Commission, IEC.

Tidigare fastställd svensk standard SS-EN 60079-14, utg 4:2014 med eventuella tillägg, ändringar och rättelser gäller ej fr o m 2027-10-04.

## Standarder underlättar utvecklingen och höjer elsäkerheten

Det finns många fördelar med att ha gemensamma tekniska regler för bl a mätning, säkerhet och provning och för utförande, skötsel och dokumentation av elprodukter och elanläggningar.

Genom att utforma sådana standarder blir säkerhetsfordringar tydliga och utvecklingskostnaderna rimliga samtidigt som marknadens acceptans för produkten eller tjänsten ökar.

Många standarder inom elområdet beskriver tekniska lösningar och metoder som åstadkommer den elsäkerhet som föreskrivs av svenska myndigheter och av EU.

## SEK är Sveriges röst i standardiseringsarbetet inom elområdet

SEK Svensk Elstandard svarar för standardiseringen inom elområdet i Sverige och samordnar svensk medverkan i internationell och europeisk standardisering. SEK är en ideell organisation med frivilligt deltagande från svenska myndigheter, företag och organisationer som vill medverka till och påverka utformningen av tekniska regler inom elektrotekniken.

SEK samordnar svenska intressenters medverkan i SEKs tekniska kommittéer och stödjer svenska experters medverkan i internationella och europeiska projekt.

## Stora delar av arbetet sker internationellt

Utformningen av standarder sker i allt väsentligt i internationellt och europeiskt samarbete. SEK är svensk nationalkommitté av International Electrotechnical Commission (IEC) och Comité Européen de Normalisation Electrotechnique (CENELEC).

Standardiseringsarbetet inom SEK är organiserat i referensgrupper bestående av ett antal tekniska kommittéer som speglar hur arbetet inom IEC och CENELEC är organiserat.

Arbetet i de tekniska kommittéerna är öppet för alla svenska organisationer, företag, institutioner, myndigheter och statliga verk. Den årliga avgiften för deltagandet och intäkter från försäljning finansierar SEKs standardiseringsverksamhet och medlemsavgift till IEC och CENELEC.

## Var med och påverka!

Den som deltar i SEKs tekniska kommittéarbete har möjlighet att påverka framtida standarder och får tidig tillgång till information och dokumentation om utvecklingen inom sitt teknikområde. Arbetet och kontakterna med kollegor, kunder och konkurrenter kan gynnsamt påverka enskilda företags affärsutveckling och bidrar till deltagarnas egen kompetensutveckling.

Du som vill dra nytta av dessa möjligheter är välkommen att kontakta SEKs kansli för mer information.

## SEK Svensk Elstandard

Box 1042  
172 21 Sundbyberg  
Tel 08-444 14 00  
elstandard.se

English Version

Explosive atmospheres - Part 14: Electrical installation design,  
selection and installation of equipment, including initial  
inspection  
(IEC 60079-14:2024)

Atmosphères explosives - Partie 14: Conception des  
installations électriques, sélection et installation des  
appareils, comprenant l'inspection initiale  
(IEC 60079-14:2024)

Explosionsgefährdete Bereiche - Teil 14: Projektierung,  
Auswahl und Errichtung elektrischer Anlagen  
(IEC 60079-14:2024)

This European Standard was approved by CENELEC on 2024-10-04. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Republic of North Macedonia, Romania, Serbia, Slovakia, Slovenia, Spain, Sweden, Switzerland, Türkiye and the United Kingdom.



European Committee for Electrotechnical Standardization  
Comité Européen de Normalisation Electrotechnique  
Europäisches Komitee für Elektrotechnische Normung

CEN-CENELEC Management Centre: Rue de la Science 23, B-1040 Brussels

## **European foreword**

The text of document 31J/366/FDIS, future edition 6 of IEC 60079-14, prepared by SC 31J "Classification of hazardous areas and installation requirements" of IEC/TC 31 "Equipment for explosive atmospheres" was submitted to the IEC-CENELEC parallel vote and approved by CENELEC as EN IEC 60079-14:2024.

The following dates are fixed:

- latest date by which the document has to be implemented at national (dop) 2025-07-04 level by publication of an identical national standard or by endorsement
- latest date by which the national standards conflicting with the (dow) 2027-10-04 document have to be withdrawn

This document supersedes EN 60079-14:2014 and all of its amendments and corrigenda (if any).

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC shall not be held responsible for identifying any or all such patent rights.

Any feedback and questions on this document should be directed to the users' national committee. A complete listing of these bodies can be found on the CENELEC website.

## **Endorsement notice**

The text of the International Standard IEC 60079-14:2024 was approved by CENELEC as a European Standard without any modification.

In the official version, for Bibliography, the following notes have to be added for the standard indicated:

IEC 60034-1	NOTE Approved as EN 60034-1
IEC 60034-5	NOTE Approved as EN IEC 60034-5
IEC 60064	NOTE Approved as EN 60064
IEC 60079 (series)	NOTE Approved as EN IEC 60079 (series)
IEC 60079-1	NOTE Approved as EN 60079-1
IEC 60079-2	NOTE Approved as EN 60079-2
IEC 60079-5	NOTE Approved as EN 60079-5
IEC 60079-6	NOTE Approved as EN 60079-6
IEC 60079-10-1	NOTE Approved as EN IEC 60079-10-1
IEC 60079-10-2	NOTE Approved as EN 60079-10-2
IEC 60079-13	NOTE Approved as EN 60079-13
IEC 60079-14	NOTE Approved as EN 60079-14
IEC 60079-18	NOTE Approved as EN 60079-18
IEC 60079-26	NOTE Approved as EN IEC 60079-26
IEC 60079-29-2	NOTE Approved as EN 60079-29-2
IEC 60079-29-3	NOTE Approved as EN 60079-29-3

IEC 60079-31	NOTE Approved as EN 60079-31
IEC 60079-33	NOTE Approved as CLC/TR 60079-33
IEC 60081	NOTE Approved as EN 60081
IEC 60192	NOTE Approved as EN 60192
IEC 60195	NOTE Approved as EN 60195
IEC 60204 (series)	NOTE Approved as EN 60204 (series)
IEC 60332-1-2	NOTE Approved as EN 60332-1-2
IEC 60332-3 (series)	NOTE Approved as EN IEC 60332-3 (series)
IEC 60332-3-22	NOTE Approved as EN IEC 60332-3-22
IEC 60364 (series)	NOTE Approved as HD 60364 (series)
IEC 60364-5-51	NOTE Approved as HD 60364-5-51
IEC 60432-1	NOTE Approved as EN 60432-1
IEC 60432-2	NOTE Approved as EN 60432-2
IEC 60079-14:2024	NOTE Approved as EN IEC 60079-14:2024 (not modified)
IEC 60529	NOTE Approved as EN 60529
IEC 60626-1	NOTE Approved as EN IEC 60626-1
IEC 60654-4	NOTE Approved as EN 60654-4
IEC 60664-1	NOTE Approved as EN IEC 60664-1
IEC 60721-3 (series)	NOTE Approved as EN IEC 60721-3 (series)
IEC 60950 (series)	NOTE Approved as EN 60950 (series)
IEC 61008-1	NOTE Approved as EN 61008-1
IEC 61010-1	NOTE Approved as EN 61010-1
IEC 61439-1	NOTE Approved as EN IEC 61439-1
IEC 61558-2-6	NOTE Approved as EN 61558-2-6
IEC 61285	NOTE Approved as EN 61285
IEC 61914	NOTE Approved as EN IEC 61914
IEC 61936 (series)	NOTE Approved as EN IEC 61936 (series)
IEC 62035	NOTE Approved as EN 62035
IEC 62485-2	NOTE Approved as EN IEC 62485-2
IEC/IEEE 60079-30-1	NOTE Approved as EN 60079-30-1
IEC/IEEE 60079-30-2	NOTE Approved as EN 60079-30-2
ISO/IEC 80079-20-2	NOTE Approved as EN ISO/IEC 80079-20-2
ISO 4892-1	NOTE Approved as EN ISO 4892-1

## Annex ZA (normative)

### Normative references to international publications with their corresponding European publications

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

NOTE 1 Where an International Publication has been modified by common modifications, indicated by (mod), the relevant EN/HD applies.

NOTE 2 Up-to-date information on the latest versions of the European Standards listed in this annex is available here: [www.cenelec.eu](http://www.cenelec.eu).

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 60060-1	-	High-voltage test techniques - Part 1: General definitions and test requirements	EN 60060-1	-
IEC 60079-0	-	Explosive atmospheres - Part 0: Equipment - General requirements	EN IEC 60079-0	-
IEC 60079-1	-	Explosive atmospheres - Part 1: Equipment protection by flameproof enclosures "d"	EN 60079-1	-
IEC 60079-7	-	Explosive atmospheres - Part 7: Equipment protection by increased safety "e"	EN 60079-7	-
IEC 60079-11	-	Explosive atmospheres - Part 11: Equipment protection by intrinsic safety "i"	EN 60079-11	-
IEC 60079-15	-	Explosive atmospheres - Part 15: Equipment protection by type of protection "n"	EN IEC 60079-15	-
IEC 60079-17	-	Explosive atmospheres - Part 17: Electrical installations inspection and maintenance	EN IEC 60079-17	-
IEC 60079-19	-	Explosive atmospheres - Part 19: Equipment repair, overhaul and reclamation	EN IEC 60079-19	-
IEC 60079-25	-	Explosive atmospheres - Part 25: Intrinsically safe electrical systems	EN IEC 60079-25	-
IEC 60079-28	-	Explosive atmospheres - Part 28: Protection of equipment and transmission systems using optical radiation	EN 60079-28	-
IEC 60079-29-1	-	Explosive atmospheres - Part 29-1: Gas detectors - Performance requirements of detectors for flammable gases	EN 60079-29-1	-

IEC 60079-29-4	-	Explosive atmospheres - Part 29-4: Gas detectors - Performance requirements of open path detectors for flammable gases	EN 60079-29-4	-
IEC 60228	-	Conductors of insulated cables	EN IEC 60228	-
IEC 60245-4	-	Rubber insulated cables - Rated voltages up to and including 450/750 V - Part 4: Cords and flexible cables	-	-
IEC 60364-4-41	-	Low-voltage electrical installations - Part 4-41: Protection for safety - Protection against electric shock	HD 60364-4-41	-
IEC 61557-8	-	Electrical safety in low voltage distribution systems up to 1 000 V a.c. and 1 500 V d.c. - Equipment for testing, measuring or monitoring of protective measures - Part 8: Insulation monitoring devices for IT systems	EN 61557-8	-
IEC 62262	-	Degrees of protection provided by enclosures for electrical equipment against external mechanical impacts (IK code)	EN 62262	-
IEC 62305-3	-	Protection against lightning - Part 3: Physical damage to structures and life hazard	EN 62305-3	-
IEC/TS 60079-32-1	-	Explosive atmospheres - Part 32-1: Electrostatic hazards, guidance	CLC/TR 60079-32-1	-
IEC/TS 60079-47	-	Explosive atmospheres - Part 47: Equipment protection by 2-wire intrinsically safe ethernet concept (2-WISE)	CLC IEC/TS 60079-47-	

# INTERNATIONAL STANDARD

## NORME INTERNATIONALE

---

**Explosive atmospheres –  
Part 14: Electrical installation design, selection and installation of equipment,  
including initial inspection**

**Atmosphères explosives –  
Partie 14: Conception des installations électriques, sélection et installation des  
appareils, comprenant l'inspection initiale**

INTERNATIONAL  
ELECTROTECHNICAL  
COMMISSION

COMMISSION  
ELECTROTECHNIQUE  
INTERNATIONALE

---

ICS 29.260.20

ISBN 978-2-8322-9300-3

<p><b>Warning! Make sure that you obtained this publication from an authorized distributor.</b></p> <p><b>Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.</b></p>
--



## CONTENTS

FOREWORD.....	10
INTRODUCTION.....	16
1 Scope.....	19
2 Normative references .....	20
3 Terms and definitions .....	21
3.1 General.....	21
3.2 Hazardous areas.....	22
3.3 Flameproof enclosure .....	24
3.4 Increased safety .....	24
3.5 Intrinsic safety .....	25
3.6 Intrinsic safety parameters .....	26
3.7 Pressurization .....	26
3.8 Type of Protection "n" .....	26
3.9 Type of Protection "o" .....	27
3.10 Type of Protection "q" .....	27
3.11 Type of Protection "m" .....	27
3.12 Type of Protection "t" .....	27
3.13 Electrical supply systems .....	27
3.14 Equipment .....	28
3.16 Cable(s).....	28
4 General .....	30
4.1 General requirements .....	30
4.1.1 Zones and Equipment Protection Levels .....	30
4.1.2 Requirements for all Ex Equipment.....	31
4.1.3 Electrical ratings.....	31
4.1.4 Conditions of control for exceptional circumstances.....	31
4.2 Conditions of Use .....	32
4.2.1 General .....	32
4.2.2 Specific Conditions of Use.....	32
4.2.3 Use of Ex Components .....	32
4.3 Ignition sources that have an influence on the installation.....	33
4.3.1 General .....	33
4.3.2 Static electricity .....	33
4.3.3 Optical radiation .....	33
4.3.4 Lightning protection .....	33
4.3.5 Radio frequency received and transmitted in hazardous areas.....	33
4.3.6 RFID tags .....	34
5 Documentation .....	34
5.1 General.....	34
5.2 Site information.....	35
5.3 Ex Equipment information .....	35
5.4 Installation information.....	35
5.5 Personnel competency.....	36
6 Design.....	36
6.1 General.....	36
6.2 Protection from dangerous (incendive) sparking.....	36

6.2.1	Equipment (other than Ex Equipment) above hazardous areas .....	36
6.2.2	Wiring systems traversing a hazardous area .....	37
6.2.3	Construction materials .....	37
6.2.4	Danger from live parts .....	37
6.2.5	Danger from exposed and extraneous-conductive-parts .....	38
6.2.6	Protective equipotential bonding .....	39
6.2.7	Cathodically protected metallic parts .....	40
6.3	Electrical protection .....	41
6.4	Emergency stop .....	41
6.5	Electrical isolation .....	41
6.6	Cables .....	42
6.6.1	External surface temperature .....	42
6.6.2	Cables subjected to thermal insulation .....	42
6.6.3	Overhead wiring .....	42
6.7	Electrical machines .....	42
6.7.1	General .....	42
6.7.2	Electrical machines with Type of Protection "d" – Flameproof enclosures, "p" – Pressurized enclosures and "t" – Protection by enclosures .....	43
6.7.3	Electrical machines with Level of Protection "eb" – Increased safety .....	44
6.7.4	Electrical machines with Level of Protection "ec" and Type of Protection "nA" .....	46
6.7.5	Switching electrical machines above 1 kV AC .....	47
6.7.6	Prevention of falling bodies .....	48
6.8	Electric heating systems .....	48
6.8.1	General .....	48
6.8.2	Earth fault protection .....	48
6.8.3	Limiting temperature .....	49
6.8.4	Temperature safety device .....	49
6.9	Plugs, socket outlets and couplers .....	50
6.9.1	Specific requirements for explosive dust atmospheres .....	50
6.9.2	Location .....	50
6.10	Cells and batteries .....	51
6.10.1	Charging of secondary cells and batteries .....	51
6.10.2	Ventilation .....	51
6.11	Gas detection systems .....	51
6.12	Type of Protection "d" – Flameproof enclosures .....	51
6.13	Type of Protection "e" – Increased safety .....	51
6.13.1	Maximum dissipated power of junction boxes .....	51
6.13.2	Maximum number of conductors .....	52
6.14	Type of Protection "i" – Intrinsic safety .....	53
6.14.1	General .....	53
6.14.2	Cables .....	54
6.14.3	Verification of intrinsically safe circuits .....	54
6.14.4	Earthing of conducting screens .....	56
6.14.5	Cable armour bonding .....	57
6.14.6	Marking of cables .....	57
6.14.7	Cables carrying more than one intrinsically safe circuit .....	58
6.14.8	Types of cables carrying more than one intrinsically safe circuit and applicable fault considerations .....	58

6.14.9	Earthing of intrinsically safe circuits .....	58
6.14.10	Installations to meet the requirements of EPL Ga or EPL Da .....	60
6.14.11	Simple apparatus .....	61
6.14.12	Junction boxes .....	62
6.14.13	Plugs and sockets used for external connections .....	63
6.14.14	Special application: Combining intrinsically safe and non-intrinsically safe circuits .....	63
6.15	Type of Protection "m" – Encapsulation .....	63
6.16	Type of Protection "n" .....	63
6.16.1	General .....	63
6.16.2	Type of Protection "nR" .....	64
6.17	Type of Protection "o" – Liquid immersion (former Oil immersion) .....	64
6.18	Type of Protection "p" .....	64
6.18.1	General .....	64
6.18.2	Ducting .....	65
6.18.3	Action to be taken on failure of pressurization .....	65
6.19	Pressurized rooms and artificially ventilated rooms .....	69
6.20	Analyser houses .....	69
6.21	Type of Protection "q" – Powder filling .....	69
7	Selection .....	69
7.1	General .....	69
7.2	Assurance of conformity of Ex Equipment .....	69
7.2.1	Ex Equipment based on IEC standards .....	69
7.2.2	Ex Equipment not based on IEC standards .....	69
7.2.3	Selection of used or repaired Ex Equipment .....	70
7.3	Selection of Ex Equipment .....	70
7.3.1	Information requirements .....	70
7.3.2	External influences .....	70
7.3.3	Selection of radiating equipment .....	71
7.3.4	Selection of ultrasonic equipment .....	72
7.3.5	Selection for pollution degree .....	73
7.3.6	Selection for specific process hazards .....	73
7.3.7	Selection of Ex Equipment according to EPLs .....	74
7.3.8	Selection according to equipment grouping .....	76
7.3.9	Selection according to the ignition temperature of the gas, vapour or dust .....	77
7.3.10	Selection according to the temperature range .....	80
7.4	Selection of cables .....	80
7.4.1	General .....	80
7.4.2	Wiring systems for installation in areas requiring EPL Ga or EPL Da .....	81
7.4.3	Cables for direct entries into flameproof enclosures .....	81
7.4.4	Cables for direct entries into restricted breathing enclosures .....	81
7.4.5	Resistance to flame propagation or flame spread .....	81
7.4.6	UV or solar radiation .....	81
7.4.7	Non-flexible cables for fixed equipment .....	81
7.4.8	Flexible cables for fixed and transportable equipment (excluding intrinsic safety circuits) .....	81
7.4.9	Flexible cables for use for portable equipment .....	82
7.4.10	Cables for intrinsic safety circuits .....	82

7.4.11	Single insulated wires (excluding intrinsically safe circuits).....	82
7.4.12	Aluminium conductors.....	82
7.5	Selection of entry devices and other fittings .....	83
7.5.1	General .....	83
7.5.2	Cable entry devices .....	83
7.5.3	Adapters and Blanking Elements .....	84
7.5.4	Breathing and draining devices .....	84
7.5.5	Entry devices for fibre optic cables .....	85
7.5.6	Other entry devices .....	85
7.5.7	Cable entry device for Type of Protection "d" .....	85
7.5.8	Cable entry device for Type of Protection "nR" .....	86
7.6	Conduits .....	87
7.6.1	Group II .....	87
7.6.2	Group III .....	87
7.7	Luminaires and lamps .....	88
7.7.1	Luminaires .....	88
7.7.2	Lamps .....	88
7.8	Rotating electrical machines .....	88
8	Installation of equipment.....	88
8.1	General.....	88
8.2	Cables and wiring systems.....	88
8.2.1	Avoidance of damage .....	88
8.2.2	Equipotential bonding connections.....	89
8.2.3	Terminations.....	89
8.2.4	Penetrations in structures .....	90
8.2.5	Passage and collection of flammables .....	90
8.2.6	Group III – Accumulation of dust.....	90
8.2.7	Jointing.....	90
8.3	Entry devices and other fittings .....	90
8.3.1	General .....	90
8.3.2	Cable entry devices .....	91
8.3.3	Additional entries.....	93
8.3.4	Unused openings.....	93
8.4	Conduit systems .....	93
8.4.1	General .....	93
8.4.2	Group II .....	94
8.4.3	Group III .....	94
8.4.4	Additional requirements for flameproof sealing devices for conduit .....	95
8.5	Electrical heating systems.....	95
8.5.1	General .....	95
8.5.2	Trace heating system .....	95
8.6	Protective coating of Ex Equipment.....	95
8.7	Type of Protection "d" – Flameproof enclosures .....	96
8.7.1	General .....	96
8.7.2	Solid obstacles .....	96
8.7.3	Protection of flamepaths .....	96
8.8	Types of Protection "e" and "nA" .....	97
8.8.1	Conductor terminations.....	97

8.8.2	Combinations of terminals and conductors for general connection and junction boxes .....	97
8.9	Types of Protection "i" – Intrinsic safety .....	97
8.9.1	Earthing of conducting screens .....	97
8.9.2	Cable armour bonding .....	97
8.9.3	Installation of cables and wiring .....	98
8.10	Type of Protection "nR" .....	99
8.11	Type of Protection "o"– Liquid immersion (formerly Oil immersion).....	99
9	Initial inspection .....	99
Annex A (normative) Knowledge, skills and competencies of designers, electricians and technicians.....		100
A.1	Scope .....	100
A.2	Knowledge and skills .....	100
A.2.1	Designers .....	100
A.2.2	Electricians and technicians.....	100
A.3	Competencies .....	101
A.3.1	General .....	101
A.3.2	Designers .....	101
A.3.3	Electricians and technicians.....	101
A.4	Assessment .....	101
Annex B (informative) Safe work procedure guidelines for explosive gas atmospheres .....		102
Annex C (normative) Pressure test procedure for cables into Ex "d" enclosures.....		103
C.1	General.....	103
C.2	Test apparatus.....	103
C.3	Test method.....	103
C.4	Test report .....	104
Annex D (normative) Potential stator winding discharge hazard assessment – Ignition risk factors.....		106
Annex E (normative) Verification of intrinsically safe circuits with more than one intrinsically safe power source with linear current/voltage characteristics.....		107
E.1	General.....	107
E.2	Intrinsic safety with Level of Protection "ib" .....	107
E.3	Intrinsic safety with Level of Protection "ic" .....	107
Annex F (informative) Methods of determining the maximum system voltages and currents in intrinsically safe circuits with more than one intrinsically safe power source with linear current and voltage characteristics.....		108
F.1	Intrinsically safe circuits with linear current and voltage characteristics.....	108
F.2	Intrinsically safe circuits with non-linear current or voltage characteristics .....	109
Annex G (informative) Determination of intrinsic safety cable parameters .....		110
G.1	Measurements .....	110
G.2	Cables carrying more than one intrinsically safe circuit .....	110
G.2.1	General .....	110
G.2.2	Type A cables.....	110
G.2.3	Type B cables.....	111
G.2.4	Type C cables .....	111
G.3	FISCO .....	111
Annex H (informative) Hybrid mixtures .....		112
H.1	General.....	112
H.2	Concentration limits .....	112

H.3	Electrostatic hazard .....	112
H.4	Energy/temperature limits .....	112
H.5	Selection of equipment .....	112
H.6	Use of flameproof equipment .....	112
H.7	Installation requirements .....	112
Annex I (informative)	Transportable, portable and personal equipment .....	113
I.1	General .....	113
I.2	Transportable and portable equipment .....	113
I.3	Personal equipment .....	114
Annex J (informative)	Electrical machines operated from converters .....	115
J.1	General .....	115
J.2	Earthing, bonding and cabling .....	116
J.2.1	Objectives of earthing .....	116
J.2.2	Bonding of machines .....	116
J.2.3	Machine power cables .....	116
J.2.4	Cable terminations .....	118
J.2.5	Interruption of the shielded machine supply line .....	119
Annex K (informative)	Surge protection of an intrinsically safe circuit .....	120
K.1	General .....	120
K.2	Installation to be protected .....	120
K.3	Lightning induced surges .....	120
K.4	Preventive measures .....	120
K.5	Supporting documentation .....	121
K.6	Further protection .....	121
Annex L (informative)	Adverse environmental conditions .....	122
L.1	Climate classifications .....	122
L.2	Cables and cable entry devices .....	122
L.3	Seals and sealing materials .....	122
L.4	Storage and transportation .....	122
L.5	Low temperatures .....	122
L.5.1	General .....	122
L.5.2	Electrical machines .....	123
L.6	High humidity .....	123
L.7	Solar radiation .....	123
L.7.1	General .....	123
L.7.2	Equipment protection .....	124
L.7.3	Cables and cable entry devices .....	124
L.8	Atmospheres containing salt and chlorides .....	124
L.9	Snow conditions .....	124
L.10	Icing and winterization .....	125
L.11	Rapid cooling .....	125
Annex M (informative)	Guidance on the different duty types S1 to S10 of electrical machines .....	126
Annex N (normative)	High voltage installations with rated voltage up to 245 kV .....	127
Annex O (informative)	Inspection tables for initial inspections (from IEC 60079-17) .....	128
Annex P (informative)	Minimum degree of protection (IP Code) in accordance to Type of Protection .....	135
Annex Q (normative)	Additional requirements for simple apparatus .....	136

Q.1	Temperature classification .....	136
Q.1.1	Group II .....	136
Q.1.2	Group III .....	137
Q.2	Isolation and separation .....	137
Q.3	Enclosures and cable entry devices .....	137
Q.4	Assessment and documentation .....	138
	Bibliography .....	141
Figure 1	– Correlation between the maximum permissible surface temperature and thickness of dust layers .....	79
Figure 2	– Selection of cable entry devices .....	86
Figure C.1	– Example of a low pressure test arrangement .....	103
Figure F.1	– Series connection – Summation of voltage .....	108
Figure F.2	– Parallel connection – Summation of currents .....	109
Figure F.3	– Series and parallel connections – Summations of voltages and summations of currents .....	109
Figure J.1	– Basic structure of a converter fed drive system .....	115
Figure J.2	– Examples of shielded machine cables and connections .....	117
Figure J.3	– Cable shield connection at the machine side .....	119
Figure K.1	– Surge protection requirements of an instrument loop .....	121
Figure Q.1	– Assessment process for simple apparatus .....	138
Table 1	– Table of significant changes .....	11
Table 2	– Clauses of this document for requirements for special types of equipment .....	14
Table 3	– Clauses of this document for additional requirements for Types of Protection .....	14
Table 4	– Equipment Protection Levels (EPLs) where only zones are assigned .....	30
Table 5	– Radio frequency power thresholds .....	33
Table 6	– Radio-frequency energy thresholds .....	34
Table 7	– Requirements for the temperature safety devices .....	50
Table 8	– Example of defined terminal/conductor arrangement – Maximum number of wires in relation to the cross-section and the permissible continuous current .....	52
Table 9	– Determination of Type of Protection (with no flammable release within the enclosure) .....	64
Table 10	– Use of spark and particle barriers .....	65
Table 11	– Summary of protection requirements for enclosures without an internal source of release .....	66
Table 12	– Relationship between EPLs and Types of Protection .....	75
Table 13	– Relationship between gas/vapour or dust subdivision and equipment group .....	77
Table 14	– Relationship between gas or vapour ignition temperature and temperature class of Ex Equipment .....	78
Table 15	– Selection of cable entry devices, Type of Protection according to the enclosure Type of Protection .....	84
Table 16	– Minimum distance of obstruction from the flameproof flange joints related to the gas group of the hazardous area .....	96
Table C.1	– Example of a test report template .....	105
Table D.1	– Ignition risk factors .....	106

Table M.1 – Duty types of electrical machines .....	126
Table O.1 – Initial inspection schedule for Ex "d", Ex "e", Ex "n" and Ex "t"/"tD" installations .....	128
Table O.2 – Initial inspection schedule for Ex "i" installations.....	130
Table O.3 – Inspection schedule for Ex "p" and "pD" installations .....	131
Table O.4 – Inspection schedule for Ex "o" installations .....	132
Table P.1 – Minimum degree of protection (IP Code) in accordance with Type of Protection .....	135
Table Q.1 – Variation in maximum power dissipation with ambient temperature for Group II .....	136
Table Q.2 – Variation in maximum power dissipation with ambient temperature for Group III .....	137
Table Q.3 – Summary of requirements .....	139
Table Q.4 – Simple apparatus and junction box selection: A practical solution .....	140



## INTERNATIONAL ELECTROTECHNICAL COMMISSION

---

EXPLOSIVE ATMOSPHERES –**Part 14: Electrical installations design, selection  
and installation of equipment, including initial inspection**

## FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at <https://patents.iec.ch>. IEC shall not be held responsible for identifying any or all such patent rights.

IEC 60079-14 has been prepared by subcommittee 31J: Classification of hazardous areas and installation requirements, of IEC technical committee 31: Equipment for explosive atmospheres. It is an International Standard.

This sixth edition cancels and replaces the fifth edition published in 2013. This edition constitutes a technical revision.

Edition 6 is a major restructure and introduces a number of technical changes from the previous edition (2013). Table 1, "Table of significant changes" is provided to highlight the technical and more significant editorial changes from the previous edition. Minor editorial changes are not listed as there are too many changes to include in the "Table of significant changes".

**Table 1 – Table of significant changes**

Changes	Clause	Type		
		Minor and editorial changes	Extension	Major technical changes
List of possible ignition sources completed	Introduction	x		
Additional standard mentioned (IEC 60204 series for electrical safety of machinery)	Introduction	x		
Introduction of a new title "Electrical installation design, selection and installation of equipment, including initial inspection"	Scope			C1
New definition: certificates	3.1.4		x	
New definition: Ex Equipment	3.1.5		x	
New definition: Ex Equipment Certificates	3.1.6		x	
New definition: Equipment Protection Level	3.2.13	x		
definition: associated apparatus	3.5.2	x		
Modification definition: liquid immersion (formerly oil immersion)	3.9.1	x		
Definition equipment, portable	3.14.3	x		
Definition equipment, personal	3.14.4	x		
New definition: cables	3.16		x	
Zones and Equipment Protection Levels	4.1.1		x	
Requirements for all Ex Equipment	4.1.2		x	
Electrical ratings	4.1.3		x	
Use of Ex Components	4.1.4		x	
Static electricity (Reference to IEC TS 60079-32-1)	4.3.2	x		
RFID tags	4.3.6		B1	
Installation information (additional bullet points c) and e)	5.4		x	
TN type of system earthing	6.2.5.2	x		
Cathodically protected metallic parts	6.2.7		x	
Cables subjected to thermal insulation	6.6.2		x	
Overhead wiring	6.6.3		x	
Electrical machines with converter supply	6.7.3.4 b)		B2	
Electric heating systems	6.8		x	
Plugs, socket outlets and couplers	6.9	x		
Type of protection "e" – Increased safety	6.13	x		
Intrinsically safe circuits with only one source of power with linear characteristic	6.14.3.3	A1		
Earthing of conducting screens – Special cases	6.14.4	x		
Simple apparatus	6.14.11 Annex Q			C2
Junction boxes	6.14.12	x		
Junction boxes with non-intrinsically safe and intrinsically safe circuits	6.14.12.2	x		
Pressurized rooms	6.19	x		
Analyser houses	6.20	x		
Selection of pollution degree	7.3.5		x	
Selection of specific process hazards	7.3.6		x	

Changes	Clause	Type		
		Minor and editorial changes	Extension	Major technical changes
Selection of cables	7.4	A2		
Cables for direct entries into flameproof enclosures	7.4.3		x	
Cables for direct entries into restricted breathing enclosures	7.4.4		x	
UV or solar radiation	7.4.6		x	
Cables for intrinsic safety circuits	7.4.10		x	
Breathing and draining devices	7.5.4		x	
Entry devices for fibre optic cables	7.5.5		x	
Other entry devices	7.5.6		x	
New Flowchart: Selection of cable entry devices	7.5.7			C3
Conduits	7.6	x		
Luminaires	7.7.1	x		
Rotating electric machines	7.8	x		
New clause "General" in 8 "Installation of equipment"	8.1		x	
Equipotential bonding connections	8.2.2	x		
Penetration in structures	8.2.4	x		
Jointing	8.2.7		x	
Entry devices and other fittings	8.3	A3		
Cable entry devices	8.3.2	x		
Conduit systems	8.4	x		
Electric heating systems	8.5		x	
Protective coating of Ex Equipment	8.6		x	
Unused cores in cables	8.9.3.4	x		
Initial inspection	9		x	
Knowledge, skills and competencies of designers, electricians and technicians	Annex A	x		
New normative Annex: Pressure test for cables – test procedure	Annex C			C4
New informative Annex: Transportable, portable and personal equipment	Annex I		x	
New informative Annex: Electrical machines operated from converters	Annex J		x	
New informative Annex: Surge protection of an intrinsically safe circuit	Annex K		x	
New informative Annex: Guidance on the different duty types S1 to S10 of motors	Annex M		x	
New informative Annex: Inspection tables for initial inspections (from IEC 60079-17)	Annex O			C5
New informative Annex: Degree of protection (IP Code) in accordance to Type of Protection	Annex P		x	
New normative Annex: Simple apparatus	Annex Q			C2

NOTE 1 The technical changes referred to include the significance of technical changes in the revised IEC Standard, but they do not form an exhaustive list of all modifications from the previous edition. More guidance can be found by referring to the Redline Version of the standard.

**Explanations:****A) Definitions****Minor and editorial changes**

- clarification
- decrease of technical requirements
- minor technical change
- editorial corrections

These are changes which modify requirements in an editorial or a minor technical way. They include changes of the wording to clarify technical requirements without any technical change, or a reduction in level of existing requirement.

**Extension**

- addition of technical options

These are changes which add new or modify existing technical requirements, in a way that new options are given, but without increasing requirements for the design, selection and installation of existing installations that were fully compliant with the previous standard. Therefore, these will not have to be considered for existing installations in conformity with the preceding edition.

**Major technical changes**

- addition of technical requirements
- increase of technical requirements

These are changes to technical requirements (addition, increase of the level or removal) made in a way that an existing installation in conformity with the preceding edition will not always be able to fulfil the requirements given in the later edition.

**B) Information about the background of changes**

- A1 Clarification of the application of the 1 % rule to make users aware that the application of permissible pairs is considered first and when not available, the 1 % rule is to be applied.
- A2 The cable requirements from IEC 60079-14:2013, 9.3.2 have been changed to only include the minimum aspects removing any product requirement in this installation standard.
- A3 The application of adapters and reducers have been changed to align with product standard requirements.
- B1 The manufacturer of the RFID tag has to demonstrate and document that there is no explosion hazard.
- B2 Additionally to the use of a certified combination of an electrical machine in Type of Protection "eb" together with the converter, an electrical machine in the Type of Protection "eb" (type tested for converter supply) can be operated with an unspecified type of converter.
- C1 The title is changed to "Electrical installation design, selection and installation of equipment, including initial inspection" to ensure that all areas, including initial inspection, are mentioned in the title. The term "Installation of equipment" is replacing the word "Erection" in the title as more common wording.
- C2 The requirements for simple apparatus have been aligned with IEC 60079-11.
- C3 The flowchart is revised to include consideration of equipment groups, cable lengths and enclosures with a volume  $\leq 2\,000\text{ cm}^3$ . (Additional information can be found in the supporting document SC 31J SD 001.)

C4 The previous informative Annex C to improve details relevant to testing cables and alignment to the selection requirements in 7.5.7. (see also C3)

C5 The previous normative tables in the section "Initial inspection" are included in the informative Annex O. This allows checklists to be customized for specific installations.

All Ex Equipment and their wiring in hazardous areas are designed, selected and installed in accordance with:

- Clause 6 for design; and
- Clause 7 for selection; and
- Clause 8 for installation; and
- Subclauses given in Table 2 for specific types of equipment; and
- Subclauses given in Table 3 for additional requirements for Type of Protections.

**Table 2 – Clauses of this document for requirements for special types of equipment**

Type of equipment	Design	Selection	Installation
Cables and wiring systems	6.6	7.4	8.2
Conduits			8.4
Entry devices and other fittings		7.5	8.2.7
Luminaires and lamps		7.7	
Electrical machines	6.7	7.8	
Electrical heating systems	6.8		
Plugs and socket outlets	6.9		
RFID tags	4.3.6		
Cells and batteries	6.10		
Gas detectors and related systems	6.11		
Transportable, portable and personal equipment	Annex I		

**Table 3 – Clauses of this document for additional requirements for Types of Protection**

Type of Protection	Design	Selection	Installation
"d" – Flameproof Enclosure	6.12		8.7
"e" – Increased Safety	6.13		8.8
"i" – Intrinsic Safety	6.14		8.9
"m" – Encapsulation	6.15		
"n" – Type of Protection "n"	6.16		8.8 and 8.10
"o" – Liquid Immersion (former: oil)	6.17		8.11
"op" – Optical Radiation			
"p" – Pressurization	6.18		
Pressurized Rooms	6.19		
Analyser Houses	6.20		
"q" – Powder Filling	6.21		
"t" – Dust Protection by Enclosure			
"s" – Special Protection			

NOTE 2 Empty cells mean that additional requirements are not detailed in this document and would be included as part of manufacturer's instructions or certification documents.

The text of this International Standard is based on the following documents:

Draft	Report on voting
31J/366/FDIS	31J/367/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at [www.iec.ch/members\\_experts/refdocs](http://www.iec.ch/members_experts/refdocs). The main document types developed by IEC are described in greater detail at [www.iec.ch/publications](http://www.iec.ch/publications).

A list of all parts in the IEC 60079 series, published under the general title *Explosive atmospheres*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under [webstore.iec.ch](http://webstore.iec.ch) in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

## INTRODUCTION

Preventive measures to reduce explosions of flammable materials are based on three principles, which are normally applied in the following order:

- 1) substitution;
- 2) control; and
- 3) mitigation.

Substitution involves, for example, replacing a flammable material by one which is either not flammable or one that is less flammable.

Control involves, for example:

- a) reducing the quantity of flammables;
- b) avoiding or minimising releases;
- c) controlling the release;
- d) preventing the formation of an explosive atmosphere;
- e) collecting and containing releases; and
- f) avoiding ignition sources.

NOTE 1 With the exception of item f), all of the above is part of the process of hazardous area classification.

Mitigation involves, for example:

- a) reducing the number of people exposed;
- b) providing measures to avoid the propagation of an explosion;
- c) providing explosion pressure relief;
- d) providing explosion pressure suppression; and
- e) providing suitable personal protective equipment.

NOTE 2 The above items are part of consequence management when considering hazards.

Once the principles of substitution and control (items a) to e)) have been applied, the remaining hazardous areas should be classified into zones according to the likelihood of an explosive atmosphere being present (see IEC 60079-10-1 or IEC 60079-10-2). Such classification, which may be used in conjunction with an assessment of the consequences of an ignition, allows Equipment Protection Levels (EPL) to be determined and hence appropriate Types of Protection to be specified for each location.

For an explosion to occur, an explosive atmosphere and a source of ignition such as an electrical fault, high process temperature or open flames need to co-exist. This document only deals with the recommended protective measures required to reduce to an acceptable level, the likelihood that the electrical installation could become a source of ignition. By careful design of the electrical installation, it is frequently possible to locate much of the equipment in less hazardous or non-hazardous areas.

When Ex Equipment is installed in areas where explosive concentrations and quantities of flammable gases, vapours or dusts could be present in the atmosphere, protective measures are applied to reduce the likelihood of explosion due to ignition either in normal operation or under specified fault conditions.

In general, possible ignition sources are:

- Hot surfaces;
- Flames and hot gases (including hot particles);
- Mechanically generated impact, friction and abrasion;
- Electrical equipment and components;
- Stray electric currents, cathodic corrosion protection;
- Static electricity;
- Lightning;
- Radio frequency (RF) electromagnetic waves from  $10^4$  Hz to  $3 \times 10^{11}$  Hz;
- Electromagnetic waves from  $3 \times 10^{11}$  Hz to  $3 \times 10^{15}$  Hz (optical radiation);
- Ionizing radiation;
- Ultrasonic waves;
- Adiabatic compression and shock; and
- Exothermic reactions, including self-ignition of dust.

The focus of this document is the electrical installation, which is designed to reduce potential ignition sources from causing a fire or explosion including, for example, electrical arcs and sparks, static electricity, effects of lightning and hot surfaces caused by transformation of electrical energy to heat energy or caused by friction of moving parts of electrical equipment.

Many types of dust that are generated, processed, handled and stored, are combustible. When ignited they can burn rapidly and with considerable explosive force if mixed with air in the appropriate proportions. It is often necessary to use Ex Equipment in locations where such materials are present, and suitable precautions should therefore be taken to ensure that all such equipment is adequately protected so as to reduce the likelihood of ignition of the external explosive atmosphere.

Combustible dust can be ignited by equipment in ways including, but not limited to, the following:

- by surfaces of the equipment that are above the minimum ignition temperature of the dust concerned. The temperature at which a type of dust ignites is a function of the properties of the dust, whether the dust is in a cloud or layer, the thickness of the layer and the geometry of the heat source; or
- by arcing or sparking of electrical parts such as switches, contacts, commutators, brushes, or the like; or
- by discharge of an accumulated electrostatic charge; or
- by radiated energy (for example electromagnetic radiation); or
- by mechanical sparking or frictional sparking associated with the equipment.

In order to avoid dust ignition hazards it is important that:

- the temperature of surfaces on which dust can be deposited, or which would be in contact with a dust cloud, is kept below the temperature limitation specified in this document; and
- any electrical sparking parts, or parts having a temperature above the temperature limit specified in this document:
  - i) are contained in an enclosure which adequately prevents the ingress of dust, or
  - ii) the energy of electrical circuits is limited so as to avoid arcs, sparks or temperatures capable of igniting dust; and
- any other ignition sources are avoided.



Several Types of Protection are available for Ex Equipment in hazardous areas (see IEC 60079-0). This document provides the specific requirements for the design of electrical systems, selection, installation and the required initial inspection of electrical Ex Equipment in hazardous areas including requirements for documentation and personnel competency. This document is also based on manufacturer's instructions being followed. On-going inspection, maintenance and repair aspects also play an important role in control of hazardous area installations and the user's attention is drawn to IEC 60079-17, IEC 60079-19 and manufacturer's instructions for further information concerning these aspects.

This part of IEC 60079 is supplementary to other relevant IEC standards, for example the IEC 60364 series as regards electrical installation requirements or IEC 60204 series for electrical safety of machinery. This part also refers to IEC 60079-0 and its associated standards for the construction, testing and marking requirements of suitable electrical Ex Equipment.

In any industrial installation, there can be numerous sources of ignition apart from those associated with electrical Ex Equipment. Precautions are necessary to ensure safety from other possible ignition sources, but guidance on this aspect is outside the scope of this document.

## EXPLOSIVE ATMOSPHERES –

### Part 14: Electrical installations design, selection and installation of equipment, including initial inspection

#### 1 Scope

This part of IEC 60079 contains the specific requirements for the design of electrical systems, selection, installation and the required initial inspection of electrical installations of Ex Equipment in, or associated with, explosive atmospheres including requirements for documentation and personnel competency.

These requirements are in addition to the requirements for installations in non-hazardous areas.

NOTE 1 For voltages up to 1 000 V AC or 1 500 V DC requirements of this document are based on installation requirements in the IEC 60364 series and for higher voltages in the IEC 61936 series, but other relevant national requirements can apply. For offshore, the IEC 61892 series is applicable.

NOTE 2 Maximum voltages are limited by specific Types of Protection according to other parts of the IEC 60079 series and will be given in the documentation for the Ex Equipment.

This document applies to all electrical Ex Equipment including fixed, transportable, portable and personal, and installations, permanent or temporary.

NOTE 3 Guidance on transportable, portable or personal equipment can be found in Annex I and IEC TS 60079-48.

This document does not apply to:

- electrical installations in mines susceptible to firedamp;

NOTE 4 This document might apply to electrical installations in mines where explosive gas atmospheres other than firedamp can be formed and to electrical installations in the surface installation of mines.

- inherently explosive situations and dust from explosives or pyrophoric substances (for example explosives manufacturing and processing);
- rooms used for medical purposes;
- electrical installations in areas where the hazard is due to flammable mist; and
- installation of non-electrical Ex Equipment (unless being part of an equipment assembly according IEC TS 60079-46).

NOTE 5 Additional guidance on the requirements for hazards due to hybrid mixtures of dust or flyings and flammable gas or vapour is provided in Annex H.

NOTE 6 The use of portable tools having an Ex Equipment certificate might introduce an ignition source which is beyond the scope of this document, for example: a drill which could create a high temperature at the work piece.

No account is taken in this document of the toxic hazards that are associated with flammable gases, liquids and dusts in concentrations that are usually very much less than the lower flammable limit. In locations where personnel could be exposed to potentially toxic concentrations of flammable material, appropriate precautions are necessary. Such precautions are outside the scope of this document.

## 2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60060-1, *High-voltage test techniques – Part 1: General definitions and test requirements*

IEC 60079-0, *Explosive atmospheres – Part 0: Equipment – General requirements*

IEC 60079-1, *Explosive atmospheres – Part 1: Equipment protection by flameproof enclosures "d"*

IEC 60079-7, *Explosive atmospheres – Part 7: Equipment protection by increased safety "e"*

IEC 60079-11, *Explosive atmospheres – Part 11: Equipment protection by intrinsic safety "i"*

IEC 60079-15, *Explosive atmospheres – Part 15: Equipment protection by type of protection "n"*

IEC 60079-17, *Explosive atmospheres – Part 17: Electrical installations inspection and maintenance*

IEC 60079-19, *Explosive atmospheres – Part 19: Equipment repair, overhaul and reclamation*

IEC 60079-25, *Explosive atmospheres – Part 25: Intrinsically safe electrical systems*

IEC 60079-28, *Explosive atmospheres – Part 28: Protection of equipment and transmission systems using optical radiation*

IEC 60079-29-1, *Explosive atmospheres – Part 29-1: Gas detectors – Performance requirements of detectors for flammable gases*

IEC 60079-29-4, *Explosive atmospheres – Part 29-4: Gas detectors – Performance requirements of open path detectors for flammable gases*

IEC TS 60079-32-1, *Explosive atmospheres – Part 32-1: Electrostatic hazards, guidance*

IEC TS 60079-47, *Explosive atmospheres – Part 47: Equipment protection by 2-wire intrinsically safe ethernet concept (2-WISE)*

IEC 60228, *Conductors of insulated cables*

IEC 60245-4, *Rubber insulated cables – Rated voltages up to and including 450/750 V – Part 4: Cords and flexible cables*

IEC 60364-4-41, *Low-voltage electrical installations – Part 4-41: Protection for safety – Protection against electric shock*

IEC 61557-8, *Electrical safety in low voltage distribution systems up to 1 000 V a.c. and 1 500 V d.c. – Equipment for testing, measuring or monitoring of protective measures – Part 8: Insulation monitoring devices for IT systems*

IEC 62262, *Degrees of protection provided by enclosures for electrical equipment against external mechanical impacts (IK code)*

IEC 62305-3, *Protection against lightning – Part 3: Physical damage to structures and life hazard*