



IEC 61158-4-12

Edition 2.0 2010-08

INTERNATIONAL STANDARD



**Industrial communication networks – Fieldbus specifications –
Part 4-12: Data-link layer protocol specification – Type 12 elements**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

PRICE CODE **XG**

ICS 25.04.40; 35.100.20; 35.110

ISBN 978-2-88912-087-1

CONTENTS

FOREWORD.....	7
INTRODUCTION.....	9
1 Scope.....	10
1.1 General.....	10
1.2 Specifications.....	10
1.3 Procedures.....	10
1.4 Applicability.....	10
1.5 Conformance.....	10
2 Normative references	11
3 Terms, definitions, symbols and abbreviations.....	11
3.1 Reference model terms and definitions.....	11
3.2 Service convention terms and definitions.....	12
3.3 Common terms and definitions	13
3.4 Additional Type 12 definitions.....	13
3.5 Common symbols and abbreviations	16
3.6 Additional Type 12 symbols and abbreviations	17
3.7 Conventions	18
4 Overview of the DL-protocol	23
4.1 Operating principle	23
4.2 Topology	23
4.3 Frame processing principles.....	23
4.4 Data-link layer overview	24
4.5 Error detection overview.....	25
4.6 Node reference model	25
4.7 Operation overview	26
5 Frame structure	27
5.1 Frame coding principles	27
5.2 Data types and encoding rules	27
5.3 DLPDU structure	29
5.4 Type 12 DLPDU structure.....	32
5.5 Network variable structure.....	48
5.6 Type 12 mailbox structure	48
6 Attributes.....	50
6.1 Management	50
6.2 Statistics	66
6.3 Watchdogs	69
6.4 Slave information interface.....	72
6.5 Media independent interface (MII)	77
6.6 Fieldbus memory management unit (FMMU).....	80
6.7 Sync manager	83
6.8 Distributed clock.....	89
7 DL-user memory.....	93
7.1 Overview	93
7.2 Mailbox access type	94
7.3 Buffered access type.....	97

8	Type 12: FDL protocol state machines.....	99
8.1	Overview of slave DL state machines	99
8.2	State machine description	99
Annex A (informative)	Type 12: Additional specifications on DL-Protocol state machines	107
	Bibliography.....	141
Figure 1	Type description example	19
Figure 2	Common structure of specific fields.....	20
Figure 3	Frame structure.....	24
Figure 4	Mapping of data in a frame.....	25
Figure 5	Slave node reference model.....	26
Figure 6	Type 12 PDUs embedded in Ethernet frame.....	27
Figure 7	Type 12 PDUs embedded in UDP/IP	27
Figure 8	DL information type description	51
Figure 9	Address type description	53
Figure 10	DL control type description.....	55
Figure 11	DL status type description	57
Figure 12	Successful write sequence to DL-user control register	59
Figure 13	Successful read sequence to the DL-user status register	60
Figure 14	RX error counter type description	67
Figure 15	Lost link counter type description	68
Figure 16	Additional counter type description.....	69
Figure 17	Sync configuration type description	70
Figure 18	Watchdog divider type description.....	70
Figure 19	Sync manager watchdog type description.....	71
Figure 20	Sync manager watchdog status type description	71
Figure 21	Watchdog counter type description.....	72
Figure 22	Slave information interface access type description	72
Figure 23	Slave information interface control/status type description	74
Figure 24	Slave information interface address type description	76
Figure 25	Slave information interface data type description	77
Figure 26	MII control/status type description	78
Figure 27	MII address type description	79
Figure 28	MII data type description	80
Figure 29	FMMU mapping example	80
Figure 30	FMMU entity type description	81
Figure 31	SyncM mailbox interaction.....	84
Figure 32	SyncM buffer allocation	84
Figure 33	SyncM buffer interaction	85
Figure 34	Handling of write/read toggle with read mailbox	85
Figure 35	Sync manager channel type description	87
Figure 36	Distributed clock local time parameter type description	91
Figure 37	Successful write sequence to mailbox	94

Figure 38 – Bad write sequence to mailbox.....	95
Figure 39 – Successful read sequence to mailbox.....	95
Figure 40 – Bad read sequence to mailbox	96
Figure 41 – Successful write sequence to buffer	97
Figure 42 – Successful read sequence to buffer.....	98
Figure 43 – Structuring of the protocol machines of an slave	99
Figure 44 – Slave information interface read operation	101
Figure 45 – Slave information interface write operation.....	102
Figure 46 – Slave information interface reload operation	103
Figure 47 – Distributed clock	105
Figure 48 – Delay measurement sequence	106
Table 1 – PDU element description example.....	19
Table 2 – Example attribute description	20
Table 3 – State machine description elements	21
Table 4 – Description of state machine elements	22
Table 5 – Conventions used in state machines	22
Table 6 – Transfer Syntax for bit sequences	28
Table 7 – Transfer syntax for data type Unsignedn	28
Table 8 – Transfer syntax for data type Integern	29
Table 9 – Type 12 frame inside an Ethernet frame.....	30
Table 10 – Type 12 frame inside an UDP PDU.....	30
Table 11 – Type 12 frame structure containing Type 12 PDUs	31
Table 12 – Type 12 frame structure containing network variables	31
Table 13 – Type 12 frame structure containing mailbox	32
Table 14 – Auto increment physical read (APRD).....	32
Table 15 – Configured address physical read (FPRD).....	33
Table 16 – Broadcast read (BRD)	34
Table 17 – Logical read (LRD)	35
Table 18 – Auto Increment physical write (APWR)	37
Table 19 – Configured address physical write (FPWR).....	38
Table 20 – Broadcast write (BWR)	39
Table 21 – Logical write (LWR).....	40
Table 22 – Auto increment physical read write (APRW)	41
Table 23 – Configured address physical read write (FPRW).....	42
Table 24 – Broadcast read write (BRW)	43
Table 25 – Logical read write (LRW)	44
Table 26 – Auto increment physical read multiple write (ARMW).....	46
Table 27 – Configured address physical read multiple write (FRMW)	47
Table 28 – Network variable	48
Table 29 – Mailbox	49
Table 30 – Error Reply Service Data.....	49
Table 31 – DL information.....	52

Table 32 – Configured station address.....	54
Table 33 – DL control	55
Table 34 – DL status.....	58
Table 35 – DLS-user specific registers.....	60
Table 36 – DLS-user event	62
Table 37 – DLS-user event mask	64
Table 38 – External event	65
Table 39 – External event mask	66
Table 40 – RX error counter.....	67
Table 41 – Lost link counter	68
Table 42 – Additional counter	69
Table 43 – Watchdog divider.....	70
Table 44 – DLS-user watchdog	70
Table 45 – Sync manager channel watchdog	71
Table 46 – Sync manager watchdog Status	71
Table 47 – Watchdog counter	72
Table 48 – Slave information interface access	72
Table 49 – Slave information interface control/status	75
Table 50 – Actual slave information interface address	76
Table 51 – Actual slave information interface data	77
Table 52 – MII control/status.....	78
Table 53 – Actual MII address.....	79
Table 54 – Actual MII data	80
Table 55 – Fieldbus memory management unit (FMMU) entity	82
Table 56 – Fieldbus memory management unit (FMMU).....	83
Table 57 – Sync manager channel	87
Table 58 – Sync manager Structure	89
Table 59 – Distributed clock local time parameter	92
Table 60 – Distributed clock DLS-user parameter	93
Table A.1 – Primitives issued by DHSM to PSM	107
Table A.2 – Primitives issued by PSM to DHSM	107
Table A.3 – Parameters used with primitives exchanged between DHSM and PSM.....	107
Table A.4 – Identifier for the octets of a Ethernet frame	108
Table A.5 – DHSM state table	110
Table A.6 – DHSM function table	125
Table A.7 – Primitives issued by SYSM to DHSM.....	125
Table A.8 – Primitives issued by DHSM to SYSM.....	126
Table A.9 – Primitives issued by DL-User to SYSM.....	126
Table A.10 – Primitives issued by SYSM to DL-User.....	126
Table A.11 – Parameters used with primitives exchanged between SYSM and DHSM	126
Table A.12 – SYSM state table	128
Table A.13 – SYSM function table.....	137
Table A.14 – Primitives issued by RMSM to SYSM	137

Table A.15 – Primitives issued by SYSM to RMSM	138
Table A.16 – Parameters used with primitives exchanged between RMSM and SYSM	138
Table A.17 – RMSM state table.....	139
Table A.18 – RMSM function table	140

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**INDUSTRIAL COMMUNICATION NETWORKS –
FIELDBUS SPECIFICATIONS –****Part 4-12: Data-link layer protocol specification –
Type 12 elements**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.

International Standard IEC 61158-4-12 has been prepared by subcommittee 65C: Industrial networks, of IEC technical committee 65: Industrial-process measurement, control and automation.

This second edition cancels and replaces the first edition published in 2007. This edition constitutes a technical revision.

The main changes with respect to the previous edition are listed below:

- bug fixes and
- editorial improvements.

The text of this standard is based on the following documents:

FDIS	Report on voting
65C/605/FDIS	65C/619/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with ISO/IEC Directives, Part 2.

A list of all the parts of the IEC 61158 series, published under the general title *Industrial communication networks – Fieldbus specifications*, can be found on the IEC web site.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition, or
- amended.

NOTE The revision of this standard will be synchronized with the other parts of the IEC 61158 series.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

This part of IEC 61158 is one of a series produced to facilitate the interconnection of automation system components. It is related to other standards in the set as defined by the “three-layer” fieldbus reference model described in IEC/TR 61158-1.

The data-link protocol provides the data-link service by making use of the services available from the physical layer. The primary aim of this standard is to provide a set of rules for communication expressed in terms of the procedures to be carried out by peer data-link entities (DLEs) at the time of communication. These rules for communication are intended to provide a sound basis for development in order to serve a variety of purposes:

- a) as a guide for implementors and designers;
- b) for use in the testing and procurement of equipment;
- c) as part of an agreement for the admittance of systems into the open systems environment;
- d) as a refinement to the understanding of time-critical communications within OSI.

This standard is concerned, in particular, with the communication and interworking of sensors, effectors and other automation devices. By using this standard together with other standards positioned within the OSI or fieldbus reference models, otherwise incompatible systems may work together in any combination.

NOTE Use of some of the associated protocol types is restricted by their intellectual-property-right holders. In all cases, the commitment to limited release of intellectual-property-rights made by the holders of those rights permits a particular data-link layer protocol type to be used with physical layer and application layer protocols in Type combinations as specified explicitly in the profile parts. Use of the various protocol types in other combinations may require permission from their respective intellectual-property-right holders.

The International Electrotechnical Commission (IEC) draws attention to the fact that it is claimed that compliance with this document may involve the use of patents concerning Type 12 elements and possibly other types given as follows:

EP 1 590 927 B1	[BE] Koppler für ein Netzwerk mit Ringtopologie und ein auf Ethernet basierten Netzwerk
EP 1 789 857 B1	[BE] Datenübertragungsverfahren und automatisierungssystem zum Einsatz eines solchen Datenübertragungsverfahrens
DE 102007017835.4	[BE] Paketvermittlungsvorrichtung und lokales Kommunikationsnetz mit einer solchen Paketvermittlungsvorrichtung
EP 1 456 722 B1	[BE] Datenübertragungsverfahren, seriellcs Bussystem und Anschalteinheit für einen passiven Busteilnehmer

IEC takes no position concerning the evidence, validity and scope of these patent rights.

The holder of these patent rights has assured the IEC that he/she is willing to negotiate licences either free of charge or under reasonable and non-discriminatory terms and conditions with applicants throughout the world. In this respect, the statement of the holder of these patent rights is registered with IEC. Information may be obtained from:

[BE]: Beckhoff Automation GmbH
Eiserstraße 5
33415 Verl,
Germany

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights other than those identified above. IEC shall not be held responsible for identifying any or all such patent rights.

ISO (www.iso.org/patents) and IEC (http://www.iec.ch/tctools/patent_decl.htm) maintain on-line data bases of patents relevant to their standards. Users are encouraged to consult the data bases for the most up to date information concerning patents.

INDUSTRIAL COMMUNICATION NETWORKS – FIELDBUS SPECIFICATIONS –

Part 4-12: Data-link layer protocol specification – Type 12 elements

1 Scope

1.1 General

The data-link layer provides basic time-critical messaging communications between devices in an automation environment.

This protocol provides communication opportunities to all participating data-link entities

- a) in a synchronously-starting cyclic manner, and
- b) in a cyclic or acyclic asynchronous manner, as requested each cycle by each of those data-link entities.

Thus this protocol can be characterized as one which provides cyclic and acyclic access asynchronously but with a synchronous restart of each cycle.

1.2 Specifications

This standard specifies

- a) procedures for the transfer of data and control information from one data-link user entity to one or more user entity;
- b) the structure of the DLPDUs used for the transfer of data and control information by the protocol of this standard, and their representation as physical interface data units.

1.3 Procedures

The procedures are defined in terms of

- a) the interactions between DL-entities (DLEs) through the exchange of DLPDUs;
- b) the interactions between a DL-service (DLS) provider and a DLS-user in the same system through the exchange of DLS primitives;
- c) the interactions between a DLS-provider and the MAC services of ISO/IEC 8802-3.

1.4 Applicability

These procedures are applicable to instances of communication between systems which support time-critical communications services within the data-link layer of the OSI reference model, and which require the ability to interconnect in an open systems interconnection environment.

Profiles provide a simple multi-attribute means of summarizing an implementation's capabilities, and thus its applicability to various time-critical communications needs.

1.5 Conformance

This standard also specifies conformance requirements for systems implementing these procedures. This part of this standard does not contain tests to demonstrate compliance with such requirements.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 61158-2:2010¹, *Industrial communication networks – Fieldbus specifications – Part 2: Physical layer specification and service definition*

IEC 61158-3-12, *Industrial communication networks – Fieldbus specifications – Part 3-12: Data-link layer service definition – Type 12 elements*

IEC 61588, *Precision clock synchronization protocol for networked measurement and control system*

ISO/IEC 7498-1, *Information technology – Open Systems Interconnection – Basic Reference Model: The Basic Model*

ISO/IEC 7498-3, *Information technology – Open Systems Interconnection – Basic Reference Model: Naming and addressing*

ISO/IEC 8802-3:2000, *Information technology – Telecommunications and information exchange between systems – Local and metropolitan area networks – Specific requirements – Part 3: Carrier sense multiple access with collision detection (CSMA/CD) access method and physical layer specifications*

ISO/IEC 9899, *Programming Languages – C*

ISO/IEC 10731, *Information technology – Open Systems Interconnection – Basic Reference Model – Conventions for the definition of OSI services*

IEEE 802.1Q, *IEEE Standard for Local and metropolitan Area Networks – Virtual Bridged Local Area Networks*, available at <<http://www.ieee.org>>

IETF RFC 768, *User Datagram Protocol (UDP)*, available at <<http://www.ietf.org>>

IETF RFC 791, *Internet protocol DARPA internet program protocol specification*, available at <<http://www.ietf.org>>

¹ To be published