

© Copyright SEK. Reproduction in any form without permission is prohibited.

Elsäkerhet i elektriska starkströmsanläggningar för lågspänning – Utrustning för provning, mätning och övervakning av skyddsåtgärder – Del 12: Anordningar för mätning och övervakning av installationens egenskaper (PMD)

*Electrical safety in low voltage distribution systems up to 1000 V a.c. and 1500 V d.c. –
Equipment for testing, measuring or monitoring of protective measures –
Part 12: Performance measuring and monitoring devices (PMD)*

Som svensk standard gäller europastandarden EN 61557-12:2008. Den svenska standarden innehåller den officiella engelska språkversionen av EN 61557-12:2008.

Nationellt förord

Europastandarden EN 61557-12:2008

består av:

- **europastandardens ikraftsättningsdokument**, utarbetat inom CENELEC
- **IEC 61557-12, First edition, 2007 - Electrical safety in low voltage distribution systems up to 1000 V a.c. and 1500 V d.c. - Equipment for testing, measuring or monitoring of protective measures - Part 12: Performance measuring and monitoring devices (PMD)**

utarbetad inom International Electrotechnical Commission, IEC.

Standarden ska användas tillsammans med SS-EN 61557-1, utgåva 2, 2007.

Standarder underlättar utvecklingen och höjer elsäkerheten

Det finns många fördelar med att ha gemensamma tekniska regler för bl a säkerhet, prestanda, dokumentation, utförande och skötsel av elprodukter, elanläggningar och metoder. Genom att utforma sådana standarder blir säkerhetskraven tydliga och utvecklingskostnaderna rimliga samtidigt som marknadens acceptans för produkten eller tjänsten ökar.

Många standarder inom elområdet beskriver tekniska lösningar och metoder som åstadkommer den elsäkerhet som föreskrivs av svenska myndigheter och av EU.

SEK är Sveriges röst i standardiseringsarbetet inom elområdet

SEK Svensk Elstandard svarar för standardiseringen inom elområdet i Sverige och samordnar svensk medverkan i internationell och europeisk standardisering. SEK är en ideell organisation med frivilligt deltagande från svenska myndigheter, företag och organisationer som vill medverka till och påverka utformningen av tekniska regler inom elektrotekniken.

SEK samordnar svenska intressenters medverkan i SEKs tekniska kommittéer och stödjer svenska experters medverkan i internationella och europeiska projekt.

Stora delar av arbetet sker internationellt

Utformningen av standarder sker i allt väsentligt i internationellt och europeiskt samarbete. SEK är svensk nationalkommitté av International Electrotechnical Commission (IEC) och Comité Européen de Normalisation Electrotechnique (CENELEC).

Standardiseringsarbetet inom SEK är organiserat i referensgrupper bestående av ett antal tekniska kommittéer som speglar hur arbetet inom IEC och CENELEC är organiserat.

Arbetet i de tekniska kommittéerna är öppet för alla svenska organisationer, företag, institutioner, myndigheter och statliga verk. Den årliga avgiften för deltagandet och intäkter från försäljning finansierar SEKs standardiseringsverksamhet och medlemsavgift till IEC och CENELEC.

Var med och påverka!

Den som deltar i SEKs tekniska kommittéarbete har möjlighet att påverka framtida standarder och får tidig tillgång till information och dokumentation om utvecklingen inom sitt teknikområde. Arbetet och kontakterna med kollegor, kunder och konkurrenter kan gynnsamt påverka enskilda företags affärsutveckling och bidrar till deltagarnas egen kompetensutveckling.

Du som vill dra nytta av dessa möjligheter är välkommen att kontakta SEKs kansli för mer information.

SEK Svensk Elstandard

Box 1284
164 29 Kista
Tel 08-444 14 00
www.elstandard.se

**Electrical safety in low voltage distribution systems
up to 1 000 V a.c. and 1 500 V d.c. -
Equipment for testing, measuring or monitoring of protective measures -
Part 12: Performance measuring and monitoring devices (PMD)
(IEC 61557-12:2007)**

Sécurité électrique dans les réseaux
de distribution basse tension
de 1 000 V c.a. et 1 500 V c.c. -
Dispositifs de contrôle, de mesure ou
de surveillance de mesures de protection -
Partie 12: Dispositifs de mesure et
de surveillance des performances (PMD)
(CEI 61557-12:2007)

Elektrische Sicherheit
in Niederspannungsnetzen
bis AC 1 000 V und DC 1 500 V -
Geräte zum Prüfen, Messen oder
Überwachen von Schutzmaßnahmen -
Teil 12: Kombinierte Geräte zur Messung
und Überwachung des Betriebsverhaltens
(IEC 61557-12:2007)

This European Standard was approved by CENELEC on 2008-04-01. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the Central Secretariat or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the Central Secretariat has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Cyprus, the Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland and the United Kingdom.

CENELEC

European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

Central Secretariat: rue de Stassart 35, B - 1050 Brussels

Foreword

The text of document 85/311/FDIS, future edition 1 of IEC 61557-12, prepared by IEC TC 85, Measuring equipment for electrical and electromagnetic quantities, was submitted to the IEC-CENELEC parallel vote and was approved by CENELEC as EN 61557-12 on 2008-04-01.

This standard is to be used in conjunction with EN 61557-1:2007 (unless otherwise specified).

The following dates were fixed:

- latest date by which the EN has to be implemented
at national level by publication of an identical
national standard or by endorsement (dop) 2009-01-01
- latest date by which the national standards conflicting
with the EN have to be withdrawn (dow) 2011-04-01

This European Standard has been prepared under a mandate given to CENELEC by the European Commission and the European Free Trade Association and covers essential requirements of EC Directive 2004/108/EC. See Annex ZZ.

Annexes ZA and ZZ have been added by CENELEC.

Endorsement notice

The text of the International Standard IEC 61557-12:2007 was approved by CENELEC as a European Standard without any modification.

In the official version, for Bibliography, the following notes have to be added for the standards indicated:

IEC 60044-1	NOTE Harmonized as EN 60044-1:1999 (modified).
IEC 60044-2	NOTE Harmonized as EN 60044-2:1999 (modified).
IEC 60044-7	NOTE Harmonized as EN 60044-7:2000 (not modified).
IEC 60044-8	NOTE Harmonized as EN 60044-8:2002 (not modified).
IEC 60071-1	NOTE Harmonized as EN 60071-1:2006 (not modified).
IEC 60359	NOTE Harmonized as EN 60359:2002 (not modified).
IEC 61000-4-7	NOTE Harmonized as EN 61000-4-7:2002 (not modified).
IEC 61140	NOTE Harmonized as EN 61140:2002 (not modified).
IEC 62052-11	NOTE Harmonized as EN 62052-11:2003 (not modified).

Annex ZA (normative)

Normative references to international publications with their corresponding European publications

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

NOTE When an international publication has been modified by common modifications, indicated by (mod), the relevant EN/HD applies.


<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 60068-2-1	- ¹⁾	Environmental testing - Part 2-1: Tests - Test A: Cold	EN 60068-2-1	2007 ²⁾
IEC 60068-2-2	- ¹⁾	Environmental testing - Part 2-2: Tests - Test B: Dry heat	EN 60068-2-2	2007 ²⁾
IEC 60068-2-30	- ¹⁾	Environmental testing - Part 2-30: Tests - Test Db: Damp heat, cyclic (12 h + 12 h cycle)	EN 60068-2-30	2005 ²⁾
IEC 60364-6 (mod)	- ¹⁾	Low voltage electrical installations - Part 6: Verification	HD 60364-6	2007 ²⁾
IEC 60529	- ¹⁾	Degrees of protection provided by enclosures (IP Code)	EN 60529 + corr. May	1991 ²⁾ 1993
IEC 61000-4-5	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-5: Testing and measurement techniques - Surge immunity test	EN 61000-4-5	2006 ²⁾
IEC 61000-4-15	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-15: Testing and measurement techniques - Flickermeter - Functional and design specifications	EN 61000-4-15	1998 ²⁾
IEC 61000-4-30	2003	Electromagnetic compatibility (EMC) - Part 4-30: Testing and measurement techniques - Power quality measurement methods	EN 61000-4-30	2003
IEC 61010	Series	Safety requirements for electrical equipment for measurement, control, and laboratory use	EN 61010	Series
IEC 61010-1	2001	Safety requirements for electrical equipment for measurement, control, and laboratory use - Part 1: General requirements	EN 61010-1 + corr. June	2001 2002
IEC 61326-1	2005	Electrical equipment for measurement, control and laboratory use - EMC requirements - Part 1: General requirements	EN 61326-1	2006
IEC 61557-1	2007	Electrical safety in low voltage distribution systems up to 1 000 V a.c. and 1 500 V d.c. - Equipment for testing, measuring or monitoring of protective measures - Part 1: General requirements	EN 61557-1	2007

¹⁾ Undated reference.

²⁾ Valid edition at date of issue.

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 62053-21	2003	Electricity metering equipment (a.c.) - Particular requirements - Part 21: Static meters for active energy (classes 1 and 2)	EN 62053-21	2003
IEC 62053-22	2003	Electricity metering equipment (a.c.) - Particular requirements - Part 22: Static meters for active energy (classes 0,2 S and 0,5 S)	EN 62053-22	2003
IEC 62053-23	2003	Electricity metering equipment (a.c.) - Particular requirements - Part 23: Static meters for reactive energy (classes 2 and 3)	EN 62053-23	2003
IEC 62053-31	1998	Electricity metering equipment (a.c.) - Particular requirements - Part 31: Pulse output devices for electromechanical and electronic meters (two wires only)	EN 62053-31	1998

Annex ZZ



CONTENTS

INTRODUCTION.....	8
1 Scope.....	9
2 Normative references	10
3 Terms and definitions	11
3.1 General definitions	11
3.2 Definitions related to uncertainty and performance	12
3.3 Definitions related to electric phenomena	15
3.4 Definitions related to measurement techniques	18
3.5 Notations.....	18
3.5.1 Functions	18
3.5.2 Symbols and abbreviations.....	19
3.5.3 Indices	19
4 Requirements.....	19
4.1 General requirements.....	19
4.2 PMD general architecture	20
4.3 Classification of PMD	20
4.4 List of applicable performance classes	21
4.4.1 List of applicable function performance classes for PMD without external sensors	21
4.4.2 List of applicable system performance classes for PMD with external sensors	22
4.5 Operating and reference conditions for PMD	22
4.5.1 Reference conditions.....	22
4.5.2 Rated operating conditions	22
4.6 Start-up conditions	24
4.7 Requirements for PMD functions (except PMD-A).....	24
4.7.1 Active power (P) and active energy (E_a) measurements	24
4.7.2 Reactive power (Q_A , Q_V) and reactive energy (E_{rA} , E_{rV}) measurements	29
4.7.3 Apparent power (S_A , S_V) and apparent energy (E_{apA} , E_{apV}) measurements.....	32
4.7.4 Frequency (f) measurements	34
4.7.5 R.m.s. phase current (I) and neutral current (I_N , I_{Nc}) measurements.....	35
4.7.6 R.m.s. voltage (U) measurements.....	38
4.7.7 Power factor (PF_A , PF_V) measurements	40
4.7.8 Short term flicker (P_{St}) and long term flicker (P_{Lt}) measurements.....	40
4.7.9 Voltage dip (U_{dip}) and voltage swell (U_{SWI}) measurements	41
4.7.10 Transients overvoltage (U_{tr}) measurements	43
4.7.11 Voltage interruption (U_{int}) measurements.....	43
4.7.12 Voltage unbalance (U_{nb} , U_{nba}) measurements	44
4.7.13 Voltage harmonics (U_h) and voltage THD (THD_U and $THD-R_U$) measurements.....	45

4.7.14	Current harmonics (I_h) and current THD (THD_i and $THD-R_i$) measurements	46
4.7.15	Minimum, maximum, peak, three-phases average and demand measurements	47
4.8	Requirements for PMD-A functions	47
4.9	General mechanical requirements	48
4.9.1	Vibration requirements	48
4.9.2	IP requirements	48
4.10	Safety requirements	49
4.10.1	Clearances and creepage distances	49
4.10.2	Connection of a fixed installed PMD with a current transformer	49
4.10.3	Connection of a PMD with a high voltage sensor	49
4.10.4	Accessible parts	49
4.10.5	Hazardous live parts	50
4.11	Analog outputs	50
4.11.1	General requirements	50
4.11.2	Compliance voltage	50
4.11.3	Analog output ripple content	50
4.11.4	Analog output response time	50
4.11.5	Limiting value of the analog output signal	50
4.11.6	Pulse outputs	51
5	Marking and operating instructions	51
5.1	Marking	51
5.2	Operating and installation instructions	51
5.2.1	General characteristics	51
5.2.2	Essential characteristics	52
5.2.3	Safety characteristics	54
6	Tests	54
6.1	Type tests of PMD	54
6.1.1	Test of temperature influence	55
6.1.2	Active power	55
6.1.3	Apparent power	58
6.1.4	Power factor	58
6.1.5	Common mode voltage rejection test	58
6.1.6	Frequency	59
6.1.7	Measurement of voltage harmonics	59
6.1.8	Measurement of current harmonics	59
6.1.9	Dips and swells	60
6.1.10	Voltage interruptions	60
6.1.11	Outputs tests	60
6.1.12	Climatic tests	61
6.1.13	EMC tests	62
6.1.14	Start up tests	62
6.2	Type tests of PMD-A	62
6.3	Routine tests	62
6.3.1	Protective bonding test	62
6.3.2	Dielectric strength test	63
6.3.3	Uncertainty test	63

Annex A (informative) Definitions of electrical parameters	64
Annex B (normative) Definitions of minimum, maximum, peak and demand values	68
Annex C (informative) Intrinsic uncertainty, operating uncertainty, and overall system uncertainty.....	70
Annex D (informative) Recommended sensor classes for the different kinds of PMD.....	72
Annex E (normative) Requirements applicable to PMD and to PMD-A.....	75
Bibliography.....	76
Figure 1 – PMD generic measurement chain.....	20
Figure 2 – Description of different types of PMD	21
Figure 3 – Relationship between ambient air temperature and relative humidity.....	24
Figure 4 – Waveform for odd harmonics influence test on active power measurement	55
Figure 5 – Spectral content for odd harmonics influence test on active power measurement.....	56
Figure 6 – Waveform for sub-harmonics influence test on active power measurement	57
Figure 7 – Spectral content for sub-harmonics influence test on active power measurement.....	57
Figure 8 – Common mode voltage influence testing	58
Figure 9 – Waveform for harmonics influence test on frequency measurement.....	59
Figure A.1 – Arithmetic and vector apparent powers in sinusoidal situation.....	66
Figure A.2 – Geometric representation of active and reactive power	67
Figure B.1 – Thermal current demand.....	68
Figure C.1 – Different kind of uncertainties	70
Table 1 – Classification of PMD	21
Table 2 – List of applicable function performance classes for PMD without external sensors	21
Table 3 – List of applicable system performance classes for PMD with external sensors.....	22
Table 4 – Reference conditions for testing	22
Table 5 – Rated operating temperatures for portable equipment	23
Table 6 – Rated operating temperatures for fixed installed equipment	23
Table 7 – Humidity and altitude operating conditions	23
Table 8 – Intrinsic uncertainty table for active power and active energy measurement	25
Table 9 – Influence quantities for active power and active energy measurement.....	26
Table 10 – Starting current for active power and active energy measurement	29
Table 11 – Intrinsic uncertainty table for reactive power and reactive energy measurement.....	29
Table 12 – Influence quantities for reactive power and reactive energy measurement.....	30
Table 13 – Starting current for reactive energy measurement	32
Table 14 – Intrinsic uncertainty table for apparent power and apparent energy measurement	32
Table 15 – Influence quantities for apparent power and apparent energy measurement.....	33
Table 16 – Intrinsic uncertainty table for frequency measurement	34
Table 17 – Influence quantities for frequency measurement.....	34
Table 18 – Rated range of operation for phase current measurement	35
Table 19 – Rated range of operation for neutral current measurement	35

Table 20 – Intrinsic uncertainty table for phase current	36
Table 21 – Intrinsic uncertainty table for neutral current measurement.....	36
Table 22 – Intrinsic uncertainty table for neutral current calculation	36
Table 23 – Influence quantities for phase current and neutral current measurement	37
Table 24 – Rated range of operation for r.m.s. voltage measurement.....	38
Table 25 – Intrinsic uncertainty table for r.m.s. voltage measurement	38
Table 26 – Influence quantities for r.m.s. voltage measurement	39
Table 27 – Intrinsic uncertainty table for power factor measurement	40
Table 28 – Intrinsic uncertainty table for flicker measurement	40
Table 29 – Rated range of operation for voltage dips and swells measurement.....	41
Table 30 – Intrinsic uncertainty table for voltage dips and swells measurement	41
Table 31 – Influence quantities for dips and swells measurement	42
Table 32 – Intrinsic uncertainty table for transient overvoltage measurement.....	43
Table 33 – Intrinsic uncertainty table for voltage interruption measurement	44
Table 34 – Intrinsic uncertainty table for voltage unbalance measurement	44
Table 35 – Rated range of operation for voltage harmonics measurement	45
Table 36 – Intrinsic uncertainty table for voltage harmonics measurement	45
Table 37 – Intrinsic uncertainty table for voltage THD_U or $THD-R_U$ measurement	45
Table 38 – Rated range of operation for current harmonics measurement.....	46
Table 39 – Intrinsic uncertainty table for current harmonics measurement	46
Table 40 – Intrinsic uncertainty table for current THD_I and $THD-R_I$ measurement	47
Table 41 – Complementary characteristics of PMD-A.....	48
Table 42 – Minimum IP requirements for PMD	49
Table 43 – PMD specification form.....	52
Table 44 – Characteristics specification template.....	53
Table 45 – Characteristics specification template.....	54
Table A.1 – Symbols definition.....	64
Table A.2 – Calculation definitions of electrical parameters, for 3 phase unbalanced system with neutral.....	65
Table D.1 – PMD SD associated to current sensor or PMD DS associated to voltage sensor	72
Table D.2 – PMD SS with Current Sensor and Voltage Sensor association	73
Table D.3 – Range of applicable performance classes for PMD without its associated external sensors	74
Table D.4 – Range of applicable performance classes when calculating performance class of PMD with its associated external sensors	74
Table D.5 – List of functions affected by uncertainty of external sensors.....	74
Table E.1 – Requirements applicable to PMD and to PMD-A.....	75

INTRODUCTION

As a complement to protection measures, it becomes more and more necessary to measure different electrical parameters, in order to monitor the required performances in energy distribution systems due to:

- installation standards evolutions, for instance over current detection is now a new requirement for the neutral conductor due to harmonic content;
- technological evolutions (electronic loads, electronic measuring methods, etc.);
- end-users needs (cost saving, compliance with aspects of building regulations, etc..);
- safety and continuity of service;
- sustainable development requirements where energy measurement for instance is recognised as an essential element of energy management, part of the overall drive to reduce carbon emissions and to improve the commercial efficiency of manufacturing, commercial organisations and public services.

The devices on the current market have different characteristics, which need a common system of references. Therefore there is a need for a new standard in order to facilitate the choices of the end-users in terms of performance, safety, interpretation of the indications, etc. This standard provides a basis by which such devices can be specified and described, and their performance evaluated.

**ELECTRICAL SAFETY IN LOW VOLTAGE DISTRIBUTION SYSTEMS
UP TO 1 000 V a.c. AND 1 500 V d.c. –
EQUIPMENT FOR TESTING, MEASURING OR MONITORING
OF PROTECTIVE MEASURES –**

Part 12: Performance measuring and monitoring devices (PMD)

1 Scope

This part of IEC 61557 specifies requirements for combined performance measuring and monitoring devices that measure and monitor the electrical parameters within electrical distribution systems. These requirements also define the performance, in single and three-phase a.c. or d.c. systems having rated voltages up to 1 000 V a.c. or up to 1 500 V d.c.

These devices are fixed installed or portable. They are intended to be used indoors and/or outdoors. This standard is not applicable for:

- electricity metering equipment that complies with IEC 62053-21, IEC 62053-22 and IEC 62053-23. Nevertheless, uncertainties defined in this standard for active and reactive energy measurement are derived from those defined in the IEC 62053 standards series.
- simple remote relays or simple monitoring relays.

This standard is intended to be used in conjunction with IEC 61557-1 (unless otherwise specified), which specifies the general requirements for measuring and monitoring equipment, as required in IEC 60364-6.

The standard does not include the measurement and monitoring of electrical parameters defined in Parts 2 to 9 of IEC 61557 or in IEC 62020.

Combined performance measuring and monitoring devices (PMD), as defined in this standard, give additional safety information, which aids the verification of the installation and enhances the performance of the distribution systems. For instance, those devices help to check if the level of harmonics is still compliant with the wiring systems as required in IEC 60364-5-52.

The combined performance measuring and monitoring devices (PMD) for electrical parameters described in this standard are used for general industrial and commercial applications. A PMD-A is a specific PMD complying with requirements of IEC 61000-4-30 class A, which may be used in "power quality assessment" applications.

NOTE 1 Generally such types of devices are used in the following applications or for the following general needs:

- energy management inside the installation;
- monitoring and/or measurement of electrical parameters that may be required or usual;
- measurement and/or monitoring of the quality of energy.

NOTE 2 A measuring and monitoring device of electrical parameters usually consists of several functional modules. All or some of the functional modules are combined in one device. Examples of functional modules are mentioned below:

- measurement and indication of several electrical parameters simultaneously;

- energy measurement and/or monitoring, and also sometimes compliance with aspects of building regulations;
- alarms functions;
- power quality (harmonics, over/undervoltages, voltage dips and swells, etc).

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60068-2-1, *Environmental testing – Part 2-1: Tests – Test A: Cold*

IEC 60068-2-2, *Environmental testing – Part 2: Tests – Tests B: Dry heat*

IEC 60068-2-30, *Environmental testing – Part 2-30 – Tests – Test Db: Damp heat, cyclic (12 h + 12 h cycle)*

IEC 60364-6, *Low-voltage electrical installations – Part 6: Verification*

IEC 60529, *Degrees of protection provided by enclosures (IP Code)*

IEC 61000-4-5, *Electromagnetic compatibility (EMC) – Part 4-5: Testing and measurement techniques – Surge immunity test*

IEC 61000-4-15, *Electromagnetic compatibility (EMC) – Part 4: Testing and measurement techniques – Section 15: Flickermeter – Functional and design specifications*

IEC 61000-4-30:2003, *Electromagnetic compatibility (EMC) – Part 4-30: Testing and measurement techniques – Power quality measurement methods*

IEC 61010 (all parts), *Safety requirements for electrical equipment for measurement, control, and laboratory use*

IEC 61010-1:2001, *Safety requirements for electrical equipment for measurement, control, and laboratory use – Part 1: General requirements*

IEC 61326-1:2005, *Electrical equipment for measurement, control and laboratory use – EMC requirements – Part 1: General requirements*

IEC 61557-1:2007, *Electrical safety in low voltage distribution systems up to 1000 V a.c. and 1500 V d.c. – Equipment for testing, measuring or monitoring of protective measures – Part 1: General requirements*

IEC 62053-21:2003, *Electricity metering equipment (a.c.) – Particular requirements – Part 21: Static meters for active energy (classes 1 and 2)*

IEC 62053-22:2003, *Electricity metering equipment (a.c.) – Particular Requirements – Part 22: Static meters for active energy (classes 0,2 S and 0,5 S)*

IEC 62053-23:2003, *Electricity metering equipment (a.c.) – Particular requirements – Part 23: Static meters for reactive energy (classes 2 and 3)*

IEC 62053-31:1998, *Electricity metering equipment (a.c.) – Particular requirements – Part 31: Pulse output devices for electromechanical and electronic meters (two wires only)*