



IEC 61010-2-201

Edition 3.0 2024-10
EXTENDED VERSION

INTERNATIONAL STANDARD



This full version of IEC 61010-2-201:2024 includes the content of the references made to
IEC 61010-1:2010+AMD1:2016 CSV

**Safety requirements for electrical equipment for measurement, control, and laboratory use –
Part 2-201: Particular requirements for control equipment**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 17.020, 19.020, 25.040.40

ISBN 978-2-8322-9966-1

Warning! Make sure that you obtained this publication from an authorized distributor.

**SAFETY REQUIREMENTS FOR ELECTRICAL EQUIPMENT
FOR MEASUREMENT, CONTROL, AND LABORATORY USE –**

Part 1: General requirements

INTERPRETATION SHEET 1

This interpretation sheet has been prepared by IEC technical committee 66: Safety of measuring, control and laboratory equipment.

The text of this interpretation sheet is based on the following documents:

ISH	Report on voting
66/497A/ISH	66/505/RVD

Full information on the voting for the approval of this interpretation sheet can be found in the report on voting indicated in the above table.

IEC 61010-1:2010 contains a requirement in 6.8.3.1 pertaining to voltage testers for type tests as follows:

“The generator shall be able to supply a power of at least 500 VA.”

This has given rise to the following questions:

How does one interpret the requirement for voltage testers in 6.8.3.1 of IEC 61010-1:2010? Specifically, this subclause requires that “The generator shall be able to supply a power of at least 500 VA.” Does this requirement apply throughout the rated output range of the voltage tester? What is meant by the word “generator”? Is the “generator” the power supply within the voltage tester, or the voltage tester output, or something else?

Interpretation:

“A voltage tester used for type tests must be able to deliver at least 500 VA at its full-rated output voltage. It does not necessarily need to deliver 500 VA if set for lower voltages.

For example, a voltage tester that can deliver 100 mA at any test output voltage up to 5 000 V (and a current corresponding to 500 VA above 5 000 V) would meet the requirement.

The requirements for voltage testers used for routine (production line) tests are included in Annex F. The requirements of 6.8.3.1 do not apply to these voltage testers.”

CONTENTS

FOREWORD	9
INTRODUCTION to IEC 61010-1:2010	12
INTRODUCTION IEC 61010-2-201:2024	12
1 Scope and object	13
1.1 Scope	13
1.2 Object	14
1.3 Verification	15
1.4 Environmental conditions	15
2 Normative references	16
3 Terms and definitions	18
3.1 Equipment and states of equipment	18
3.2 Parts and accessories	19
3.3 Quantities	20
3.4 Tests	20
3.5 Safety terms	20
3.6 Insulation	22
4 Tests	25
4.1 General	25
4.2 Sequence of tests	26
4.3 Reference test conditions	26
4.4 Testing in SINGLE FAULT CONDITION	28
5 Marking and documentation	32
5.1 Marking	32
5.2 Warning markings	37
5.3 Durability of markings	38
5.4 Documentation	38
6 Protection against electric shock	42
6.1 General	42
6.2 Determination of ACCESSIBLE parts	42
6.3 Limit values for ACCESSIBLE parts	47
6.4 Primary means of protection	51
6.5 Additional means of protection in case of SINGLE FAULT CONDITIONS	51
6.6 Connections to external circuits	59
6.7 Insulation requirements	60
6.8 Procedure for voltage tests	75
6.9 Constructional requirements for protection against electric shock	78
6.10 Connection to the MAINS supply source and connections between parts of equipment	79
6.11 Disconnection from supply source	82
7 Protection against mechanical HAZARDS	82
7.1 General	82
7.2 Sharp edges	83
7.3 Moving parts	83
7.4 Stability	85
7.5 Provisions for lifting and carrying	86
7.6 Wall mounting	87

7.7	Expelled parts	87
8	Resistance to mechanical stresses	87
8.1	General	87
8.2	ENCLOSURE rigidity tests	89
8.3	Drop test	91
9	Protection against the spread of fire	92
9.1	General	92
9.2	Eliminating or reducing the sources of ignition within the equipment.....	94
9.3	Containment of fire within the equipment, should it occur	94
9.4	Limited-energy circuit	99
9.5	Requirements for equipment containing or using flammable liquids	100
9.6	Overcurrent protection.....	100
10	Equipment temperature limits and resistance to heat.....	101
10.1	Surface temperature limits for protection against burns	101
10.2	Temperatures of windings	102
10.3	Other temperature measurements	103
10.4	Conduct of temperature tests	103
10.5	Resistance to heat	108
11	Protection against HAZARDS from fluids and solid foreign objects	109
11.1	General	109
11.2	Cleaning.....	110
11.3	Spillage.....	110
11.4	Overflow.....	110
11.5	Battery electrolyte	111
11.6	Equipment RATED with a degree of ingress protection (IP code).....	111
11.7	Fluid pressure and leakage	112
12	Protection against radiation, including laser sources, and against sonic and ultrasonic pressure	115
12.1	General	115
12.2	Equipment producing ionizing radiation	115
12.3	Optical radiation	116
12.4	Microwave radiation	117
12.5	Sonic and ultrasonic pressure	117
12.6	Laser sources.....	118
13	Protection against liberated gases and substances, explosion and implosion	119
13.1	Poisonous and injurious gases and substances	119
13.2	Explosion and implosion	119
14	Components and subassemblies	120
14.1	General	120
14.2	Motors.....	121
14.3	Overtemperature protection devices	122
14.4	Fuse holders	122
14.5	MAINS voltage selection devices	122
14.6	MAINS transformers tested outside equipment.....	122
14.7	Printed wiring boards.....	123
14.8	Circuits used to limit TRANSIENT OVERVOLTAGES.....	123
14.101	Components bridging insulation	123
14.102	Switching devices	124

15 Protection by interlocks	127
16 HAZARDS resulting from application	127
16.1 REASONABLY FORESEEABLE MISUSE	127
16.2 Ergonomic aspects	128
17 RISK assessment	128
Annex A (normative) Measuring circuits for touch current (see 6.3).....	129
A.1 Measuring circuit for a.c. with frequencies up to 1 MHz and for d.c.....	129
A.2 Measuring circuits for sinusoidal a.c. with frequencies up to 100 Hz and for d.c.....	130
A.3 Current measuring circuit for electrical burns at high frequencies	130
A.4 Current measuring circuit for WET LOCATION	131
Annex B (normative) Standard test fingers (see 6.2).....	132
Annex C (normative) Measurement of CLEARANCES and CREEPAGE DISTANCES	134
Annex D (normative) Parts between which insulation requirements are specified (see 6.4 and 6.5.3)	138
Annex E (informative) Guideline for reduction of POLLUTION DEGREES	141
Annex F (normative) ROUTINE TESTS.....	143
F.1 General	143
F.2 Protective earth.....	143
F.3 MAINS CIRCUITS	143
F.4 Floating circuits	144
F.101 Supply circuits other than MAINS and floating circuits	144
Annex G (informative) Leakage and rupture from fluids under pressure	146
G.1 General	146
G.2 Pressures above 2 MPa and a product pressure and volume greater than 200 kPa·l.....	146
G.3 Pressures between 50 kPa and 2 MPa, and pressure times volume above 200 kPa·l.....	149
G.4 Pressures below 50 kPa, or pressure times volume below 200 kPa·l	149
G.5 Overpressure safety devices	150
Annex H (normative) Qualification of conformal coatings for protection against POLLUTION	151
H.1 General	151
H.2 Technical properties	151
H.3 Qualification of coatings	151
Annex I (informative) Line-to-neutral voltages for common MAINS supply systems	154
Annex J (informative) RISK assessment	156
J.1 RISK assessment procedure.....	156
J.2 Achieving TOLERABLE RISK.....	157
J.3 An application of RISK assessment procedures	158
Annex K (normative) Insulation requirements not covered by 6.7	159
K.1 Insulation for MAINS CIRCUITS	159
K.2 Insulation in secondary circuits.....	166
K.3 Insulation in circuits not addressed in 6.7, Clause K.1 or Clause K.2.....	173
K.4 Reduction of TRANSIENT OVERVOLTAGES by the use of overvoltage limiting devices.....	179
Annex L (informative) Index of defined terms	180
Annex AA (informative) General approach to safety for control equipment	181

AA.1 Personnel	181
AA.2 Operating access areas	182
AA.3 Service access areas	182
AA.4 Equipment types	182
Annex BB (informative) System drawing of isolation boundaries	184
BB.1 General	184
BB.2 Installation environment of OPEN control equipment	184
BB.3 Control equipment electrical safety drawing	186
BB.4 Applying IEC 61010-2-201 to the control equipment electrical safety drawing	187
BB.5 Conclusion	194
Annex CC (informative) Historical techniques for secondary circuits	195
CC.1 Secondary circuits background	195
CC.2 Secondary circuits without RISK of electrical shock	195
CC.3 Secondary circuits without RISK of spread of fire	197
Annex DD (normative) Flammability test for magnesium alloy fire ENCLOSURES or flame barriers (see 9.3.2)	199
DD.1 General	199
DD.2 Samples	199
DD.3 Mounting of samples	199
DD.4 Test flame	199
DD.5 Test procedure	199
Annex EE (informative) Information and documentation and correlation to their uses	200
Annex FF (informative) Measurement of CLEARANCES and CREEPAGE DISTANCES	202
Bibliography	204
 Figure 1 – Measurements through openings in ENCLOSURES	44
Figure 101 – Typical INTERFACE/PORT of control equipment	46
Figure 2 – Maximum duration of short-term ACCESSIBLE voltages in SINGLE FAULT CONDITION (see 6.3.2 a))	49
Figure 3 – Capacitance level versus voltage in NORMAL CONDITION and SINGLE FAULT CONDITION (see 6.3.1 c) and 6.3.2 c))	50
Figure 4 – Acceptable arrangement of protective means against electric shock	52
Figure 5 – Examples of binding screw assemblies	56
Figure 102 – Examples of insulation between separate circuits and between circuits and ACCESSIBLE conductive parts	61
Figure 6 – Distance between conductors on an interface between two layers	67
Figure 7 – Distance between adjacent conductors along an interface of two inner layers	67
Figure 8 – Distance between adjacent conductors located between the same two layers	68
Figure 9 – Detachable MAINS supply cords and connections	80
Figure 103 – Mechanical HAZARDS, with regard to PANEL MOUNTED EQUIPMENT	83
Figure 10 – Impact test using a sphere	90
Figure 11 – Flow chart to explain the requirements for protection against the spread of fire	93
Figure 104 – Spread of fire HAZARDS, with regard to PANEL MOUNTED EQUIPMENT	95
Figure 12 – Baffle	97

Figure 13 – Area of the bottom of an ENCLOSURE to be constructed as specified in 9.3.2 c) 1).....	98
Figure 105 – General temperature test environment	104
Figure 106 – Vented equipment	105
Figure 107 – Non-vented equipment	106
Figure 108 – PANEL MOUNTED EQUIPMENT extending through the wall of the end location ENCLOSURE.....	107
Figure 14 – Ball-pressure test apparatus	109
Figure 16 – Ratio between test pressure and maximum working pressure.....	114
Figure 15 – Flow chart for conformity options 14.1 a), b), c) and d).....	121
Figure A.1 – Measuring circuit for a.c. with frequencies up to 1 MHz and for d.c.	129
Figure A.2 – Measuring circuits for sinusoidal a.c. with frequencies up to 100 Hz and for d.c.	130
Figure A.3 – Current measuring circuit for electrical burns	131
Figure A.4 – Current measuring circuit for wet contact.....	131
Figure B.1 – Rigid test finger	132
Figure B.2 – Jointed test finger	133
Figure C.1 – Examples of methods of measuring CLEARANCES and CREEPAGE DISTANCES	137
Figures D.1a) to d) – Protection between HAZARDOUS LIVE circuits and ACCESSIBLE parts	139
Figures D.1e) to h) – Protection between HAZARDOUS LIVE circuits and circuits with ACCESSIBLE external TERMINALS	139
Figures D.2 a) and D.2 b) – Protection between a HAZARDOUS LIVE internal circuit and an ACCESSIBLE part which is not bonded to other ACCESSIBLE parts.....	140
Figures D.2 c) and D.2 d) – Protection between a HAZARDOUS LIVE primary circuit and circuits which have ACCESSIBLE external TERMINALS.....	140
Figure D.3 – Protection of external ACCESSIBLE TERMINALS of two HAZARDOUS LIVE circuits.....	140
Figure G.1 – Conformity verification process (see G.2)	147
Figure H.1 – Test sequence and conformity	153
Figure J.1 – Iterative process of RISK assessment and RISK reduction	156
Figure J.2 – RISK reduction	157
Figure K.1 – Distance between conductors on an interface between two layers	163
Figure K.2 – Distance between adjacent conductors along an interface of an inner layer	164
Figure K.3 – Distance between adjacent conductors located between the same two layers	165
Figure K.4 – Example of recurring peak voltage	177
Figure AA.1 – Control equipment access and safety concerns	181
Figure BB.1 – Typical system ENCLOSURE layout	185
Figure BB.2 – Simplified system schematic.....	186
Figure BB.3 – HAZARD situation of the control equipment.....	187
Figure BB.4 – Application of IEC 61010-2-201 to the control equipment safety drawing	188
Figure BB.5 – Application of 6.7.1.5 items a) and b) to the control equipment safety drawing.....	188

Figure BB.6 – Application of 6.7.1.5 items a), b), c) and d) to the control equipment safety drawing	189
Figure BB.7 – REINFORCED INSULATION.....	190
Figure BB.8 – BASIC INSULATION.....	191
Figure BB.9 – REINFORCED INSULATION, BASIC INSULATION and impedance	192
Figure BB.10 – REINFORCED INSULATION from external power supplies	193
Figure BB.11 – BASIC INSULATION from external power supplies	194
Figure EE.1 – Information and documentation for component products	200
Figure EE.2 – Information and documentation accumulation and segregation tree for an example installation	201
Figure FF.1 – Path of a component mounted to a PWB (side view)	203
Figure FF.2 – Path of a component mounted to a PWB (side view)	203
 Table 1 – Symbols	35
Table 101 – INTERFACES, PORTS AND TERMINALS considered as OPERATOR ACCESSIBLE for OPEN and ENCLOSED EQUIPMENT	45
Table 2 – Tightening torque for binding screw assemblies	56
Table 3 – Multiplication factors for CLEARANCES of equipment RATED for operation at altitudes up to 5 000 m	62
Table 4 – CLEARANCE and CREEPAGE DISTANCES for MAINS CIRCUITS of OVERVOLTAGE CATEGORY II up to 300 V	65
Table 5 – Test voltages for solid insulation between MAINS and between MAINS and secondary circuits OVERVOLTAGE CATEGORY II up to 300 V	66
Table 6 – CLEARANCES and test voltages for secondary circuits derived from MAINS CIRCUITS of OVERVOLTAGE CATEGORY II up to 300 V	70
Table 7 – CREEPAGE DISTANCES for secondary circuits	72
Table 8 – Minimum values for distance or thickness (see 6.7.3.4.2 to 6.7.3.4.4)	74
Table 9 – Distances between TERMINALS and foil.....	75
Table 10 – Correction factors according to test site altitude for test voltages for CLEARANCES	76
Table 11 – Values for physical tests on cord anchorages	81
Table 12 – Protective measures against mechanical HAZARDS to body parts.....	85
Table 15 – Impact energy levels, test height and corresponding IK codes	90
Table 16 – Acceptable perforation of the bottom of an ENCLOSURE	97
Table 17 – Limits of maximum available current.....	99
Table 18 – Values for overcurrent protection devices.....	100
Table 19 – Surface temperature limits, under NORMAL CONDITION.....	102
Table 20 – Maximum temperatures for insulation material of windings	103
Table 22 – Lamp or lamp systems considered photobiologically safe	117
Table 23 – Lamp or lamp systems considered photobiologically safe under certain conditions	117
Table 21 – Impulse voltages for OVERVOLTAGECATEGORY II	123
Table 102 – Overload and endurance test voltages.....	125
Table 103 – Overload test circuit values	126
Table 104 – Endurance test circuit values	127
Table C.1 – Dimensions of X.....	134

Table E.1 – Environmental situations	141
Table E.2 – Reduction of POLLUTION DEGREES (PD)	142
Table F.1 – Test voltages for ROUTINE TESTS of MAINS CIRCUITS	144
Table G.1 – Test pressures for equipment with pressures above 14 Mpa	149
Table H.1 – Test parameters, test conditions and test procedures	152
Table I.1 – Line-to-neutral voltages for common MAINS supply systems	154
Table J.1 – Severity of harm	158
Table J.2 – Probability of harm	158
Table J.3 – RISK category	158
Table K.1 – Multiplication factors for CLEARANCES for equipment RATED for operation at altitudes up to 5 000 m	160
Table K.2 – CLEARANCES and CREEPAGE DISTANCES for MAINS CIRCUITS of OVERVOLTAGE CATEGORY II above 300 V	160
Table K.3 – CLEARANCES and CREEPAGE DISTANCES for MAINS CIRCUITS of OVERVOLTAGE CATEGORY III	161
Table K.4 – CLEARANCES and CREEPAGE DISTANCES for MAINS CIRCUITS of OVERVOLTAGE CATEGORY IV	161
Table K.5 – Test voltages for solid insulation in MAINS CIRCUITS of OVERVOLTAGE CATEGORY II above 300 V	162
Table K.6 – Test voltages for solid insulation in MAINS CIRCUITS of OVERVOLTAGE CATEGORY III	162
Table K.7 – Test voltages for solid insulation in MAINS CIRCUITS of OVERVOLTAGE CATEGORY IV	162
Table K.8 – Test voltages for testing long-term stress of solid insulation in MAINS CIRCUITS	163
Table K.9 – Minimum values for distance or thickness of solid insulation	164
Table K.10 – CLEARANCES and test voltages for secondary circuits derived from MAINS CIRCUITS of OVERVOLTAGE CATEGORY II above 300 V	167
Table K.11 – CLEARANCES and test voltages for secondary circuits derived from MAINS CIRCUITS of OVERVOLTAGE CATEGORY III	168
Table K.12 – CLEARANCES and test voltages for secondary circuits derived from MAINS CIRCUITS of OVERVOLTAGE CATEGORY IV	169
Table K.13 – CREEPAGE DISTANCES for secondary circuits	170
Table K.14 – Minimum values for distance or thickness (see K.2.4.2 to K.2.4.4)	172
Table K.15 – CLEARANCE values for the calculation of K.3.2	175
Table K.16 – Test voltages based on CLEARANCES	176
Table K.17 – CLEARANCES for BASIC INSULATION in circuits having recurring peak voltages or WORKING VOLTAGES with frequencies above 30 kHz	178
Table CC.1 – Limits of output current and output power for inherently limited power sources	198
Table CC.2 – Limits of output current, output power and RATINGS for over-current protective devices for non-inherently limited power sources	198
Table FF.1 – Dimensions of X	202

INTERNATIONAL ELECTROTECHNICAL COMMISSION

SAFETY REQUIREMENTS FOR ELECTRICAL EQUIPMENT FOR MEASUREMENT, CONTROL, AND LABORATORY USE –

Part 2-201: Particular requirements for control equipment

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at <https://patents.iec.ch>. IEC shall not be held responsible for identifying any or all such patent rights.

This extended version (EXV) of the official IEC Standard provides the user with the full content of the Standard.

IEC 61010-2-201:2024 EXV includes the content of IEC 61010-2-201:2024, and the references made to IEC 61010-1:2010+AMD1:2016 CSV.

The specific content of IEC 61010-2-201:2024 is displayed on a blue background.

IEC 61010-2-201 has been prepared by IEC technical committee 65: Industrial-process measurement, control and automation. It is an International Standard.

This third edition cancels and replaces the second edition published in 2017. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) 1.1.1: the related equipment included in the Scope has been clarified;
- b) 4.3.2.101: the optical fibre module has been deleted;
- c) 5.4.3: equipment installation has been clarified;
- d) 6.7.1.1: revision of the figure representing insulation between separate circuits has been included;
- e) 6.7.101: the subclause relating to insulation for FIELD WIRING TERMINALS of OVERVOLTAGE CATEGORY II with a nominal voltage up to 1 000 V has been deleted;
- f) 6.7.1.101: a new subclause relating to insulation for SELV/PELV CIRCUITS has been included;
- g) 6.8.3: specification of voltage tester has been added;
- h) 6.9.3: an additional exception relating to colour coding has been included;
- i) 6.9.101: a new subclause relating to wiring for secondary circuits e.g. SELV/PELV has been included;
- j) 8.2.2.101: additional requirements for glass displays have been included;
- k) 8.3: the subclause relating to the drop test has been removed;
- l) 9.3.2: additional requirements for material of connectors and insulating material have been included;
- m) The particular requirements for non-metallic material have been clarified;
- n) Clause 11: the particular requirements for protection against HAZARDS from fluid and solid foreign objects have been removed;
- o) 12.4: an additional subclause relating to microwave radiation has been included;
- p) 14.102: the description of switching devices has been clarified;

The text of this International Standard is based on the following documents:

Draft	Report on voting
65/1049/FDIS	65/1095/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

A list of all parts in the IEC 61010 series, published under the general title *Safety requirements for electrical equipment for measurement, control, and laboratory use*, can be found on the IEC website.

This document is to be used in conjunction with IEC 61010-1:2010, and IEC 61010-1:2010/AMD1:2016.

This document supplements or modifies the corresponding clauses in IEC 61010-1 so as to convert that publication into the IEC standard: *Particular requirements for control equipment*.

Where a particular subclause of IEC 61010-1 is not mentioned in this document, that subclause applies as far as is reasonable. Where this document states "addition", "modification", "replacement", or "deletion", the relevant requirement, test specification or note in IEC 61010-1 should be adapted accordingly.

In this document,

- a) the following print types are used:
 - requirements and definitions: in roman type;
 - NOTES: in smaller roman type;
 - *conformity and tests*: in italic type;
 - terms used throughout this document which have been defined in Clause 3: SMALL ROMAN CAPITALS.
- b) subclauses, figures, tables and notes which are additional to those in IEC 61010-1 are numbered starting from 101. Additional annexes are lettered starting from AA and additional list items are lettered from aa).

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

IMPORTANT – The "colour inside" logo on the cover page of this document indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION to IEC 61010-1:2010

This International Standard specifies the safety requirements that are generally applicable to all equipment within its scope. For certain types of equipment, these requirements will be supplemented or modified by the special requirements of one, or more than one, particular part 2 of the standard which must be read in conjunction with the part 1 requirements.

INTRODUCTION IEC 61010-2-201:2024

IEC 61010-2-2xx documents are a series of standards on the safety of industrial-process measurement, control and automation equipment.

This document specifies the complete safety related requirements and related tests for control equipment (e.g. programmable controller (PLC), the components of distributed control systems (DCS), I/O devices, human machine interface (HMI)).

Safety terms of general use are defined in IEC 61010-1. More specific terms are defined in each relevant part of the IEC 61010 series.

SAFETY REQUIREMENTS FOR ELECTRICAL EQUIPMENT FOR MEASUREMENT, CONTROL, AND LABORATORY USE –

Part 2-201: Particular requirements for control equipment

1 Scope and object

1.1 Scope

1.1.1 Equipment included in scope

This part of IEC 61010 specifies safety requirements and related verification tests for control equipment or their associated peripherals, or both.

Some equipment examples are:

- programmable logic controller (PLC);
- programmable automation controller (PAC);
- distributed control systems (DCS);
- industrial PC (computers) and panel PC;
- programming and debugging tools (PADTs);
- displays and human-machine interfaces (HMI);
- any product performing the function of control equipment or their associated peripherals, or both;
- positioners; and
- control equipment which have as their intended use the command and control of machines, automated manufacturing and industrial processes, for example discrete and continuous control.

Components of the above named equipment and within the scope of this document are, for example:

- (auxiliary) stand-alone power supplies;
- peripherals such as digital and analogue I/O,
- remote-I/O;
- industrial network equipment, embedded or stand-alone (e.g. switches, routers, wireless base station).

Control equipment and their associated peripherals are intended to be used in an industrial environment. This document considers equipment designed as OPEN or ENCLOSED EQUIPMENT.

NOTE 1 Control equipment intended also for use in other environments or for other purposes (example: for use in building installations to control light or other electrical installations, or for use on cars, trains or ships) can have additional conformity requirements defined by the safety standard(s) for these applications. These requirements can involve for example: insulation, spacings and power restrictions.

NOTE 2 Computing devices and similar equipment within the scope of the IEC 60950 series or the IEC 62368 series and conforming to their requirements are considered to be suitable for use with control equipment within the scope of this document. However, some of the requirements of the IEC 60950 series for resistance to moisture and liquids are less stringent, IEC 61010-1:2010, 5.4.4, second paragraph takes this aspect into account.

Control equipment covered in this document is typically intended for use in OVERVOLTAGE CATEGORY II (IEC 60664-1) in low-voltage installations, where the RATED equipment supply voltage does not exceed 1 000 V a.c. RMS (50/60 Hz), or 1 000 V d.c..

Where control equipment is intended for installation to supply systems with OVERVOLTAGE CATEGORY III or IV, additional requirements are identified in Annex K.

The requirements of ISO/IEC Guide 51 and IEC Guide 104, as they relate to this part of IEC 61010, are incorporated herein.

1.1.2 Equipment excluded from scope

This document does not deal with aspects of the overall automated system, for example a complete assembly line. Control equipment (e.g. DCS and PLC), their application programme and their associated peripherals are considered as components (components in this context are items which perform no useful function by themselves) of an overall automated system.

Since control equipment (e.g. DCS and PLC) are component devices, safety considerations for the overall automated system including installation and application are beyond the scope of this document. Refer to the IEC 60364 series or applicable national and local regulations for electrical installation and guidelines.

1.1.3 Computing equipment

This standard applies only to computers, processors, etc. which form part of equipment within the scope of this standard or are designed for use exclusively with the equipment.

NOTE Computing devices and similar equipment within the scope of IEC 60950 and conforming to its requirements are considered to be suitable for use with equipment within the scope of this standard. However, some of the requirements of IEC 60950 for resistance to moisture and liquids are less stringent than those in this standard (see 5.4.4 second paragraph).

1.2 Object

1.2.1 Aspects included in scope

The purpose of the requirements of this document is to ensure that all HAZARDS to the OPERATOR, SERVICE PERSONNEL and the surrounding area are reduced to a tolerable level.

NOTE By using the terms "OPERATOR" and "SERVICE PERSONNEL" this document considers the perception of HAZARDS depending on training and skills. Annex AA provides a general approach in this regard.

Requirements for protection against particular types of HAZARD are given in Clauses 6 to 13, as follows:

- a) electric shock or burn (see Clause 6);
- b) mechanical HAZARDS (see Clauses 7 and 8);
- c) spread of fire from the equipment (see Clause 9);
- d) excessive temperature (see Clause 10);
- e) effects of fluids and fluid pressure (see Clause 11);
- f) effects of radiation, including lasers sources, and sonic and ultrasonic pressure (see Clause 12);
- g) liberated gases, explosion and implosion (see Clause 13).

Requirements for protection against HAZARDS arising from REASONABLY FORESEEABLE MISUSE and ergonomic factors are specified in Clause 16.

RISK assessment for HAZARDS or environments not fully covered above is specified in Clause 17.

NOTE Attention is drawn to the existence of additional requirements regarding the health and safety of labour forces.

1.2.2 Aspects excluded from scope

This document does not cover:

- a) reliability, functionality, performance, or other properties of the control equipment not related to safety;
- b) mechanical or climatic requirements for operation, transport or storage;
- c) EMC requirements (see e.g. the IEC 61326 series or IEC 61131-2);
- d) protective measures for explosive atmospheres (see e.g. the IEC 60079 series);
- e) functional safety (see e.g. the IEC 61508 series, IEC 61131-6).

1.3 Verification

This standard also specifies methods of verifying that the equipment meets the requirements of this standard, through inspection, TYPE TESTS, ROUTINE TESTS, and RISK assessment.

1.4 Environmental conditions

1.4.1 Normal environmental conditions

This standard applies to equipment designed to be safe at least under the following conditions:

- a) indoor use;
- b) altitude up to 2 000 m;
- c) temperature 5 °C to 40 °C;
- d) maximum relative humidity 80 % for temperatures up to 31 °C decreasing linearly to 50 % relative humidity at 40 °C;
- e) MAINS supply voltage fluctuations up to ±10 % of the nominal voltage;
- f) TRANSIENT OVERVOLTAGES up to the levels of OVERVOLTAGE CATEGORY II;

NOTE 1 These levels of transient overvoltage are typical for equipment supplied from the building wiring.

- g) TEMPORARY OVERVOLTAGES occurring on the MAINS supply.
- h) applicable POLLUTION DEGREE of the intended environment (POLLUTION DEGREE 2 in most cases).

NOTE 2 Manufacturers may specify more restricted environmental conditions for operation; nevertheless the equipment must be safe within these normal environmental conditions.

1.4.2 Extended environmental conditions

This standard applies to equipment designed to be safe not only in the environmental conditions specified in 1.4.1, but also in any of the following conditions as RATED by the manufacturer of the equipment:

- a) outdoor use;
- b) altitude above 2 000 m;
- c) ambient temperatures below 5 °C or above 40 °C;
- d) relative humidity above the levels specified in 1.4.1;
- e) MAINS supply voltage fluctuations exceeding ±10 % of the nominal voltage;
- f) WET LOCATION;

g) TRANSIENT OVERVOLTAGES up to the levels of OVERVOLTAGE CATEGORY III or IV (see Annex K).

2 Normative references

The following referenced documents, where applicable, are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60027 (all parts), *Letter symbols to be used in electrical technology*

IEC 60065, *Audio, video and similar electronic apparatus – Safety requirements*

IEC 60068-2-14, *Environmental testing – Part 2-14: Tests – Test N: Change of temperature*

IEC 60068-2-75, *Environmental testing – Part 2-75: Tests – Test Eh: Hammer tests*

IEC 60073, *Basic and safety principles for man-machine interface, marking and identification – Coding principles for indicators and actuators*

IEC 60227 (all parts), *Polyvinyl chloride insulated cables of rated voltages up to and including 450/750 V*

IEC 60245 (all parts), *Rubber insulated cables – Rated voltages up to and including 450/750 V*

IEC 60309 (all parts), *Plugs, socket-outlets and couplers for industrial purposes*

IEC 60320 (all parts), *Appliance couplers for household and similar general purposes*

IEC 60332-1-2, *Tests on electric and optical fibre cables under fire conditions – Part 1-2: Test for vertical flame propagation for a single insulated wire or cable – Procedure for 1 kW pre-mixed flame*

IEC 60332-2-2, *Tests on electric and optical fibre cables under fire conditions – Part 2-2: Test for vertical flame propagation for a single small insulated wire or cable – Procedure for diffusion flame*

IEC 60335-2-24, *Household and similar electrical appliances – Safety – Part 2-24: Particular requirements for refrigerating appliances, ice-cream appliances and ice-makers.*

IEC 60335-2-89, *Household and similar electrical appliances – Safety – Part 2-89: Particular requirements for commercial refrigerating appliances with an incorporated or remote refrigerant condensing unit or compressor*

IEC 60364-4-44:2007, *Low-voltage electrical installations – Part 4-44: Protection for safety – Protection against voltage disturbances and electromagnetic disturbances*
IEC 60364-4-44:2007/AMD1:2015

IEC 60384-14, *Fixed capacitors for use in electronic equipment – Part 14: Sectional specification – Fixed capacitors for electromagnetic interference suppression and connection to the supply mains*

IEC 60417, *Graphical symbols for use on equipment*

IEC 60529, *Degrees of protection provided by enclosures (IP Code)*

IEC 60664-3, *Insulation coordination for equipment within low-voltage systems – Part 3: Use of coating, potting or moulding for protection against pollution*

IEC 60695-2-11, *Fire hazard testing – Part 2-11: Glowing/hot-wire based test methods – Glow-wire flammability test method for end products (GWEPT)*

IEC 60695-11-3, *Fire hazard testing – Part 11-3: Test flames – 500 W flames – Apparatus and confirmational test methods*

IEC 60695-11-10, *Fire hazard testing – Part 11-10: Test flames – 50 W horizontal and vertical flame test methods*

IEC 60695-11-20, *Fire hazard testing – Part 11-20: Test flames – 500 W flame test method*

IEC 60799, *Electrical accessories – Cord sets and interconnection cord sets*

IEC 60825-1, *Safety of laser products – Part 1: Equipment classification and requirements*

IEC 60947-1, *Low-voltage switchgear and controlgear – Part 1: General rules*

IEC 60947-2, *Low-voltage switchgear and controlgear – Part 2: Circuit-breakers*

IEC 60947-3, *Low-voltage switchgear and controlgear – Part 3: Switches, disconnectors, switch-disconnectors and fuse-combination units*

IEC 60947-4-1, *Low-voltage switchgear and controlgear – Part 4-1: Contactors and motor-starters – Electromechanical contactors and motor-starters*

IEC 60947-4-2, *Low-voltage switchgear and controlgear – Part 4-2: Contactors and motor-starters – Semiconductor motor controllers, starters and soft-starters*

IEC 60947-5-1:2016, *Low-voltage switchgear and controlgear – Part 5-1: Control circuit devices and switching elements – Electromechanical control circuit devices*

IEC 61010-031, *Safety requirements for electrical equipment for measurement, control and laboratory use – Part 031: Safety requirements for hand-held probe assemblies for electrical measurement and test*

IEC 61010-1:2010, *Safety requirements for electrical equipment for measurement, control, and laboratory use – Part 1: General requirements*

IEC 61010-1:2010/AMD1:2016

IEC 61010-2-030, *Safety requirements for electrical equipment for measurement, control, and laboratory use – Part 2-030: Particular requirements for equipment having testing or measuring circuits*

IEC 61180 (all parts), *High-voltage test techniques for low-voltage equipment*

IEC 61180-1, *High-voltage test techniques for low-voltage equipment – Part 1: Definitions, test and procedure requirements*

IEC 61180-2, *High-voltage test techniques for low-voltage equipment – Part 2: Test equipment*

IEC 61672-1, *Electroacoustics – Sound level meters – Part 1: Specifications*

IEC 61672-2, *Electroacoustics – Sound level meters – Part 2: Pattern evaluation tests*

IEC 61810-1:2015, *Electromechanical elementary relays – Part 1: General and safety requirements*

IEC 62262, *Degrees of protection provided by enclosures for electrical equipment against external impacts (IK code)*

IEC 62471, *Photobiological safety of lamps and lamp systems*

IEC TR 62471-2, *Photobiological safety of lamps and lamp systems – Part 2: Guidance on manufacturing requirements relating to non-laser optical radiation safety*

IEC 62598, *Nuclear instrumentation – Constructional requirements and classification of radiometric gauges*

IEC Guide 104, *The preparation of safety publications and the use of basic safety publications and group safety publications*

ISO/IEC Guide 51, *Safety aspects – Guidelines for their inclusion in standards*

ISO 306:2013, *Plastics – Thermoplastic materials – Determination of Vicat softening temperature (VST)*

ISO 361, *Basic ionizing radiation symbol*

ISO 3746, *Acoustics – Determination of sound power levels of noise sources using sound pressure – Survey method using an enveloping measurement surface over a reflecting plane*

ISO 7000, *Graphical symbols for use on equipment*

ISO 9614-1, *Acoustics – Determination of sound power levels of noise sources using sound intensity – Part 1: Measurement at discrete points*

ISO 13857, *Safety of machinery – Safety distances to prevent hazard zones being reached by upper and lower limbs*

EN 378-2, *Refrigerating systems and heat pumps – Safety and environmental requirements. Design, construction, testing, marking and documentation*



IEC 61010-2-201

Edition 3.0 2024-10

INTERNATIONAL STANDARD

NORME INTERNATIONALE



**Safety requirements for electrical equipment for measurement, control, and laboratory use –
Part 2-201: Particular requirements for control equipment**

**Exigences de sécurité pour appareils électriques de mesurage, de régulation et de laboratoire –
Partie 2-201: Exigences particulières pour les équipements de commande**



CONTENTS

FOREWORD	4
INTRODUCTION	7
1 Scope and object	8
2 Normative references	10
3 Terms and definitions	10
4 Tests	13
5 Marking and documentation	14
6 Protection against electric shock	17
7 Protection against mechanical HAZARDS	31
8 Resistance to mechanical stresses	32
9 Protection against the spread of fire	34
10 Equipment temperature limits and resistance to heat	39
11 Protection against HAZARDS from fluids and solid foreign objects	45
12 Protection against radiation, including laser sources, and against sonic and ultrasonic pressure	45
13 Protection against liberated gases and substances, explosion and implosion	46
14 Components and subassemblies	46
15 Protection by interlocks	50
16 HAZARDS resulting from application	50
17 RISK assessment	50
Annexes	51
Annex E (informative) Guidelines for reduction of POLLUTION DEGREES	52
Annex F (normative) ROUTINE TESTS	54
Annex L (informative) Index of defined terms	56
Annex AA (informative) General approach to safety for control equipment	57
Annex BB (informative) System drawing of isolation boundaries	60
Annex CC (informative) Historical techniques for secondary circuits	71
Annex DD (normative) Flammability test for magnesium alloy fire ENCLOSURES or flame barriers (see 9.3.2)	75
Annex EE (informative) Information and documentation and correlation to their uses	76
Annex FF (informative) Measurement of CLEARANCES and CREEPAGE DISTANCES	78
Bibliography	80
 Figure 101 – Typical INTERFACE/PORT of control equipment	19
Figure 102 – Examples of insulation between separate circuits and between circuits and ACCESSIBLE conductive parts	24
Figure 103 – Mechanical HAZARDS, with regard to PANEL MOUNTED EQUIPMENT	31
Figure 104 – Spread of fire HAZARDS, with regard to PANEL MOUNTED EQUIPMENT	35
Figure 12 – Baffle	37
Figure 13 – Area of the bottom of an ENCLOSURE to be constructed as specified in 9.3.2 c) 1)	38
Figure 105 – General temperature test environment	41
Figure 106 – Vented equipment	42

Figure 107 – Non-vented equipment	43
Figure 108 – PANEL MOUNTED EQUIPMENT extending through the wall of the end location ENCLOSURE.....	44
Figure AA.1 – Control equipment access and safety concerns	57
Figure BB.1 – Typical system ENCLOSURE layout	60
Figure BB.2 – Simplified system schematic.....	62
Figure BB.3 – HAZARD situation of the control equipment.....	63
Figure BB.4 – Application of IEC 61010-2-201 to the control equipment safety drawing	64
Figure BB.5 – Application of 6.7.1.5 items a) and b) to the control equipment safety drawing.....	64
Figure BB.6 – Application of 6.7.1.5 items a), b), c) and d) to the control equipment safety drawing	65
Figure BB.7 – REINFORCED INSULATION.....	66
Figure BB.8 – BASIC INSULATION.....	67
Figure BB.9 – REINFORCED INSULATION, BASIC INSULATION and impedance	68
Figure BB.10 – REINFORCED INSULATION from external power supplies	69
Figure BB.11 – BASIC INSULATION from external power supplies	70
Figure EE.1 – Information and documentation for component products	76
Figure EE.2 – Information and documentation accumulation and segregation tree for an example installation	77
Figure FF.1 – Path of a component mounted to a PWB (side view)	79
Figure FF.2 – Path of a component mounted to a PWB (side view)	79
 Table 101 – INTERFACES, PORTS AND TERMINALS considered as OPERATOR ACCESSIBLE for OPEN and ENCLOSED EQUIPMENT	18
Table 3 – Multiplication factors for clearances of equipment rated for operation at altitudes up to 5 000 m	25
Table 4 – CLEARANCE and CREEPAGE DISTANCES for MAINS CIRCUITS of OVERVOLTAGE CATEGORY II up to 300 V.....	27
Table 5 – Test voltages for solid insulation between MAINS and between MAINS and secondary circuits OVERVOLTAGE CATEGORY II up to 300 V	28
Table 6 – CLEARANCES and test voltages for secondary circuits derived from MAINS CIRCUITS of OVERVOLTAGE CATEGORY II up to 300 V	29
Table 16 – Acceptable perforation of the bottom of an ENCLOSURE	36
Table 19 – Surface temperature limits, under NORMAL CONDITION.....	39
Table 102 – Overload and endurance test voltages.....	47
Table 103 – Overload test circuit values	49
Table 104 – Endurance test circuit values	50
Table E.1 – Environmental situations	52
Table E.2 – Reduction of POLLUTION DEGREES (PD)	53
Table CC.1 – Limits of output current and output power for inherently limited power sources.....	74
Table CC.2 – Limits of output current, output power and RATINGS for over-current protective devices for non-inherently limited power sources	74
Table FF.1 – Dimensions of X.....	78

INTERNATIONAL ELECTROTECHNICAL COMMISSION

SAFETY REQUIREMENTS FOR ELECTRICAL EQUIPMENT FOR MEASUREMENT, CONTROL, AND LABORATORY USE –

Part 2-201: Particular requirements for control equipment

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at <https://patents.iec.ch>. IEC shall not be held responsible for identifying any or all such patent rights.

IEC 61010-2-201 has been prepared by IEC technical committee 65: Industrial-process measurement, control and automation. It is an International Standard.

This third edition cancels and replaces the second edition published in 2017. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) 1.1.1: the related equipment included in the Scope has been clarified;
- b) 4.3.2.101: the optical fibre module has been deleted;
- c) 5.4.3: equipment installation has been clarified;

- d) 6.7.1.1: revision of the figure representing insulation between separate circuits has been included;
- e) 6.7.101: the subclause relating to insulation for FIELD WIRING TERMINALS of OVERVOLTAGE CATEGORY II with a nominal voltage up to 1 000 V has been deleted;
- f) 6.7.1.101: a new subclause relating to insulation for SELV/PELV CIRCUITS has been included;
- g) 6.8.3: specification of voltage tester has been added;
- h) 6.9.3: an additional exception relating to colour coding has been included;
- i) 6.9.101: a new subclause relating to wiring for secondary circuits e.g. SELV/PELV has been included;
- j) 8.2.2.101: additional requirements for glass displays have been included;
- k) 8.3: the subclause relating to the drop test has been removed;
- l) 9.3.2: additional requirements for material of connectors and insulating material have been included;
- m) The particular requirements for non-metallic material have been clarified;
- n) Clause 11: the particular requirements for protection against HAZARDS from fluid and solid foreign objects have been removed;
- o) 12.4: an additional subclause relating to microwave radiation has been included;
- p) 14.102: the description of switching devices has been clarified;

The text of this International Standard is based on the following documents:

Draft	Report on voting
65/1049/FDIS	65/1095/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

A list of all parts in the IEC 61010 series, published under the general title *Safety requirements for electrical equipment for measurement, control, and laboratory use*, can be found on the IEC website.

This document is to be used in conjunction with IEC 61010-1:2010, and IEC 61010-1:2010/AMD1:2016.

This document supplements or modifies the corresponding clauses in IEC 61010-1 so as to convert that publication into the IEC standard: *Particular requirements for control equipment*.

Where a particular subclause of IEC 61010-1 is not mentioned in this document, that subclause applies as far as is reasonable. Where this document states "addition", "modification", "replacement", or "deletion", the relevant requirement, test specification or note in IEC 61010-1 should be adapted accordingly.

In this document,

- a) the following print types are used:
 - requirements and definitions: in roman type;
 - NOTES: in smaller roman type;
 - *conformity and tests*: in italic type;
 - terms used throughout this document which have been defined in Clause 3: SMALL ROMAN CAPITALS.
- b) subclauses, figures, tables and notes which are additional to those in IEC 61010-1 are numbered starting from 101. Additional annexes are lettered starting from AA and additional list items are lettered from aa).

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

IMPORTANT – The "colour inside" logo on the cover page of this document indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

IEC 61010-2-2xx documents are a series of standards on the safety of industrial-process measurement, control and automation equipment.

This document specifies the complete safety related requirements and related tests for control equipment (e.g. programmable controller (PLC), the components of distributed control systems (DCS), I/O devices, human machine interface (HMI)).

Safety terms of general use are defined in IEC 61010-1. More specific terms are defined in each relevant part of the IEC 61010 series.

SAFETY REQUIREMENTS FOR ELECTRICAL EQUIPMENT FOR MEASUREMENT, CONTROL, AND LABORATORY USE –

Part 2-201: Particular requirements for control equipment

1 Scope and object

IEC 61010-1:2010, Clause 1 and IEC 61010-1:2010/AMD1:2016, Clause 1 apply, except as follows:

1.1.1 Equipment included in scope

Replacement:

Replace the existing text with the following:

This part of IEC 61010 specifies safety requirements and related verification tests for control equipment or their associated peripherals, or both.

Some equipment examples are:

- programmable logic controller (PLC);
- programmable automation controller (PAC);
- distributed control systems (DCS);
- industrial PC (computers) and panel PC;
- programming and debugging tools (PADTs);
- displays and human-machine interfaces (HMI);
- any product performing the function of control equipment or their associated peripherals, or both;
- positioners; and
- control equipment which have as their intended use the command and control of machines, automated manufacturing and industrial processes, for example discrete and continuous control.

Components of the above named equipment and within the scope of this document are, for example:

- (auxiliary) stand-alone power supplies;
- peripherals such as digital and analogue I/O,
- remote-I/O;
- industrial network equipment, embedded or stand-alone (e.g. switches, routers, wireless base station).

Control equipment and their associated peripherals are intended to be used in an industrial environment. This document considers equipment designed as OPEN or ENCLOSED EQUIPMENT.

NOTE 1 Control equipment intended also for use in other environments or for other purposes (example: for use in building installations to control light or other electrical installations, or for use on cars, trains or ships) can have additional conformity requirements defined by the safety standard(s) for these applications. These requirements can involve for example: insulation, spacings and power restrictions.

NOTE 2 Computing devices and similar equipment within the scope of the IEC 60950 series or the IEC 62368 series and conforming to their requirements are considered to be suitable for use with control equipment within the scope of this document. However, some of the requirements of the IEC 60950 series for resistance to moisture and liquids are less stringent, IEC 61010-1:2010, 5.4.4, second paragraph takes this aspect into account.

Control equipment covered in this document is typically intended for use in OVERVOLTAGE CATEGORY II (IEC 60664-1) in low-voltage installations, where the RATED equipment supply voltage does not exceed 1 000 V a.c. RMS (50/60 Hz), or 1 000 V d.c..

Where control equipment is intended for installation to supply systems with OVERVOLTAGE CATEGORY III or IV, additional requirements are identified in Annex K.

The requirements of ISO/IEC Guide 51 and IEC Guide 104, as they relate to this part of IEC 61010, are incorporated herein.

1.1.2 Equipment excluded from scope

Replacement:

Replace the existing text with the following:

This document does not deal with aspects of the overall automated system, for example a complete assembly line. Control equipment (e.g. DCS and PLC), their application programme and their associated peripherals are considered as components (components in this context are items which perform no useful function by themselves) of an overall automated system.

Since control equipment (e.g. DCS and PLC) are component devices, safety considerations for the overall automated system including installation and application are beyond the scope of this document. Refer to the IEC 60364 series or applicable national and local regulations for electrical installation and guidelines.

1.2.1 Aspects included in scope

Replace the first sentence with the following:

The purpose of the requirements of this document is to ensure that all HAZARDS to the OPERATOR, SERVICE PERSONNEL and the surrounding area are reduced to a tolerable level.

NOTE By using the terms "OPERATOR" and "SERVICE PERSONNEL" this document considers the perception of HAZARDS depending on training and skills. Annex AA provides a general approach in this regard.

1.2.2 Aspects excluded from scope

Replacement:

Replace the existing text with the following:

This document does not cover:

- a) reliability, functionality, performance, or other properties of the control equipment not related to safety;
- b) mechanical or climatic requirements for operation, transport or storage;
- c) EMC requirements (see e.g. the IEC 61326 series or IEC 61131-2);
- d) protective measures for explosive atmospheres (see e.g. the IEC 60079 series);
- e) functional safety (see e.g. the IEC 61508 series, IEC 61131-6).

2 Normative references

IEC 61010-1:2010, Clause 2 and IEC 61010-1:2010/AMD1:2016, Clause 2 apply, except as follows:

Addition:

Add the following new references:

IEC 60384-14, *Fixed capacitors for use in electronic equipment – Part 14: Sectional specification – Fixed capacitors for electromagnetic interference suppression and connection to the supply mains*

IEC 60695-2-11, *Fire hazard testing – Part 2-11: Glowing/hot-wire based test methods – Glow-wire flammability test method for end products (GWEPT)*

IEC 60695-11-3, *Fire hazard testing – Part 11-3: Test flames – 500 W flames – Apparatus and confirmational test methods*

IEC 60695-11-20, *Fire hazard testing – Part 11-20: Test flames – 500 W flame test method*

IEC 60947-4-1, *Low-voltage switchgear and controlgear – Part 4-1: Contactors and motor-starters – Electromechanical contactors and motor-starters*

IEC 60947-4-2, *Low-voltage switchgear and controlgear – Part 4-2: Contactors and motor-starters – Semiconductor motor controllers, starters and soft-starters*

IEC 60947-5-1:2016, *Low-voltage switchgear and controlgear – Part 5-1: Control circuit devices and switching elements – Electromechanical control circuit devices*

IEC 61010-1:2010, *Safety requirements for electrical equipment for measurement, control, and laboratory use – Part 1: General requirements*

IEC 61010-1:2010/AMD1:2016

IEC 61010-2-030, *Safety requirements for electrical equipment for measurement, control, and laboratory use – Part 2-030: Particular requirements for equipment having testing or measuring circuits*

IEC 61810-1:2015, *Electromechanical elementary relays – Part 1: General and safety requirements*

SOMMAIRE

AVANT-PROPOS	85
INTRODUCTION	88
1 Domaine d'application et objet	89
2 Références normatives	91
3 Termes et définitions	92
4 Essais	95
5 Marquage et documentation	96
6 Protection contre les chocs électriques	98
7 Protection contre les DANGERS mécaniques	114
8 Résistance aux contraintes mécaniques	115
9 Protection contre la propagation du feu	117
10 Limites de température de l'appareil et résistance à la chaleur	122
11 Protection contre les DANGERS des fluides et des corps solides étrangers	128
12 Protection contre les radiations, y compris les sources laser, et contre la pression acoustique et ultrasonique	128
13 Protection contre les émissions de gaz et substances, les explosions et les implosions	129
14 Composants et sous-ensembles	129
15 Protection par systèmes de verrouillage	133
16 DANGERS résultant de l'application	133
17 Appréciation du RISQUE	134
Annexes	135
Annexe E (informative) Lignes directrices pour la réduction des DEGRES DE POLLUTION	136
Annexe F (normative) ESSAIS INDIVIDUELS DE SERIE	138
Annexe L (informative) Index des termes définis	140
Annexe AA (informative) Approche générale des questions de sécurité relative aux équipements de commande	141
Annexe BB (informative) Dessin applicable aux limites d'isolation	144
Annexe CC (informative) Techniques traditionnelles utilisées pour les circuits secondaires	155
Annexe DD (normative) Essai d'inflammabilité des ENVELOPPES ignifuges ou des barrières coupe-flammes constituées d'un alliage de magnésium (voir le 9.3.2)	159
Annexe EE (informative) Informations, documentation et corrélation avec leurs utilisations	160
Annexe FF (informative) Mesurage des DISTANCES D'ISOLEMENT et des LIGNES DE FUITE	162
Bibliographie	164
 Figure 101 – INTERFACES/ACCES types des équipements de commande	101
Figure 102 – Exemples d'isolation entre des circuits séparés et entre les circuits et des parties conductrices ACCESSIBLES	107
Figure 103 – Exigences relatives aux DANGERS mécaniques pour les EQUIPEMENTS MONTES SUR PANNEAU	114
Figure 104 – DANGERS relatifs à la propagation du feu pour les EQUIPEMENTS MONTES SUR PANNEAU	118

Figure 12 – Chicane.....	120
Figure 13 – Emplacement du fond d'une ENVELOPPE à construire comme cela est spécifié en 9.3.2 c) 1)	121
Figure 105 – Environnement d'essai de température général	124
Figure 106 – Équipement ventilé.....	125
Figure 107 – Équipement non ventilé	126
Figure 108 – ÉQUIPEMENT MONTE SUR PANNEAU qui s'étend sur la paroi d'une l'ENVELOPPE de l'emplacement final.....	127
Figure AA.1 – Accès aux équipements de commande et sécurité connexe.....	141
Figure BB.1 – Disposition type d'une ENVELOPPE de système	145
Figure BB.2 – Schéma simplifié du système.....	146
Figure BB.3 – Situation de DANGER pour l'équipement de commande	147
Figure BB.4 – Application de l'IEC 61010-2-201 au dessin sur la sécurité des équipements de commande	148
Figure BB.5 – Application des points a) et b) du 6.7.1.5 au dessin sur la sécurité des équipements de commande	149
Figure BB.6 – Application des points a), b), c) et d) du 6.7.1.5 au dessin sur la sécurité des équipements de commande.....	149
Figure BB.7 – ISOLATION RENFORCEE	150
Figure BB.8 – ISOLATION PRINCIPALE	151
Figure BB.9 – ISOLATION RENFORCEE, ISOLATION PRINCIPALE et impédance.....	152
Figure BB.10 – ISOLATION RENFORCEE assurée par les alimentations externes	153
Figure BB.11 – ISOLATION PRINCIPALE assurée par les alimentations externes.....	154
Figure EE.1 – Informations et documentation sur les composants	160
Figure EE.2 – Arbre de compilation et de répartition des informations et de la documentation pour un exemple d'installation	161
Figure FF.1 – Chemin d'un composant monté sur une CCI (vue latérale)	163
Figure FF.2 – Chemin d'un composant monté sur une CCI (vue latérale)	163
 Tableau 101 – INTERFACES, ACCES ET BORNES considérés comme ACCESSIBLES PAR L'OPERATEUR pour les EQUIPEMENTS OUVERTS et les EQUIPEMENTS SOUS ENVELOPPE	100
Tableau 3 – Facteurs de multiplication des distances d'isolement des équipements assignés pour un fonctionnement à des altitudes inférieures ou égales à 5 000 m	108
Tableau 4 – DISTANCES D'ISOLEMENT et LIGNES DE FUITE des CIRCUITS RESEAU de CATEGORIE DE SURTENSION II avec une tension maximale de 300 V	110
Tableau 5 – Tensions d'essai de l'isolation solide entre le RESEAU D'ALIMENTATION et entre les circuits RESEAU et secondaires de CATEGORIE DE SURTENSION II avec une tension maximale de 300 V	111
Tableau 6 – DISTANCES D'ISOLEMENT et tensions d'essai des circuits secondaires obtenus à partir des CIRCUITS RESEAU de CATEGORIE DE SURTENSION II avec une tension maximale de 300 V	112
Tableau 16 – Perforation acceptable du fond d'une ENVELOPPE	120
Tableau 19 – Limites de température des surfaces en CONDITION NORMALE	122
Tableau 102 – Tensions des essais de surcharge et d'endurance	130
Tableau 103 – Valeurs du circuit d'essai de surcharge.....	132
Tableau 104 – Valeurs du circuit d'essai d'endurance	133
Tableau E.1 – Situations environnementales.....	136

Tableau E.2 – Réduction des DEGRES DE POLLUTION (PD)	137
Tableau CC.1 – Limites de courant et de puissance de sortie relatives aux sources de puissance intrinsèquement limitée	158
Tableau CC.2 – Limites de courant de sortie, de puissance de sortie et de CARACTERISTIQUES ASSIGNEES relatives aux appareils de protection contre les surintensités pour les sources de puissance non intrinsèquement limitée	158
Tableau FF.1 – Dimensions X	162

COMMISSION ÉLECTROTECHNIQUE INTERNATIONALE

EXIGENCES DE SÉCURITÉ POUR APPAREILS ÉLECTRIQUES DE MESURAGE, DE RÉGULATION ET DE LABORATOIRE –

Partie 2-201: Exigences particulières pour les équipements de commande

AVANT-PROPOS

- 1) La Commission Électrotechnique Internationale (IEC) est une organisation mondiale de normalisation composée de l'ensemble des comités électrotechniques nationaux (Comités nationaux de l'IEC). L'IEC a pour objet de favoriser la coopération internationale pour toutes les questions de normalisation dans les domaines de l'électricité et de l'électronique. À cet effet, l'IEC – entre autres activités – publie des Normes internationales, des Spécifications techniques, des Rapports techniques, des Spécifications accessibles au public (PAS) et des Guides (ci-après dénommés "Publication(s) de l'IEC"). Leur élaboration est confiée à des comités d'études, aux travaux desquels tout Comité national intéressé par le sujet traité peut participer. Les organisations internationales, gouvernementales et non gouvernementales, en liaison avec l'IEC, participent également aux travaux. L'IEC collabore étroitement avec l'Organisation Internationale de Normalisation (ISO), selon des conditions fixées par accord entre les deux organisations.
- 2) Les décisions ou accords officiels de l'IEC concernant les questions techniques représentent, dans la mesure du possible, un accord international sur les sujets étudiés, étant donné que les Comités nationaux de l'IEC intéressés sont représentés dans chaque comité d'études.
- 3) Les Publications de l'IEC se présentent sous la forme de recommandations internationales et sont agréées comme telles par les Comités nationaux de l'IEC. Tous les efforts raisonnables sont entrepris afin que l'IEC s'assure de l'exactitude du contenu technique de ses publications; l'IEC ne peut pas être tenue responsable de l'éventuelle mauvaise utilisation ou interprétation qui en est faite par un quelconque utilisateur final.
- 4) Dans le but d'encourager l'uniformité internationale, les Comités nationaux de l'IEC s'engagent, dans toute la mesure possible, à appliquer de façon transparente les Publications de l'IEC dans leurs publications nationales et régionales. Toutes divergences entre toutes Publications de l'IEC et toutes publications nationales ou régionales correspondantes doivent être indiquées en termes clairs dans ces dernières.
- 5) L'IEC elle-même ne fournit aucune attestation de conformité. Des organismes de certification indépendants fournissent des services d'évaluation de conformité et, dans certains secteurs, accèdent aux marques de conformité de l'IEC. L'IEC n'est responsable d'aucun des services effectués par les organismes de certification indépendants.
- 6) Tous les utilisateurs doivent s'assurer qu'ils sont en possession de la dernière édition de cette publication.
- 7) Aucune responsabilité ne doit être imputée à l'IEC, à ses administrateurs, employés, auxiliaires ou mandataires, y compris ses experts particuliers et les membres de ses comités d'études et des Comités nationaux de l'IEC, pour tout préjudice causé en cas de dommages corporels et matériels, ou de tout autre dommage de quelque nature que ce soit, directe ou indirecte, ou pour supporter les coûts (y compris les frais de justice) et les dépenses découlant de la publication ou de l'utilisation de cette Publication de l'IEC ou de toute autre Publication de l'IEC, ou au crédit qui lui est accordé.
- 8) L'attention est attirée sur les références normatives citées dans cette publication. L'utilisation de publications référencées est obligatoire pour une application correcte de la présente publication.
- 9) L'IEC attire l'attention sur le fait que la mise en application du présent document peut entraîner l'utilisation d'un ou de plusieurs brevets. L'IEC ne prend pas position quant à la preuve, à la validité et à l'applicabilité de tout droit de brevet revendiqué à cet égard. À la date de publication du présent document, l'IEC n'avait pas reçu notification qu'un ou plusieurs brevets pouvaient être nécessaires à sa mise en application. Toutefois, il y a lieu d'avertir les responsables de la mise en application du présent document que des informations plus récentes sont susceptibles de figurer dans la base de données de brevets, disponible à l'adresse <https://patents.iec.ch>. L'IEC ne saurait être tenue pour responsable de ne pas avoir identifié tout ou partie de tels droits de brevet.

L'IEC 61010-2-201 a été établie par le comité d'études 65 de l'IEC: Mesure, commande et automation dans les processus industriels. Il s'agit d'une Norme internationale.

Cette troisième édition annule et remplace la deuxième édition parue en 2017. Cette édition constitue une révision technique.

Cette édition inclut les modifications techniques majeures suivantes par rapport à l'édition précédente:

- a) 1.1.1: clarification concernant les équipements inclus dans le domaine d'application;
- b) 4.3.2.101: suppression du module à fibre optique;
- c) 5.4.3: clarification de l'installation de l'équipement;
- d) 6.7.1.1: révision de la figure représentant l'isolation entre des circuits séparés;
- e) 6.7.101: suppression du paragraphe concernant l'isolation des BORNES A CABLER SUR PLACE de CATEGORIE DE SURTENSION II avec une tension nominale maximale de 1 000 V;
- f) 6.7.1.101: ajout d'un nouveau paragraphe concernant l'isolation des CIRCUITS TBTS/TBTP;
- g) 6.8.3: ajout d'une spécification pour le contrôleur de tension;
- h) 6.9.3: ajout d'une exception supplémentaire pour le codage des couleurs;
- i) 6.9.101: ajout d'un nouveau paragraphe concernant le câblage des circuits secondaires, par exemple TBTS/TBTP;
- j) 8.2.2.101: ajout d'exigences supplémentaires pour les écrans en verre;
- k) 8.3: suppression du paragraphe concernant l'essai de chute;
- l) 9.3.2: ajout d'exigences supplémentaires pour les matériaux des connecteurs et les matériaux isolants;
- m) clarification des exigences particulières relatives aux matériaux non métalliques;
- n) Article 11: suppression des exigences particulières concernant la protection contre les DANGERS des fluides et des corps solides étrangers;
- o) 12.4: ajout d'un paragraphe supplémentaire concernant le rayonnement hyperfréquence;
- p) 14.102: clarification concernant la description des appareils de commutation.

Le texte de cette Norme internationale est issu des documents suivants:

Projet	Rapport de vote
65/1049/FDIS	65/1095/RVD

Le rapport de vote indiqué dans le tableau ci-dessus donne toute information sur le vote ayant abouti à son approbation.

La langue employée pour l'élaboration de cette Norme internationale est l'anglais.

La version française de la norme n'a pas été soumise au vote.

Ce document a été rédigé selon les Directives ISO/IEC, Partie 2, il a été développé selon les Directives ISO/IEC, Partie 1 et les Directives ISO/IEC, Supplément IEC, disponibles sous www.iec.ch/members_experts/refdocs. Les principaux types de documents développés par l'IEC sont décrits plus en détail sous www.iec.ch/standardsdev/publications.

Une liste de toutes les parties de la série IEC 61010, publiées sous le titre général *Exigences de sécurité pour appareils électriques de mesurage, de régulation et de laboratoire*, se trouve sur le site web de l'IEC.

Le présent document doit être utilisé conjointement avec l'IEC 61010-1:2010 et l'IEC 61010-1:2010/AMD1:2016.

Le présent document complète ou modifie les articles correspondants de l'IEC 61010-1, de façon à transformer cette publication en norme IEC: *Exigences particulières pour les équipements de commande*.

Lorsqu'un paragraphe particulier de l'IEC 61010-1 n'est pas mentionné dans le présent document, ce paragraphe s'applique pour autant que cela soit raisonnable. Lorsque le présent document mentionne "addition", "modification", "remplacement" ou "suppression", il convient d'adapter l'exigence, la spécification d'essai ou la note correspondante de l'IEC 61010-1 en conséquence.

Dans le présent document,

- a) les caractères d'imprimerie suivants sont utilisés:
 - exigences et définitions: caractères romains;
 - NOTES: petits caractères romains;
 - *conformité et essais: caractères italiques*;
 - termes utilisés dans l'ensemble du présent document qui ont été définis à l'Article 3: PETITES MAJUSCULES EN CARACTÈRES ROMAINS.
- b) les paragraphes, figures, tableaux et notes qui s'ajoutent à ceux de l'IEC 61010-1 sont numérotés à partir de 101. Les annexes qui sont ajoutées sont désignées AA et les éléments de liste supplémentaires sont désignés aa).

Le comité a décidé que le contenu de ce document ne sera pas modifié avant la date de stabilité indiquée sur le site web de l'IEC sous webstore.iec.ch dans les données relatives au document recherché. À cette date, le document sera

- reconduit,
- supprimé, ou
- révisé.

IMPORTANT – Le logo "colour inside" qui se trouve sur la page de couverture de ce document indique qu'il contient des couleurs qui sont considérées comme utiles à une bonne compréhension de son contenu. Les utilisateurs devraient, par conséquent, imprimer ce document en utilisant une imprimante couleur.

INTRODUCTION

Les documents IEC 61010-2-2xx composent une série de normes relatives à la sécurité des appareils de mesure, de régulation et d'automatisation des processus industriels.

Le présent document spécifie l'ensemble des exigences et essais de sécurité relatifs aux équipements de commande (par exemple, automates programmables [PLC]), aux composants des systèmes à commande répartie (DCS), aux appareils d'E/S et à l'interface homme/machine (IHM).

Les termes de sécurité génériques sont définis dans l'IEC 61010-1. Les termes plus spécifiques sont définis dans chaque partie pertinente de la série IEC 61010.

EXIGENCES DE SÉCURITÉ POUR APPAREILS ÉLECTRIQUES DE MESURAGE, DE RÉGULATION ET DE LABORATOIRE –

Partie 2-201: Exigences particulières pour les équipements de commande

1 Domaine d'application et objet

L'Article 1 de l'IEC 61010-1:2010 et l'Article 1 de l'IEC 61010-1:2010/AMD1:2016 s'appliquent, avec les exceptions suivantes:

1.1.1 Appareils inclus dans le domaine d'application

Remplacement:

Remplacer le texte existant par ce qui suit:

La présente partie de l'IEC 61010 spécifie les exigences de sécurité et les essais de vérification associés pour les équipements de commande ou leurs périphériques associés, ou les deux.

Les équipements suivants en sont des exemples:

- les automates programmables (PLC, *Programmable Logic Controller*);
- les contrôleurs d'automatisation programmables (PAC, *Programmable Automation Controller*);
- les systèmes à commande répartie (DCS, *Distributed Control Systems*);
- les ordinateurs (PC) industriels et combinés PC-écran;
- les outils de programmation et de débogage (PADT, *Programming and Debugging Tools*);
- les affichages et les interfaces homme/machine (IHM);
- tout produit remplissant la fonction d'équipement de commande ou ses périphériques associés, ou les deux;
- les positionneurs; et
- les équipements de commande dont l'utilisation prévue consiste à contrôler et commander les machines, les processus industriels et de fabrication automatisés, par exemple par le biais d'un contrôle discret et continu.

Les composants des équipements susmentionnés et inclus dans le domaine d'application du présent document sont, par exemple:

- les alimentations autonomes (auxiliaires);
- les périphériques tels que les E/S numériques et analogiques;
- les E/S à distance;
- les équipements de réseau industriels, intégrés ou autonomes (par exemple, commutateurs, routeurs, stations de base sans fil).

Les équipements de commande et leurs périphériques associés sont conçus pour être utilisés dans un environnement industriel. Le présent document concerne les équipements conçus comme des EQUIPEMENTS OUVERTS ou des EQUIPEMENTS SOUS ENVELOPPE.

NOTE 1 Les équipements de commande également conçus pour être utilisés dans d'autres environnements ou à d'autres fins (par exemple, au sein de bâtiments pour commander l'éclairage ou d'autres installations électriques ou à bord de voitures, trains ou bateaux) peuvent faire l'objet d'exigences de conformité supplémentaires définies par la ou les normes de sécurité applicables à ces applications. Ces exigences peuvent concerner, par exemple, l'isolation, les espacements et les restrictions de puissance.

NOTE 2 Les calculateurs et équipements analogues inclus dans le domaine d'application de la série IEC 60950 ou de la série IEC 62368 et conformes à leurs exigences sont réputés être adaptés à une utilisation avec les équipements de commande inclus dans le domaine d'application du présent document. Cependant, certaines des exigences de la série IEC 60950 relative à la tenue à l'humidité et aux liquides sont moins strictes, le deuxième alinéa du 5.4.4 de l'IEC 61010-1:2010 tient compte de cet aspect.

Les équipements de commande couverts par le présent document sont généralement destinés à être utilisés dans des installations à basse tension de CATEGORIE DE SURTENSION II (IEC 60664-1), où la tension d'alimentation ASSIGNEE des équipements ne dépasse pas 1 000 V (valeur efficace) en courant alternatif (50/60 Hz) ou 1 000 V en courant continu.

Pour les équipements de commande destinés à être installés pour alimenter des systèmes de CATEGORIE DE SURTENSION III ou IV, des exigences supplémentaires sont indiquées à l'Annexe K.

Les exigences du Guide ISO/IEC 51 et du Guide IEC 104, en rapport avec la présente partie de l'IEC 61010, sont intégrées au présent document.

1.1.2 Appareils exclus du domaine d'application

Remplacement:

Remplacer le texte existant par ce qui suit:

Le présent document ne traite pas des aspects du système automatisé global, par exemple une chaîne de montage complète. Les équipements de commande (par exemple, DCS et PLC), leurs programmes d'application et leurs périphériques associés sont considérés comme des composants (les composants dans ce contexte sont des éléments qui n'accomplissent aucune fonction utile) d'un système automatisé global.

Étant donné que les équipements de commande (par exemple, DCS et PLC) sont des appareils de type composants, les considérations relatives à la sécurité du système automatisé global qui portent sur l'installation et l'application ne relèvent pas du domaine d'application du présent document. Se reporter à la série IEC 60364 ou aux réglementations nationales et locales applicables pour l'installation électrique et les lignes directrices.

1.2.1 Aspects inclus dans le domaine d'application

Remplacer la première phrase par ce qui suit:

L'objet des exigences du présent document est de s'assurer que tous les DANGERS pour l'OPÉRATEUR, le PERSONNEL D'ENTRETIEN et la zone environnante sont réduits à un niveau acceptable.

NOTE En utilisant les termes "OPÉRATEUR" et "PERSONNEL D'ENTRETIEN", le présent document prend en compte la perception des DANGERS en fonction de la formation et des compétences. Le Annexe AA fournit une approche générale à cet égard.

1.2.2 Aspects exclus du domaine d'application

Remplacement:

Remplacer le texte existant par ce qui suit:

Le présent document ne couvre pas:

- a) la fiabilité, les fonctionnalités, les performances, ni les autres propriétés de l'équipement de commande qui ne sont pas liées à la sécurité;
- b) les exigences mécaniques ou climatiques relatives à l'exploitation, au transport ou à l'entreposage;
- c) les exigences relatives à la CEM (par exemple, la série IEC 61326 ou l'IEC 61131-2);
- d) les mesures de protection relatives aux atmosphères explosives (par exemple, la série IEC 60079);
- e) la sécurité fonctionnelle (par exemple, la série IEC 61508 ou l'IEC 61131-6).

2 Références normatives

L'Article 2 de l'IEC 61010-1:2010 et l'Article 2 de l'IEC 61010-1:2010/AMD1:2016 s'appliquent, avec les exceptions suivantes:

Addition:

Ajouter les nouvelles références suivantes:

IEC 60384-14, *Condensateurs fixes utilisés dans les équipements électroniques – Partie 14: Spécification intermédiaire – Condensateurs fixes pour la suppression des interférences électromagnétiques et la connexion au réseau d'alimentation*

IEC 60695-2-11, *Essais relatifs aux risques du feu – Partie 2-11: Essais au fil incandescent/chauffant – Méthode d'essai d'inflammabilité pour produits finis (GWEPT)*

IEC 60695-11-3, *Essais relatifs aux risques du feu – Partie 11-3: Flammes d'essai – Flamme de 500 W – Appareillage et méthodes d'essai de vérification*

IEC 60695-11-20, *Essais relatifs aux risques du feu – Partie 11-20: Flammes d'essai – Méthode d'essai à la flamme de 500 W*

IEC 60947-4-1, *Appareillage à basse tension – Partie 4-1: Contacteurs et démarreurs de moteurs – Contacteurs et démarreurs électromécaniques*

IEC 60947-4-2, *Appareillage à basse tension – Partie 4-2: Contacteurs et démarreurs de moteurs – Gradateurs, démarreurs et démarreurs progressifs à semiconducteurs de moteurs*

IEC 60947-5-1:2016, *Appareillage à basse tension – Partie 5-1: Appareils et éléments de commutation pour circuits de commande – Appareils électromécaniques pour circuits de commande*

IEC 61010-1:2010, *Règles de sécurité pour appareils électriques de mesurage, de régulation et de laboratoire – Partie 1: Exigences générales*
IEC 61010-1:2010/AMD1:2016

IEC 61010-2-030, *Exigences de sécurité pour appareils électriques de mesurage, de régulation et de laboratoire – Partie 2-030: Exigences particulières pour les appareils équipés de circuits d'essai ou de mesure*

IEC 61810-1:2015, *Relais électromécaniques élémentaires – Partie 1: Exigences générales et de sécurité*